

MAMBASNAKE G3PRO

MAMBASNAKE ATTACK SHARK G3PRO Wireless Gaming Mouse User Manual

Model: G3PRO

1. INTRODUCTION

Thank you for choosing the MAMBASNAKE ATTACK SHARK G3PRO Wireless Gaming Mouse. This high-performance mouse is designed for precision and versatility, featuring tri-mode connectivity, a high-accuracy optical sensor, an ultra-lightweight design, and a convenient RGB magnetic charging dock. This manual provides detailed instructions for setup, operation, maintenance, and troubleshooting to ensure optimal performance.

2. PACKAGE CONTENTS

Please verify that all items are present in your package:

- MAMBASNAKE ATTACK SHARK G3PRO Gaming Mouse
- RGB Magnetic Charging Dock
- USB-C Cable
- USB Receiver (2.4G)
- Non-Slip Grip Tape
- Instruction Manual (this document)

3. PRODUCT OVERVIEW

Familiarize yourself with the components of your G3PRO mouse and charging dock:



Image: Labeled diagram of the G3PRO mouse and charging dock.

1. **Left Button:** Primary click function.
2. **Right Button:** Secondary click function.
3. **Scroll Wheel:** For scrolling and middle-click.
4. **Forward Button:** Navigational button (default: forward).
5. **Backward Button:** Navigational button (default: backward).
6. **DPI Cycle Button:** Cycles through DPI settings.
7. **DPI Indicator Light:** Shows current DPI level.
8. **2.4G/OFF/BT Switch:** Selects connection mode or powers off the mouse.
9. **Charging Thimble:** Connects to the charging dock.
10. **USB Receiver Slot:** Stores the 2.4G USB receiver.
11. **USB Interface (on dock):** For connecting the USB-C cable.
12. **Charging Cable:** USB-C to USB-A cable for power and wired connection.
13. **Double-layer Floor Mats:** For smooth gliding.

4. SETUP

4.1 Initial Charging

Before first use, it is recommended to fully charge the mouse. Connect the USB-C cable to the charging dock and then to a power source (e.g., computer USB port or USB wall adapter). Place the mouse onto the magnetic charging dock. The dock's RGB lighting will indicate charging status.



Image: The G3PRO mouse magnetically attached to its RGB charging dock.

4.2 Connecting the Mouse

The G3PRO mouse supports three connection modes: 2.4GHz Wireless, Bluetooth, and Wired USB-C.

4.2.1 2.4GHz Wireless Mode

1. Remove the USB receiver from its storage slot on the bottom of the mouse.
2. Plug the USB receiver into an available USB port on your computer.
3. Slide the switch on the bottom of the mouse to the "2.4G" position.
4. The mouse should connect automatically. If not, press the DPI button briefly to wake it up.

4.2.2 Bluetooth Mode

1. Slide the switch on the bottom of the mouse to the "BT" position.
2. On your computer or device, open Bluetooth settings and search for new devices.
3. Select "ATTACK SHARK G3PRO" from the list of available devices to pair.
4. The mouse's indicator light will confirm successful pairing.

4.2.3 Wired USB-C Mode

1. Connect the USB-C cable directly from the mouse to your computer's USB port.
2. Slide the switch on the bottom of the mouse to the "OFF" position. The mouse will operate in wired mode and charge simultaneously.

5. OPERATING INSTRUCTIONS

5.1 DPI Adjustment

The G3PRO mouse features a PixArt 3311 optical sensor with up to 25,000 DPI. You can cycle through 6 adjustable DPI levels using the DPI Cycle Button located on the bottom of the mouse. Each DPI level is indicated by a specific color on the DPI indicator light.

25,000 DPI OPTICAL SENSOR FOR GAMING PRECISION

Provides fast and precise mouse swipes with 400IPS and 40G acceleration, programmed to achieve up to 50 degrees of accuracy.



Image: Visual representation of DPI levels and their impact on mouse movement sensitivity.

5.2 RGB Lighting on Charging Dock

The RGB Magnetic Charging Dock features a touch-sensitive switch. Lightly tap this switch to toggle between different RGB lighting effects. This allows for personalization of your setup.

6. CUSTOMIZATION (SOFTWARE)

For advanced customization of DPI settings, button assignments, macro management, and polling rate, download the official software. The software allows you to create and save custom profiles for different applications or games.



Image: Software interface for customizing mouse settings.

Driver Download: bit.ly/G3SOFT

HUB WEB: szslxd-tech.com/#/

7. MAINTENANCE

7.1 Cleaning

To maintain optimal performance, regularly clean your mouse. Use a soft, dry cloth to wipe the surface. For stubborn dirt, a slightly damp cloth can be used, ensuring no moisture enters the internal components. Avoid harsh chemicals or abrasive materials.

7.2 Battery Care

The G3PRO mouse has a built-in rechargeable battery. To prolong battery life:

- Avoid fully discharging the battery frequently.
- Store the mouse in a cool, dry place when not in use for extended periods.
- Use the provided charging dock or USB-C cable for charging.

8. TROUBLESHOOTING

Problem	Possible Cause	Solution
Mouse not responding	Low battery; Incorrect connection mode; USB receiver issue; Bluetooth pairing issue.	Charge the mouse; Ensure the mode switch (2.4G/OFF/BT) is in the correct position; Re-plug the USB receiver; Re-pair Bluetooth.
DPI not changing	DPI button not pressed correctly; Software conflict.	Ensure a firm press on the DPI button; Check software settings if installed.
Charging dock RGB not working	Dock not powered; Touch switch not activated.	Ensure USB-C cable is connected and powered; Lightly tap the touch-sensitive switch on the dock.
Lag or disconnections in wireless mode	Interference; Distance from receiver; Low battery.	Move closer to the receiver; Ensure no strong interference sources nearby; Charge the mouse.

9. SPECIFICATIONS

- **Model:** G3PRO
- **Connectivity:** Tri-Mode (2.4GHz Wireless, Bluetooth, USB-C Wired)
- **Sensor:** PixArt 3311 Optical Sensor
- **DPI:** Up to 25,000 DPI (6 adjustable levels)
- **Polling Rate:** Up to 1000Hz
- **Switches:** Omron Micro Switches (100 Million Clicks lifespan)
- **Weight:** Approximately 62g
- **Charging:** RGB Magnetic Charging Dock, USB-C
- **Special Features:** Ergonomic Design, Programmable Buttons, Ultra-Lightweight
- **Compatible OS:** Windows 7/8/10/11/XP, Mac OS, Android, Linux

10. PRODUCT VIDEO GUIDE

Watch the official product video for a visual guide on the G3PRO mouse features and functionality:

Your browser does not support the video tag.

Video: An overview of the ATTACK SHARK G3PRO Gaming Mouse, demonstrating its magnetic charging, tri-mode connectivity, DPI adjustment, and customizable features.

11. WARRANTY AND SUPPORT

11.1 Warranty Information

MAMBASNAKE products are covered by a manufacturer's warranty. Please refer to the warranty card included in your package or visit the official MAMBASNAKE website for detailed warranty terms and conditions.

11.2 Customer Support

If you encounter any issues or have questions regarding your G3PRO mouse, please contact MAMBASNAKE customer support through the official website or the contact information provided in your warranty documentation. Our support team is available to assist you.