

ORGBRO Z3

ORGBRO Z3 Label Maker Machine User Manual

Model: Z3

INTRODUCTION

Thank you for choosing the ORGBRO Z3 Label Maker Machine. This portable thermal label printer is designed for versatile use in home organization, small businesses, offices, and schools. It offers high-quality, ink-free printing and is compatible with various devices. This manual provides detailed instructions to help you set up, operate, and maintain your device for optimal performance.

WHAT'S IN THE BOX

- 1x ORGBRO Z3 Label Maker Machine
- 1x Type-C Charging Cable
- 1x Roll of 50x30mm White Labels (230 Pcs)
- 1x User Manual
- 1x Drive USB

SETUP GUIDE

1. Charging the Device

Before first use, fully charge the ORGBRO Z3 Label Maker. Connect the provided Type-C charging cable to the device's charging port and a suitable USB power adapter. The LED screen will indicate charging status. A full charge provides approximately 4 weeks of runtime.

Portable Label Maker

Conveniently for Business/Home/Office

2200 mAh
Built-in rechargeable battery



Image: The ORGBRO Z3 Label Maker showing its charging port and indicating a 2200mAh built-in rechargeable battery, emphasizing its portability.

2. Loading Label Paper

1. Open the label compartment cover.
2. Insert the label roll with the printing surface facing up, ensuring it aligns correctly with the paper guides.
3. Close the cover firmly. The printer supports label widths from 0.8 to 3.15 inches.

Print **0.78"-3.15"** Wide Label Paper

Various Style Labels



Image: A visual guide demonstrating the correct method for loading label paper into the ORGBRO Z3, highlighting its compatibility with 0.78-3.15 inch wide labels.

3. Connecting to Devices

The ORGBRO Z3 supports connection via Bluetooth for mobile devices (Android/iOS) and USB for computers (Windows/Mac/Chrome OS/Linux).

Bluetooth Connection (Mobile Devices)

1. Download the free "4BarCode" app from your device's app store (Google Play for Android, App Store for iOS).
2. Ensure Bluetooth is enabled on your mobile device.
3. Open the "4BarCode" app. **Do not connect directly via phone's Bluetooth settings.** Connect through the app.
4. Within the app, search for and select your ORGBRO Z3 device to pair. The LED screen will show Bluetooth status.

USB Connection (Computers)

1. Connect the ORGBRO Z3 to your computer using the provided USB cable.
2. Install the necessary drivers from the included Drive USB or download them from the official ORGBRO website.
3. Once drivers are installed, the printer will be recognized by your computer's operating system.



Image: The ORGBRO Z3 Label Maker demonstrating its connectivity options, supporting both Bluetooth for phones (iOS, Android) and USB for computers (Apple, Windows, Chrome OS, Linux).

OPERATING INSTRUCTIONS

1. Using the "4BarCode" App

The "4BarCode" app is your primary interface for creating and printing labels. It offers extensive customization options:

- **Templates:** Access over 150 pre-designed templates for various uses.
- **Fonts & Frames:** Choose from 80+ fonts and 150+ frames to personalize your labels.

- **Icons & Images:** Utilize 670+ built-in icons or import images directly from your mobile device.
- **Content Types:** Easily add text, barcodes, QR codes, shapes, and lines.

Multiple Labels and Templates for Choosing in APP



Image: The "4BarCode" app interface, showcasing its rich features including over 150 templates, 80+ fonts, and 670+ icons for comprehensive label design.

2. Creating and Printing Labels

1. Open the "4BarCode" app and ensure your ORGBRO Z3 is connected.
2. Select "New Label" or choose an existing template.
3. Customize your label by adding text, barcodes, QR codes, images, and other elements. Adjust size, font, and position as needed.
4. Preview your label to ensure it appears as desired.
5. Tap the "Print" button. The printer will begin printing at speeds up to 50mm/s with a crisp 203dpi resolution.



Image: The ORGBRO Z3 in action, demonstrating its capability for fast and clear printing, producing up to 52 labels per minute at a resolution of 203 DPI.



Image: The ORGBRO Z3 Label Maker showcasing its versatility with examples of different label types it can produce, such as product labels, thank you stickers, and clothing tags.

APPLICATIONS

Home Use

The ORGBRO Z3 is ideal for organizing your home. Create labels for storage bins, kitchen containers, spice jars, files, and more to maintain a tidy and efficient living space.

For Home Use



Image: Examples of the ORGBRO Z3 Label Maker's utility in home organization, including labels for coffee beans, vanilla extract, stockings, scarves, and office files.

Business Use

For small businesses, the Z3 can print price barcodes, QR codes, product logos, address labels, and inventory tags. It helps streamline operations and enhance professionalism.

For Business Use



Image: Demonstrations of the ORGBRO Z3 Label Maker's application in business, such as shipping labels for packages, labels for baked goods, and jewelry tags.

MAINTENANCE

Cleaning the Print Head

To ensure clear and consistent print quality, regularly clean the print head. Use a cotton swab lightly dampened with isopropyl alcohol. Gently wipe the print head surface. Allow it to dry completely before closing the cover and resuming use.

Battery Care

To prolong battery life, avoid fully discharging the device frequently. Charge the device when the battery indicator is low. If storing the device for an extended period, ensure it is charged to at least 50% and recharge every few months.

TROUBLESHOOTING

Printer Not Responding

- Ensure the device is powered on and fully charged.
- Check Bluetooth connection in the "4BarCode" app or USB cable connection for PC.
- Restart the printer and your connected device.

Poor Print Quality

- Verify that the label paper is loaded correctly and is thermal paper.
- Clean the print head as described in the Maintenance section.
- Ensure the label design in the app is not too complex or has very fine lines that might be difficult to print at 203 DPI.

Labels Not Feeding Correctly

- Check for any obstructions in the paper path.
- Ensure the label roll is properly seated and aligned within the guides.
- Make sure the label compartment cover is securely closed.

SPECIFICATIONS

Model Name	Z3 Label Maker
Brand	ORGBRO
Printing Technology	Thermal
Resolution	203 DPI (Dots Per Inch)
Max Print Speed	Up to 50mm/s (approx. 52 labels/min for 50x30mm labels)
Maximum Media Size	3.14 inches (0.8-3.15 inch wide labels)
Connectivity	Bluetooth, USB Type-C
Compatible Devices	iOS, Android, Windows 7+, Chrome OS, Mac OS 10+, Linux
Battery	2200mAh Rechargeable Battery
Product Dimensions	4.2 x 4.4 x 2.4 inches
Item Weight	1.21 pounds

WARRANTY INFORMATION

The ORGBRO Z3 Label Maker Machine comes with a**Limited Warranty**. Please refer to the warranty card included in your product packaging for specific terms, conditions, and duration. Retain your proof of purchase for warranty






claims.

SUPPORT

For further assistance, technical support, or inquiries regarding your ORGBRO Z3 Label Maker Machine, please contact our customer service team. Refer to the contact information provided on the ORGBRO official website or the support section of the "4BarCode" app.

© 2025 ORGBRO. All rights reserved.

Related Documents - Z3

	<p>ORGBRO X1 Thermal Label Printer User Guide</p> <p>Comprehensive user guide for the ORGBRO X1 Thermal Label Printer, covering setup, operation, charging, product information, and FCC compliance.</p>
	<p>KY Y Z3 15.6" Full HD Portable Monitor User Guide</p> <p>User guide for the KY Y Z3 15.6" Full HD Portable Monitor, covering package contents, introduction to features, smart cover usage, connection methods for various devices, mode settings, supported devices, specifications, notices, and troubleshooting.</p>
	<p>Zalman Z3 Iceberg ATX Mid Tower Computer Case User's Manual</p> <p>This user's manual provides detailed instructions and precautions for installing and using the Zalman Z3 Iceberg ATX Mid Tower Computer Case. It covers safety guidelines, component compatibility, and assembly steps.</p>
	<p>Zalman Z3 Series ATX Mid Tower PC Case User Manual</p> <p>Comprehensive user manual for the Zalman Z3 Series ATX Mid Tower PC Case, covering installation, components, and warranty information.</p>
	<p>Manuel d'utilisation Lave-vaisselle Commercial GGM Gastro GE500M</p> <p>Manuel complet pour le lave-vaisselle commercial GGM Gastro GE500M, incluant les spécifications techniques, les instructions d'installation, d'utilisation, de maintenance, de dépannage, et la liste des pièces.</p>

