

Welio Jr One

Welio Wwatch Jr. One User Manual

MODEL: JR ONE

Introduction

This manual provides essential information for the safe and effective use of your Welio Wwatch Jr. One Android Smart Kids Tracking Watch. Please read this manual thoroughly before using the device and retain it for future reference. The watch is designed to offer communication, tracking, and safety features for children, operating on an Android system with 4G LTE connectivity.

Package Contents

Ensure all items are present in the box:

- Welio Wwatch Jr. One Smart Watch
- User Manual (Documents)
- Magnetic Charging Cable
- Silicone Strap (Pre-installed or separate)
- Additional Strap (Fabric or Silicone)

Device Overview

The Welio Wwatch Jr. One features a 1.75-inch square touch screen display and a durable ABS + Plastic body with a silicone strap. It includes a front-facing camera, speaker, microphone, and physical buttons for operation.



Front view of the Welio Wwatch Jr. One smart watch, displaying a digital clock face. The watch features a camera at the top of the bezel and a KVK Teknik Servis logo in the upper right corner, indicating technical service support.

Setup

1. Charging the Device

Before first use, fully charge the watch. Connect the magnetic charging cable to the charging pins on the back of the watch and plug the USB end into a compatible power adapter (not included) or computer USB port.



Back view of the Welio Wwatch Jr. One smart watch, showing the four magnetic charging pins located on the center of the back casing. The blue silicone strap is also visible.

2. SIM Card Installation

The watch requires a Nano-SIM card for cellular connectivity, calls, and location tracking. Carefully open the SIM card slot cover on the side of the watch and insert the Nano-SIM card with the gold contacts facing up, as indicated by the diagram on the watch. Ensure the cover is securely closed after insertion to maintain water and dust resistance.



Side view of the Welio Wwatch Jr. One smart watch, showing the SIM card slot cover with a small SIM icon next to it. A speaker grille is also visible on the side of the watch casing.

3. Powering On/Off

To power on the watch, press and hold the power button (usually located on the side) until the screen illuminates. To power off, press and hold the power button, then select 'Power Off' on the screen.

4. Connecting to the Parental Control App

For full functionality, including parental control, remote monitoring, and safe zone setup, download the dedicated Welio companion app on your smartphone (compatible with Android and iOS). Follow the in-app instructions to pair the watch with your smartphone. This app enables features like remote shutdown and managing watch settings.

Operating Instructions

1. Basic Navigation

The watch features a touch-sensitive display. Swipe left, right, up, or down to navigate through menus and applications. Tap to select an item. Use the physical buttons for quick actions like returning to the home screen or activating the SOS function.

2. Making and Receiving Calls

Once a SIM card is installed and activated, the watch can make and receive calls. Use the contacts list on the watch to initiate calls. Incoming calls will display on the screen, allowing you to accept or reject them.

3. Using the Camera

Access the camera application from the watch's menu. The 0.3 MP camera supports taking photos and recording videos. Tap the screen to capture images or start/stop video recording.

4. Location Tracking (GPS/LBS)

The watch utilizes GPS and LBS (Location Based Service) for accurate positioning. Location data can be viewed through the parental control app on the paired smartphone, allowing for real-time tracking and setting up safe zones.

5. SOS Function

In an emergency, press and hold the designated SOS button (refer to your watch's specific button layout). The watch will automatically dial pre-set emergency contacts and send location alerts.

6. Other Features

The Welio Wwatch Jr. One includes various applications and features:

- **Smart Notifications:** Receive alerts for incoming calls, SMS, and app notifications.
- **Alarm & Reminders:** Set alarms and reminders for daily tasks.
- **Music Player & Storage:** Play music stored on the device.
- **Pedometer & Activity Tracking:** Monitor steps and activity history.
- **Sleep Monitor:** Track sleep patterns.
- **Flashlight:** Use the built-in light function.
- **Google Play Store:** Install additional compatible applications.
- **Video Calls:** Engage in video calls with approved contacts.

Maintenance

1. Cleaning

Wipe the watch screen and body with a soft, dry, or slightly damp cloth. Avoid using harsh chemicals or abrasive materials, which can damage the device's finish or screen.

2. Water and Dust Resistance

The Welio Wwatch Jr. One is rated IP6X for dust resistance and IPX7 for water resistance. This means it is protected against dust ingress and can withstand immersion in water up to 1 meter for 30 minutes. It is suitable for everyday use and splashes but should not be used for swimming or diving. Ensure the SIM card slot cover is always securely closed.

3. Battery Care

To prolong battery life, avoid exposing the watch to extreme temperatures. Charge the device regularly, but avoid overcharging. If the watch will not be used for an extended period, charge it to about 50% before storing.

Troubleshooting

Common Issues

- **Watch not powering on:** Ensure the watch is fully charged. If it still doesn't power on, try connecting it to the charger for at least 30 minutes.
- **No network signal/calls not working:** Check if the Nano-SIM card is correctly inserted and activated. Verify that your cellular plan supports the watch's 2G/3G/4G bands (GSM, WCDMA, LTE).
- **Inaccurate location tracking:** Ensure the watch has a clear view of the sky for GPS signals. LBS accuracy can vary depending on cellular network coverage.
- **App connection issues:** Make sure Bluetooth and Wi-Fi are enabled on your smartphone and the watch. Reinstall the companion app if necessary.
- **Screen unresponsive:** Try restarting the watch. If the issue persists, a factory reset might be required.

Factory Reset

If the watch experiences persistent software issues, a factory reset can resolve them. This will erase all data on the watch and restore it to its original factory settings. Consult the parental control app or the watch's settings menu for the factory reset option. **Warning: Back up any important data before performing a factory reset.**

Specifications

Brand	Welio
Model Name	Jr One
Operating System	Android 8.1
Processor	ARM Cortex-A55, 1.5 GHz Quad-Core (ASR8601 Chipset)
RAM	2 GB
Internal Storage	16 GB
Display	1.75 inch IPS LCD, 240x296 pixels, Touchscreen
Camera	0.3 MP, Video Recording
Battery Capacity	700 mAh Lithium-ion
Average Battery Life	Up to 2 days
Charging Method	Magnetic Charging Station
SIM Type	Nano-SIM
Connectivity	2G GSM, 3G WCDMA, 4G LTE, Wi-Fi, Bluetooth (No direct USB data connection)
Location Services	GPS, LBS
Sensors	Accelerometer, Gyroscope
Water Resistance	IPX7
Dust Resistance	IP6X
Body Material	ABS + Plastic

Strap Material	Silicone (Replaceable)
Weight	52 g
Compatible OS	Android, iOS (for companion app)

Warranty and Support

Warranty Information

The Welio Wwatch Jr. One comes with KVK warranty, ensuring support for manufacturing defects and malfunctions under normal use. Please refer to the warranty card included in your package for specific terms, conditions, and duration of coverage.

Customer Support

For technical assistance, troubleshooting, or warranty claims, please contact Welio Türkiye customer support. Contact details can typically be found on the official Welio website or within the product documentation. When contacting support, please have your product model (Jr One) and purchase information ready.