

[Manuals.plus](#) /

› [ZHIWHIS](#) /

› ZHIWHIS ZWS-700 Bluetooth Speaker Radio MP3 Player User Manual

ZHIWHIS ZWS-700

ZHIWHIS ZWS-700 Bluetooth Speaker Radio MP3 Player User Manual

Model: ZWS-700 | Brand: ZHIWHIS

1. INTRODUCTION

Thank you for purchasing the ZHIWHIS ZWS-700 Bluetooth Speaker Radio MP3 Player. This device combines a multi-band radio, Bluetooth speaker, and MP3 player in a compact, durable design. It features advanced DSP reception, multiple tuning methods, and app control for enhanced usability. Please read this manual carefully to ensure proper operation and to fully utilize all functions.

ポータブルスピーカー


ラジオ受信 / Bluetooth5.1再生 / MicroSD カード再生



選局ダイヤル



ワイドFM/
FM/AM/SW



音量調整
つまみ



3W高音質
スピーカー



3.5mm
イヤホン対応




スリープ
タイマー



EQ(音質)選択
繰返し再生選択



コントロール
APP



TYPE-C
USB充電



ATS
オート選局
&メモリー
AM/FM/SW各
99局メモリー



219 - 229056

1000mAh
便利で長時間
連続使用可能

10時間

*中音量

音楽リズムランプ

ポケット高感度

外部アンテナ



Image: The ZHIWHIS ZWS-700 device, showcasing its compact and robust design.

2. PRODUCT FEATURES

- **Multi-Band Radio:** Supports FM, AM, Shortwave (SW), and Wide FM bands with high-sensitivity DSP reception.
- **Bluetooth 5.1 Connectivity:** Seamless wireless audio streaming from compatible devices.
- **MP3 Player:** Supports MicroSD card playback up to 256GB with various audio formats (MP3, WMA, WAV, APE,

FLAC).

- **APP Control:** Intelligent remote control functionality via a dedicated mobile application.
- **High-Quality Audio:** Built-in 4Ω 3W speaker with enhanced bass output.
- **Headphone Support:** Connect headphones via the included USB Type-C to 3.5mm jack cable.
- **Selectable EQ Effects:** 6 equalizer sound effects for personalized audio.
- **Music Rhythm Lamp:** Visual light effect that synchronizes with music playback.
- **Sleep Timer:** Adjustable off-timer function up to 70 minutes in 10-minute increments.
- **Rechargeable Battery:** Equipped with a replaceable 1000mAh lithium battery, offering approximately 10 hours of continuous playback.
- **USB-C Charging:** Modern USB Type-C port for convenient charging.
- **Portable Design:** Compact (88x53x37mm) and lightweight (100g) with an included strap and waterproof storage bag.

3. PACKAGE CONTENTS

Please check the box for the following items:

- 1 x ZWS-700 Portable Radio Speaker Unit
- 1 x 1000mAh Lithium Battery
- 1 x USB Type-C Charging Cable
- 1 x USB Type-C to 3.5mm Jack Cable
- 1 x External Extension Antenna
- 1 x Strap
- 1 x Waterproof Storage Bag
- 1 x User Manual & Warranty Card (Japanese)



Image: All items included in the ZHIWHIS ZWS-700 package.

4. CONTROLS AND FUNCTIONS

Familiarize yourself with the buttons, dials, and ports on your ZWS-700 device.

1000 MAH リチウム電池

USB接続で充電でき、4時間の充電でも10時間以上の再生が可能。

USB
充電式



Image: Rear view of the ZWS-700 showing the USB-C port, MicroSD slot, and battery compartment.

Key Components:

- **Tuning Dial:** Located on the side for manual frequency selection.

- **Volume Control:** Adjusts audio output level.
 - **Mode Button (MOD):** Switches between Radio, Bluetooth, and MicroSD playback modes. Double-press to activate Music Rhythm Lamp.
 - **EQ Button:** Cycles through available equalizer presets.
 - **Playback Controls:** Play/Pause, Next/Previous track buttons.
 - **USB Type-C Port:** For charging and connecting the 3.5mm headphone adapter.
 - **MicroSD Card Slot:** Insert MicroSD card for MP3 playback.
 - **Antenna:** Telescopic antenna for FM/SW/Wide FM reception. External antenna port for enhanced reception.
 - **Battery Compartment:** Houses the replaceable 1000mAh lithium battery.
-

5. SETUP

5.1. Battery Installation and Charging

1. Open the battery compartment cover on the back of the device.
2. Insert the provided 1000mAh lithium battery, ensuring correct polarity.
3. Close the battery compartment cover securely.
4. Connect the USB Type-C charging cable to the device's USB-C port and a compatible USB power adapter (not included).
5. The charging indicator lamp will illuminate during charging. A full charge takes approximately 4 hours.

1000 MAH リチウム電池

USB接続で充電でき、4時間の充電でも10時間以上の再生が可能。

USB
充電式



1000mAh
大容量充電式リチウム電池

バッテリーインジケータ

充電やバッテリー残量を確認することができます。

Image: The battery compartment and USB-C charging port on the ZWS-700.

5.2. Antenna Setup

- For FM/SW/Wide FM reception, extend the telescopic antenna fully.
- For improved reception, especially for Shortwave, connect the external extension antenna to the designated port.
- AM reception uses an internal bar antenna and does not require extending the telescopic antenna.



Image: The ZWS-700 with the external antenna connected for enhanced reception.

6. OPERATING INSTRUCTIONS

6.1. Power On/Off

Press and hold the power button to turn the device on or off.

6.2. Radio Operation

1. Press the **MODE** button to select the Radio mode (FM, AM, SW, or Wide FM).
2. **Tuning Methods:**
 - **Manual Tuning:** Rotate the tuning dial on the side to adjust the frequency.
 - **Automatic Tuning (ATS):** Press the **SCAN** button to automatically scan and save available stations. The device can store up to 99 presets per band.
 - **Preset Selection:** Use the M+ / M- buttons to navigate through saved preset stations.
3. Adjust the volume using the volume control dial.



選局ダイヤル

ダイヤルを回して周波数を選択します。



チャンネル選択方法：

1. 「▶▶」または「◀◀」ボタンを押します。
2. 側面の選局ダイヤルを使用します。

選局ダイヤル



APPコントロール

製品はAPPインテリジェント リモートコントロール機能があります。



Image: A hand operating the tuning dial for radio frequency selection.

高音質3Wスピーカー

強化された低音出力

- ✓ FM/AM/SWラジオ
- ✓ MicroSDカード対応
- ✓ Bluetooth 5.1



Image: The ZWS-700 demonstrating multi-band radio reception capabilities, including FM, AM, SW, and Wide FM.

6.3. Bluetooth Playback

1. Press the **MODE** button to select Bluetooth mode. The device will enter pairing mode, indicated by a flashing Bluetooth icon.
2. On your smartphone or other Bluetooth-enabled device, search for "ZWS-700" in the Bluetooth settings and select it to pair.
3. Once paired, you can play audio from your device through the ZWS-700 speaker.

4. Use the playback controls on the ZWS-700 or your connected device to manage music.



Image: The ZWS-700 connected via Bluetooth to a smartphone, ready for audio playback.

6.4. MicroSD Card Playback

1. Insert a MicroSD card (up to 256GB) with MP3, WMA, WAV, APE, or FLAC audio files into the MicroSD card slot.
2. Press the **MODE** button to select MicroSD playback mode.
3. The device will automatically start playing music from the card.
4. Use the playback controls (Play/Pause, Next/Previous) to navigate your music.
5. Press the **EQ** button to cycle through 6 available equalizer sound effects.
6. The MicroSD playback also supports 4 repeat modes: All songs, Single song, All songs in folder, and Random all songs.



Image: A MicroSD card being inserted into the dedicated slot on the ZWS-700.

6.5. APP Control

1. Download the dedicated ZHIWHIS control application from your smartphone's app store.
2. Ensure Bluetooth is enabled on your smartphone and the ZWS-700 is in Bluetooth mode.
3. Open the app and follow the on-screen instructions to connect to your ZWS-700.
4. The app allows for remote control of various functions, including tuning, mode selection, volume, and EQ settings.

マルチバンドが受信可能です！

FM/AM/SW/ワイドFM対応

ワイドFM対応

FM: 76-108MHz

AM: 522-1620KHz

SW: 5.70-17.90MHz

20m

FM/SW(短波)/ワイドFM用の伸縮ロッドアンテナを内蔵し、AM用の内蔵バーアンテナと3メートル延長アンテナを備え、すべての帯域で高感度な受信効果を提供することができます。

Image: The ZWS-700 being controlled remotely via its dedicated smartphone application.

6.6. Music Rhythm Lamp

While the device is powered on, quickly press the **MODE** button twice to activate the music rhythm lamp. The lights will flash in sync with the music playback.

6.7. Sleep Timer

1. The sleep timer function allows the device to automatically power off after a set period.

2. Refer to the device's display or the app for timer settings. The timer can be set in 10-minute increments, up to a maximum of 70 minutes.



高音質スピーカー & スリープタイマー



高音質スピーカー

本体内蔵の高音質 $\Phi 40\text{mm}/4\Omega/3\text{W}$ スピーカーはクリアで明快な低中高音と更に豊かなディテールを備えた高音質スピーカーです！



スリープタイマー機能

指定した時間後に自動的に電源オフにする機能で、最長 70 分まで 10 分 刻みで設定可能です。

Image: The ZWS-700 being used with its sleep timer function, ideal for bedtime listening.

6.8. Headphone Use

Connect the included USB Type-C to 3.5mm jack cable to the USB-C port on the device, then plug your 3.5mm headphones (not included) into the adapter for private listening.

7. MAINTENANCE

- **Cleaning:** Wipe the device with a soft, dry cloth. Do not use liquid cleaners or abrasive materials.
- **Storage:** When not in use for extended periods, store the device in a cool, dry place. Remove the battery if storing for several months.
- **Battery Care:** Recharge the battery regularly, even if not in use, to maintain its lifespan. Avoid extreme temperatures.
- **Antenna Care:** Handle the telescopic antenna gently to prevent bending or breaking.

8. TROUBLESHOOTING

Problem	Possible Cause	Solution
No power	Battery is depleted or not installed correctly.	Charge the battery. Ensure the battery is inserted with correct polarity.
Poor radio reception	Antenna not extended, weak signal, or interference.	Extend the telescopic antenna fully. Try connecting the external antenna. Move to an area with better signal.
Bluetooth not pairing	Device not in pairing mode, or already connected to another device.	Ensure the ZWS-700 is in Bluetooth pairing mode. Disconnect from other devices. Restart both devices.
MicroSD card not playing	Card not inserted correctly, unsupported file format, or corrupted card.	Reinsert the MicroSD card. Ensure files are in supported formats (MP3, WMA, WAV, APE, FLAC). Try a different MicroSD card.
No sound from headphones	USB-C to 3.5mm adapter or headphones not connected properly.	Ensure the adapter is fully inserted into the USB-C port and headphones are fully plugged into the adapter. Check headphone functionality with another device.

9. SPECIFICATIONS

Feature	Detail
Model Number	ZWS-700
Dimensions (L x W x H)	8.8 x 5.3 x 3.7 cm
Weight	100 g
Material	Plastic
Tuner Type	FM/AM/Shortwave/Wide FM
Display Type	Analog Scale
Connectivity	Bluetooth 5.1, USB

Feature	Detail
Power Source	Battery Operated (1000mAh Lithium Battery)
Charging Port	USB Type-C
Charging Time	Approx. 4 hours
Playback Time	Approx. 10 hours (standard use)
Speaker Output	4Ω 3W
MicroSD Support	Up to 256GB (MP3, WMA, WAV, APE, FLAC)
Special Features	APP Control, 6 EQ Sound Effects, Music Rhythm Lamp, Sleep Timer, ATS Presets
Certifications	TELEC Certified (Frequency band: 2402MHz~2480MHz)

10. WARRANTY AND SUPPORT

The ZHIWHIS ZWS-700 is a TELEC certified product, ensuring compliance with technical standards. For warranty claims or technical support, please refer to the warranty card included in your package or contact your retailer. Keep your purchase receipt as proof of purchase.