

## LaLuLa Crystal Chandeliers

# LaLuLa Large White Crystal Chandelier Flush Mount 18-inch User Manual

## 1. INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your LaLuLa Large White Crystal Chandelier Flush Mount. This 18-inch flush mount chandelier features a handmade cotton shade and premium crystal droplets, designed to provide ambient lighting. It requires four E12 base bulbs (max 40W each, not included) and is compatible with LED, incandescent, or halogen bulbs. The fixture is dimmable when used with a compatible dimmer switch and dimmable bulbs. Please read all instructions carefully before beginning installation.

## 2. SAFETY INFORMATION

- **Electrical Safety:** Always turn off the main power supply at the circuit breaker before installing, cleaning, or servicing the fixture.
- **Qualified Electrician:** If you are unsure about electrical wiring, consult a qualified electrician.
- **Grounding:** Ensure the fixture is properly grounded to avoid potential electrical shock.
- **Bulb Requirements:** Use only E12 base bulbs, maximum 40 watts per bulb. Do not exceed the recommended wattage.
- **Handling Crystals:** Handle crystal droplets with care to prevent breakage or injury.
- **Secure Mounting:** Ensure the mounting surface can support the weight of the fixture.

## 3. PACKAGE CONTENTS

Verify that all components are present before beginning installation:

- Chandelier Fixture (with cotton shade and chrome canopy)
- Crystal Droplets (pre-attached or requiring assembly)
- Mounting Hardware (screws, wire nuts, mounting bracket)
- Instruction Manual

## 4. SETUP AND INSTALLATION

**Tools Required:** Screwdriver, wire strippers, electrical tape, ladder, safety glasses.

1. **Turn Off Power:** Before starting, ensure the power to the installation area is completely OFF at the circuit breaker.
2. **Prepare Mounting Surface:** Remove any existing light fixture. Install the mounting bracket to the junction box in the ceiling using the provided screws. Ensure it is securely fastened.
3. **Wiring Connections:** Connect the fixture's wires to the household electrical wires. Match the black wire (live) from the fixture to the black wire from the ceiling, the white wire (neutral) from the fixture to the white wire from the ceiling, and the ground wire (bare copper or green) from the fixture to the ground wire from the ceiling. Secure connections with wire nuts and electrical tape.
4. **Mount the Canopy:** Carefully push the wired canopy up to the ceiling, aligning the screw holes on the canopy with the mounting bracket. Secure the canopy with the provided screws.
5. **Attach Shade and Crystals:** The cotton shade is typically pre-attached. If crystal droplets are not pre-attached, carefully hook each crystal strand onto the designated loops on the fixture. Ensure all crystals are securely fastened.



Figure 3: Product dimensions and key components, showing the canopy, shade, and crystal arrangement.

6. **Install Bulbs:** Screw four E12 base bulbs (not included) into the sockets. Do not overtighten.
7. **Restore Power:** Once installation is complete and all components are secure, turn the power back ON at the circuit breaker.

The chandelier is now ready for use. Below are examples of the chandelier installed in various settings:



Figure 1: Chandelier installed in a closet setting.



Figure 2: Chandelier installed in a bedroom setting.



Figure 5: Chandelier installed in a nursery setting.



Figure 6: Chandelier installed in a hallway setting.

## 5. OPERATING INSTRUCTIONS

---

To operate the chandelier, use the standard wall switch connected to the fixture's electrical circuit. If a compatible dimmer switch and dimmable E12 bulbs are installed, you can adjust the light intensity.

- **Turning On/Off:** Flip the wall switch to turn the chandelier on or off.
- **Dimming Function:** If equipped with a dimmer switch and dimmable bulbs, rotate or slide the dimmer control to adjust the brightness level.
- **Bulb Replacement:** Ensure power is off at the circuit breaker before replacing bulbs. Allow bulbs to cool completely before touching. Unscrew old bulbs and screw in new E12 base bulbs (max 40W).

# PRODUCT DETAILS

**15.7in**

**9.7in**

**18in**

**Premium Cotton Hand-Wrapped**  
Each piece is unique

**Exquisite Crystal Flower**  
Brings timeless elegance

**Chrome-Plated Canopy**  
Premium & sophisticated look

Requires 4 E12 base bulbs  
(max 40W per bulb) BULBS NOT INCLUDED

Figure 4: Chandelier illumination comparison (ON vs. OFF), demonstrating the light output.

## 6. MAINTENANCE

- **Cleaning:** Turn off power before cleaning. Use a soft, dry cloth to wipe the chrome canopy and cotton shade. For crystal droplets, a slightly damp cloth with mild glass cleaner can be used, ensuring no liquid drips into electrical components.
- **Regular Checks:** Periodically check all connections and mounting hardware to ensure they remain secure.
- **Bulb Longevity:** Replace bulbs as needed. Using LED bulbs can extend the time between replacements and reduce energy consumption.

## 7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on	No power supply; Loose wiring; Faulty bulb; Faulty switch	Check circuit breaker; Verify wire connections; Replace bulb; Test/replace switch.

Problem	Possible Cause	Solution
Light flickers	Loose bulb; Incompatible dimmer/bulb; Loose wiring	Tighten bulb; Ensure dimmer and bulbs are compatible; Check wiring connections.
Crystals fall off	Improper attachment; Damaged hooks	Re-attach crystals securely; Replace damaged hooks if necessary.

## 8. SPECIFICATIONS

Feature	Detail
Brand	LaLuLa
Model Name	Crystal Chandeliers
Color	White
Material	Cotton Thread, Crystal, Metal
Product Dimensions	18"L x 18"W x 9.7"H
Installation Type	Flush Mount
Number of Light Sources	4
Bulb Base	E12
Max Wattage per Bulb	40 Watts
Voltage	120 Volts
Special Feature	Dimmable (with compatible switch/bulbs)
Item Weight	8.48 pounds

## 9. WARRANTY INFORMATION

Please refer to your purchase documentation or contact the retailer/manufacturer directly for specific warranty details regarding your LaLuLa Large White Crystal Chandelier Flush Mount.

## 10. SUPPORT

For further assistance, technical support, or to inquire about replacement parts, please contact LaLuLa customer service or visit the official LaLuLa store online.

**LaLuLa Store:** <https://www.amazon.com/stores/LaLuLaLighting/page/578CB255-E74C-4F71-B64E-73D620B40E1E>