

MARYETTZK-NATURALLIGHT-CHROMEL100CM

Modern Light Luxury Crystal s-Shaped Chandelier

Model: MARYETTZK-NATURALLIGHT-CHROMEL100CM

INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your new Modern Light Luxury Crystal s-Shaped Chandelier. Please read this manual thoroughly before installation and retain it for future reference. Proper installation and adherence to safety guidelines are crucial for optimal performance and safety.

IMPORTANT SAFETY INSTRUCTIONS

- **WARNING:** To avoid electric shock, ensure power is turned off at the circuit breaker before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with electrical wiring.
- This fixture is intended for indoor use only. Do not expose to water or moisture.
- Ensure the mounting surface can support the weight of the fixture.
- Do not connect this fixture to an ungrounded electrical system.
- Handle crystal components with care to prevent breakage.

PACKAGE CONTENTS

Verify that all components listed below are present and undamaged before proceeding with installation.

- Chandelier Frame with Integrated LED Bulbs
- Crystal Elements
- Mounting Hardware (Canopy, Mounting Bracket, Screws, Wire Nuts)
- Instruction Manual

PRODUCT SPECIFICATIONS

Specification	Detail
---------------	--------

Brand	Generic
Model Name	MARYETTZK-NATURALLIGHT-CHROMEL100CM
Voltage	AC85-265V
Light Source	Integrated LED
Mounted Method	Suspension Type
Body Material	Metal (Polished Stainless Steel), Crystal
Light Color Options	Warm Light, White Light, Neutral Light, Dimmable (depending on variant)
Safety Certification	UL Listed Components
Overall Length	100cm (approx. 39.4 inches)
Canopy Dimensions	L80cm x W12cm x H4cm (approx. 31.5"L x 4.7"W x 1.6"H)
Adjustable Wire Height	Up to 150cm (approx. 59 inches)

Refer to the image below for visual dimensions.



Figure 1: Chandelier Dimensions. This diagram illustrates the key measurements of the chandelier, including the canopy and adjustable suspension wires.

INSTALLATION GUIDE

1. Pre-Installation Checklist

- Turn off power at the main circuit breaker.
- Ensure you have all necessary components as listed in "Package Contents".
- Prepare the installation area, ensuring it is clean and dry.

2. Tools Required (Not Included)

- Phillips Head Screwdriver
- Wire Strippers
- Electrical Tape
- Ladder
- Safety Glasses

3. Mounting the Canopy

1. Carefully unpack the chandelier and its components.
2. Attach the mounting bracket to the junction box in the ceiling using the provided screws. Ensure it is securely fastened.
3. Feed the electrical wires from the ceiling through the center hole of the mounting bracket and canopy.

4. Wiring Instructions

1. Connect the fixture's live (black or smooth) wire to the house's live wire using a wire nut.
2. Connect the fixture's neutral (white or ribbed) wire to the house's neutral wire using a wire nut.
3. Connect the fixture's ground wire (green or bare copper) to the house's ground wire and the mounting bracket's ground screw.
4. Secure all wire connections with electrical tape.
5. Carefully tuck all wires into the junction box.

5. Attaching the Crystal Elements

The chandelier features elegant crystal shades. Attach these carefully according to the design. The crystals are typically pre-assembled or hook onto designated points on the fixture frame.



Figure 2: Detail of Crystal Elements. This image shows the intricate arrangement of the crystal components on the chandelier frame.

6. Adjusting Height

The suspension wires are adjustable up to 150cm. Adjust the wire length to achieve your desired hanging height before securing the canopy to the mounting bracket. Ensure the fixture is level.

7. Finalizing Installation

1. Align the canopy with the mounting bracket and secure it with the provided screws.
2. Restore power at the circuit breaker and test the light fixture.



Figure 3: Installed Chandelier. An example of the chandelier installed in a dining room, demonstrating its appearance when fully assembled and lit.

OPERATING INSTRUCTIONS

Once installed and power is restored, operate the chandelier using a standard wall switch. If you have a dimmable variant, ensure you use a compatible LED dimmer switch for proper functionality.

MAINTENANCE

- **Cleaning:** Turn off power before cleaning. Use a soft, dry, or slightly damp cloth to wipe the metal frame. For crystal elements, use a specialized crystal cleaner or a damp cloth with mild soap, then dry immediately to prevent water spots. Do not use abrasive cleaners or solvents.
- **LED Bulbs:** The LED bulbs are integrated and designed for long life. They are not user-replaceable. If the LEDs fail, contact customer support.
- **Inspection:** Periodically check all connections and mounting hardware to ensure they remain secure.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on	No power to the fixture; Loose wiring; Faulty switch	Check circuit breaker; Verify all wire connections; Test wall switch.
Light flickers	Loose wiring; Incompatible dimmer switch (if applicable)	Check wire connections; Ensure dimmer is LED compatible.
Fixture is unstable	Mounting bracket not secure; Loose canopy screws	Tighten mounting bracket screws; Secure canopy screws.

WARRANTY AND SUPPORT

This product is covered by a standard manufacturer's warranty against defects in materials and workmanship. For warranty claims, technical support, or replacement parts, please contact the retailer or manufacturer directly. Keep your purchase receipt as proof of purchase.