Eureka Forbes AP 230

Eureka Forbes AP 230 Air Purifier User Manual

Model: AP 230

Introduction Features Setup Operation Maintenance Troubleshooting Specifications Support

1. Introduction

Thank you for choosing the Eureka Forbes AP 230 Air Purifier. This manual provides essential information for the safe and efficient operation of your new appliance. Please read it thoroughly before use and retain it for future reference. The AP 230 is designed to improve your indoor air quality by effectively removing airborne pollutants.



Image 1: Eureka Forbes AP 230 Air Purifier. This image displays the compact, cylindrical design of the white air purifier with its control panel on top.

2. Product Features

The Eureka Forbes AP 230 Air Purifier incorporates advanced technologies to ensure superior air purification:

- **Surround 360° Air Intake Technology:** Efficiently draws in air from all directions to capture pollutants quickly.
- **4-Stage Advanced Purification:** A comprehensive filtration system designed to remove 99.97% of dust and particulate matter as small as 0.1 µm.
- **True HEPA H13 Filter:** Targets ultra-fine particles including pollen, mold, and microbes.
- **Activated Carbon Filter:** Absorbs odors, Volatile Organic Compounds (VOCs), and smoke.
- **Ionizer:** Further eliminates harmful viruses and bacteria.
- **Long Filter Life:** Filters are designed to last approximately 1.5 to 2 years, depending on usage and environmental conditions.

- **Real-Time Air Quality Indicator (PM2.5):** Provides immediate feedback on current air quality.
- **Ultra-Quiet Sleep Mode:** Operates at a reduced noise level for undisturbed rest.
- **3-Speed Fan Control:** Allows adjustment of airflow intensity.
- **Filter Change Alert:** Notifies you when it's time to replace the filter.
- **Energy Saving Timers:** Schedule operation for energy efficiency.
- **Coverage Area:** Effective for rooms up to 310 sq. ft.



Image 2: Diagram illustrating the 4-stage filtration process. This image shows the internal components of the air purifier, detailing the Pre-filter, HEPA filter, Activated Carbon Filter, and Ionizer.



Image 3: Visual representation of Surround 360° Air Technology. This image depicts the air purifier in a living room setting, illustrating how it draws in air from all sides.



Image 4: Close-up of the air purifier's control panel. This image highlights the touch controls for fan speed, sleep mode, timers, and the air quality indicator.

3. Setup Instructions

3.1 Unpacking

1. Carefully remove the air purifier from its packaging.
2. Remove all protective plastic films and packaging materials.
3. Verify that all included components (Air Purifier, User Manual) are present.

3.2 Filter Installation

The filters are typically pre-installed but may have protective packaging that needs to be removed before first use.

1. Turn the air purifier upside down and twist the base counter-clockwise to unlock and remove it.
2. Gently pull out the integrated filter cartridge.

3. Remove any plastic bags or protective wrapping from the filter.
4. Insert the unwrapped filter back into the air purifier, ensuring it is seated correctly.
5. Replace the base and twist clockwise to lock it securely.

3.3 Placement

For optimal performance, place the air purifier on a flat, stable surface in the room where air purification is desired. Ensure there is at least 20 cm of clear space around all sides for unrestricted airflow.

3.4 Power Connection

Plug the power cord into a suitable electrical outlet. The unit is not cordless.

4. Operating Instructions

The AP 230 features a touch control panel for easy operation.

4.1 Power On/Off

- To turn on the air purifier, touch the **Power** button on the control panel.
- To turn off the air purifier, touch the **Power** button again.

4.2 Adjusting Fan Speed

- Touch the **Fan Speed** button to cycle through the available fan speeds (Low, Medium, High).

4.3 Activating Sleep Mode

- Touch the **Sleep Mode** button to activate the ultra-quiet operation. The display lights will dim, and the fan speed will reduce.
- Touch the **Sleep Mode** button again to exit Sleep Mode.



Image 5: Air purifier operating in Sleep Mode. This image shows the air purifier next to a sleeping child, emphasizing its quiet operation.

4.4 Setting Timers

- Touch the **Timer** button to set the desired operating duration (e.g., 1H, 2H, 4H, 8H). The unit will automatically turn off after the set time.

4.5 Understanding the Air Quality Indicator

The PM2.5 indicator on the control panel changes color to reflect the current air quality. Refer to the manual for specific color meanings (e.g., Blue for Good, Green for Moderate, Red for Poor).

5. Maintenance

Regular maintenance ensures optimal performance and extends the life of your air purifier.

5.1 Filter Replacement

The integrated filter has a life expectancy of approximately 1.5 to 2 years. The unit will provide a filter change alert when replacement is necessary.



Image 6: Illustration of the air purifier's long filter life. This image highlights the internal filter and indicates a lifespan of 1.5 to 2 years.

1. Unplug the air purifier from the power outlet.
2. Turn the unit upside down and twist the base counter-clockwise to remove it.
3. Remove the old filter cartridge.
4. Insert a new, genuine Eureka Forbes AP 230 replacement filter.
5. Replace the base and twist clockwise to lock it securely.
6. Plug in the air purifier and reset the filter life indicator (refer to the control panel section for specific instructions).

5.2 Cleaning the Exterior

- Ensure the air purifier is unplugged before cleaning.
- Wipe the exterior surfaces with a soft, damp cloth. Do not use abrasive cleaners or solvents.

- Gently clean the air intake and outlet vents to remove any accumulated dust.

6. Troubleshooting

If you encounter issues with your air purifier, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Unit does not turn on	No power supply	Check if the power cord is securely plugged into the outlet and the unit. Test the outlet with another device.
Weak airflow	Blocked air intake/outlet or dirty filter	Ensure vents are clear. Check and clean the pre-filter. Replace the main filter if the filter change alert is active.
Unusual noise	Foreign object or improper filter installation	Unplug the unit and check for any foreign objects. Reinstall the filter to ensure it is seated correctly.
Odor persists	Activated Carbon Filter saturation	Replace the integrated filter.

If the problem persists after attempting these solutions, please contact customer support.

7. Specifications

Feature	Detail
Brand	Eureka Forbes
Model Name	AP 230
Filter Type	HEPA Filter (True HEPA H13)
Control Method	Touch
Coverage Area	310 Sq. Ft.
Color	White
Item Weight	3 kg 300 g
Included Components	Air Purifier, User Manual
Is It Cordless?	No
Manufacturer	Eureka Forbes Ltd
Item Model Number	GAPDF230KJB000



Image 7: Diagram showing the dimensions and coverage area of the air purifier. This image illustrates the height (360 mm) and width (220 mm) of the unit, along with its 310 sq. ft. coverage.

8. Warranty and Support

Eureka Forbes is committed to providing excellent customer service. Your AP 230 Air Purifier is backed by a wide service network.

- **Extensive Service Network:** Covering over 19,500 Pincodes across India.
- **12-Hour Support:** Available via toll-free call for prompt assistance.
- **Video Call Assistance:** Support available within 24 hours for visual troubleshooting.

For service requests, technical assistance, or warranty information, please contact Eureka Forbes customer support through their official channels.



Image 8: Representation of Eureka Forbes' extensive service network. This image features a service technician and highlights the wide coverage and support options available.

© 2025 Eureka Forbes. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question