

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Enbrighten](#) /

› [Enbrighten Vibe Eternity Accent Light Power Supply \(Model 86132\) Instruction Manual](#)

Enbrighten 86132

Enbrighten Vibe Eternity Accent Light Power Supply (Model 86132) Instruction Manual

Brand: Enbrighten | **Model:** 86132

1. PRODUCT OVERVIEW

The Enbrighten Vibe Eternity Accent Light Power Supply (Model 86132) is designed to enhance and expand the plug-in capabilities of your existing Enbrighten VIBE Eternity Accent Light sets. This unit serves as a dedicated power source and is not a standalone lighting product. It is specifically engineered to be compatible with Enbrighten VIBE 50ft., 100ft., and 150ft. Eternity Accent Light sets (sold separately).

This power supply includes a 20ft. lead cord, along with clips and mounting screws for reliable installation. It is safety certified to meet ETL and NEC requirements for outdoor lighting, featuring an all-weather rating suitable for operating temperatures from -4°F to 131°F, ensuring year-round enjoyment.

Power Supply Only

Directly compatible with Enbrighten VIBE
50ft., 100ft. and 150ft. Eternity Accent Lights.



Image 1.1: Example of Enbrighten Vibe Eternity Accent Lights installed on a home. This power supply is designed to power such light sets.

2. PACKAGE CONTENTS

Please verify that all components are present in your package:

- 1 x Enbrighten Vibe Eternity Accent Light Power Supply
- 1 x 20ft. Lead Cord (integrated with power supply)
- Mounting Clips
- Mounting Screws



Image 2.1: Included components: Power supply unit with lead cord, clips, and screws.

3. SAFETY INFORMATION AND WARNINGS

WARNING:

- This product is intended for outdoor use and is safety certified to meet ETL and NEC requirements.
- Always unplug the power supply from the outlet before installation, maintenance, or when not in use.
- Do not submerge the power supply or any electrical components in water.
- Ensure all connections are secure and protected from moisture.
- Do not attempt to open or modify the power supply unit. There are no user-serviceable parts inside.
- Operate only within the specified temperature range of -4°F to 131°F (-20°C to 55°C).

Proposition 65 Warning:

This product may contain chemicals known to the State of California to cause cancer and birth defects or

other reproductive harm.

4. SETUP AND INSTALLATION

This power supply is designed to be used with Enbrighten VIBE Eternity Accent Light sets (50ft, 100ft, or 150ft). It cannot be used as a standalone lighting product.

1. **Plan Your Installation:** Determine the optimal placement for your Eternity Accent Lights and the power supply. The power supply includes a 20ft lead cord for flexible placement.
2. **Mount the Power Supply:** Use the provided mounting clips and screws to securely attach the power supply unit in a suitable outdoor location, ensuring it is protected from direct heavy rainfall if possible, though it is weatherproof.
3. **Connect Light Strands:** Connect your Enbrighten VIBE Eternity Accent Light strands to the power supply's output connector. Ensure the connection is firm and secure.
4. **Secure Light Strands:** Utilize the provided cord clips and screws (which may include premium 3M VHB tape for additional adhesion) to neatly organize and secure the light strands along your desired installation path (e.g., eaves, pergolas, balconies).
5. **Extend Coverage (Optional):** For larger installations, you can connect multiple Eternity Accent Light strands or extensions, up to a total length of 150ft, to this power supply. Refer to your Eternity Accent Light set manual for specific linking instructions.
6. **Fine-Tune Length (Optional):** The end of the Eternity Accent Light strand can be cut to fine-tune your setup. Refer to your Eternity Accent Light set manual for safe cutting instructions.
7. **Plug In:** Once all connections are secure and the light strands are installed, plug the power supply into a suitable outdoor GFCI-protected electrical outlet.

Extend your lights



85710



85714



85716



Image 4.1: The power supply is compatible with 50ft, 100ft, and 150ft Eternity Accent Light sets.

5. OPERATING INSTRUCTIONS

The Enbrighten VIBE Eternity Accent Lights, powered by this supply, are controlled through the free Enbrighten app. This app is available for download on both the Apple App Store and Google Play.

- Download the Enbrighten app from your device's app store.
- Follow the in-app instructions to pair your Eternity Accent Light system with your smartphone or tablet.
- Use the app to customize lighting effects, schedules, and other features.

6. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your power supply and accent lights.

- **Cleaning:** Periodically wipe the power supply unit and visible parts of the lead cord with a soft, damp cloth. Do not use harsh chemicals or abrasive cleaners.
- **Inspection:** Annually inspect the power supply, lead cord, and all connections for any signs of

damage, wear, or corrosion. Ensure all mounting points remain secure.

- **Connection Integrity:** Verify that all electrical connections remain tight and free from moisture.
- **Storage:** If storing the unit for an extended period, disconnect it from power and store it in a cool, dry place.

7. TROUBLESHOOTING

If you encounter issues with your Enbrighten Vibe Eternity Accent Light Power Supply, please refer to the following common solutions:

- **Lights Not Turning On:**
 - Ensure the power supply is securely plugged into a working GFCI-protected outlet.
 - Verify that the accent light strands are correctly connected to the power supply.
 - Check your home's circuit breaker to ensure power is supplied to the outlet.
 - Confirm the lights are turned on via the Enbrighten app.
- **Incompatibility with Light Strands:**
 - This power supply is specifically designed for Enbrighten VIBE 50ft., 100ft., and 150ft. Eternity Accent Light sets. It may not be compatible with other Enbrighten light products or older versions. Verify your light strand model number for compatibility.
- **App Connection or Software Update Issues:**
 - Ensure your smartphone or tablet has a stable Wi-Fi connection.
 - Restart the Enbrighten app and attempt to reconnect or update the software again.
 - Unplug the power supply from the outlet for 30 seconds, then plug it back in to perform a soft reset.
 - If issues persist, consult the Enbrighten app's help section or contact customer support.

8. SPECIFICATIONS

Feature	Detail
Model Number	86132
Brand	Enbrighten
Manufacturer	Jasco Products Company, LLC
Lead Cord Length	20ft.
Color	Black
Material	Plastic
Power Source	Corded Electric
Compatibility	Enbrighten VIBE 50ft., 100ft., and 150ft. Eternity Accent Light sets
Certifications	ETL, NEC
Operating Temperature	-4°F to 131°F (-20°C to 55°C)
Special Features	Linkable (with compatible light sets)

Item Weight	1.76 pounds (approx.)
Package Dimensions	8.74 x 5.75 x 2.6 inches (approx.)

9. WARRANTY AND CUSTOMER SUPPORT

This Enbrighten Vibe Eternity Accent Light Power Supply is backed by a**Limited-Lifetime Warranty**. For detailed warranty information, please refer to the documentation included with your original Eternity Accent Light set or visit the Enbrighten official website.

For technical support, troubleshooting assistance, or warranty claims, please contact Jasco Products Company, LLC, the manufacturer of Enbrighten products. Contact information can typically be found on the Enbrighten website or within the Enbrighten app.

Manufacturer: Jasco Products Company, LLC

Website: byjasco.com/enbrighten (Example link, actual link might vary)