

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Jazmm](#) /

› **Jazmm AM01 Rechargeable AM/FM Radio with Bluetooth User Manual**

Jazmm AM01

Jazmm AM01 Rechargeable AM/FM Radio with Bluetooth User Manual

Model: AM01



INTRODUCTION

This manual provides detailed instructions for the operation and maintenance of your Jazmm AM01 Rechargeable AM/FM Radio with Bluetooth. Please read this manual thoroughly before using the device to ensure proper function and longevity.

WHAT'S IN THE BOX

- Portable Radio x 1
- Owner's Manual x 1
- Back Clip x 1
- USB Type-C Charging Cable x 1



Image: The Jazmm AM01 radio, USB-C cable, and user manual are shown next to the product box.

Your browser does not support the video tag.

Video: This video demonstrates the unboxing of the Jazmm AM01 radio, showing the radio unit, charging cable, and user manual included in the package.

PRODUCT OVERVIEW

The Jazmm AM01 is a compact, multi-functional radio designed for portability and ease of use. It features AM/FM reception, Bluetooth connectivity, a built-in flashlight, and an LCD screen.



Image: Front view of the Jazmm AM01 radio displaying the time and Bluetooth logo, alongside a side view showing the controls and ports.

Controls and Ports

- **Power Button:** Turns the radio on/off.
- **MENU/SCAN Button:** Short press to cycle modes (AM/FM/Bluetooth). Long press for auto-scan in radio mode.
- **TUNING Buttons (Left/Right Arrows):** Adjust frequency in radio mode, navigate menus.
- **MEM/SLEEP Button:** Short press to access preset stations. Long press to set sleep timer.
- **M+/M- Buttons:** Navigate preset stations, adjust time/alarm settings.
- **TIME/AL Button:** Short press to view time. Long press to set time/alarm.
- **LOCK/ST. Button:** Locks buttons to prevent accidental presses.
- **Volume Slider:** Adjusts audio volume.
- **3.5mm Earphone Jack:** For private listening with wired headphones.
- **USB-C Charging Port:** For charging the internal battery.
- **Flashlight:** Integrated LED light.
- **Extendable Antenna:** For improved radio reception.
- **Back Clip:** For attaching the radio to clothing or a bag.

2000mAh Rechargeable Battery

Support charge by car/power bank/wall

Charging with **Type-C**

Charging Time **2-3h**

Using Time **8-25h**



Image: A close-up of the radio's side, highlighting the power button, volume slider, USB-C port, and headphone jack.

Your browser does not support the video tag.

Video: This video demonstrates the radio's display and physical features, including the extendable antenna and back clip.

SETUP

Initial Charging

Before first use, fully charge the radio. Connect the provided USB-C cable to the radio's charging port and the other end to a USB power adapter (not included) or a computer USB port. The battery indicator on the LCD screen will show charging status. A full charge typically takes 2.5-3 hours.

Two types of playback

Loud Clear Speaker



Supports 3.5mm Stereo Headphone Output



Image: The Jazmm AM01 radio is shown connected to a wall charger via its USB-C cable, indicating the charging process.

Your browser does not support the video tag.

Video: This video demonstrates connecting the USB-C charging cable to the radio and a power source, showing the charging indicator on the screen.

OPERATING INSTRUCTIONS

Power On/Off

Press and hold the **Power** button (located on the side) to turn the radio on or off.

AM/FM Radio Mode

1. **Select Mode:** Short press the **MENU/SCAN** button until "FM" or "AM" appears on the display.
2. **Extend Antenna:** For optimal reception, extend the telescopic antenna.
3. **Auto-Scan and Save Presets:** Long press the **MENU/SCAN** button. The radio will automatically scan for available stations and save them as presets (P01, P02, etc.).
4. **Manual Tuning:** Use the **TUNING** buttons (left/right arrows) to manually adjust the frequency.
5. **Access Presets:** Short press the **MEM/SLEEP** button, then use the **M+/M-** buttons to cycle through saved preset stations.
6. **Manually Store Presets:**
 - a. Tune to your desired station using the **TUNING** buttons.
 - b. Long press the **MEM/SCAN** button. The display will show "P01" (or the next available slot).
 - c. Use the **M+/M-** buttons to select the desired preset number.
 - d. Short press the **Power** button to confirm and save the station to the selected preset.

AM FM Radio

Powerful DSP chip and long antenna



Auto Scan



20 Preset Station



Digital Frequency



Image: The Jazmm AM01 radio is shown with its antenna extended, displaying various FM frequencies, illustrating its reception capabilities.

Your browser does not support the video tag.

Video: This video demonstrates how to automatically scan and save preset radio stations on the Jazmm AM01 radio.

Your browser does not support the video tag.

Video: This video illustrates the process of manually storing a radio station as a preset on the Jazmm AM01 radio.

Bluetooth Mode

1. **Activate Bluetooth:** Short press the **MENU/SCAN** button until "bt" appears on the display. The radio is now in Bluetooth pairing mode.
2. **Pair Device:** On your smartphone or other Bluetooth-enabled device, go to Bluetooth settings and search for "AM01". Select it to pair.
3. **Play Audio:** Once paired, audio from your device will play through the radio's speaker.

Note: The radio cannot connect to Bluetooth headphones.

Bluetooth 5.0 Connect

Easily connect and play music



Image: The Jazmm AM01 radio is shown wirelessly connected to a smartphone via Bluetooth, with music playing.

Your browser does not support the video tag.

Video: This video demonstrates how to activate Bluetooth mode on the radio and pair it with a smartphone to play audio.

Using Earphones

Plug any standard 3.5mm wired earphones into the earphone jack on the side of the radio for private listening.



Image: The Jazmm AM01 radio is shown with wired earphones connected to its 3.5mm jack, indicating private listening.

Your browser does not support the video tag.

Video: This video demonstrates plugging 3.5mm earphones into the radio for private audio listening.

Setting the Time

- Enter Time Setting Mode:** Long press the **TIME/AL** button. The hour display will start flashing.
- Adjust Hour:** Use the **TUNING** buttons (left/right arrows) to set the hour.
- Confirm Hour:** Short press the **TIME/AL** button to confirm the hour. The minute display will start flashing.
- Adjust Minute:** Use the **TUNING** buttons (left/right arrows) to set the minute.
- Confirm Minute:** Short press the **TIME/AL** button to confirm the minute.
- Set 12/24 Hour Format:** Use the **TUNING** buttons to select between 12H or 24H format.
- Confirm Format:** Short press the **TIME/AL** button to finalize the time setting.

Your browser does not support the video tag.

Video: This video provides instructions on how to set the current time on the Jazmm AM01 radio.

Setting the Alarm Clock

- Enter Alarm Setting Mode:** Long press the **TIME/AL** button until the alarm icon appears and the hour display flashes.
- Adjust Alarm Hour:** Use the **TUNING** buttons to set the desired alarm hour.
- Confirm Alarm Hour:** Short press the **TIME/AL** button. The minute display will flash.
- Adjust Alarm Minute:** Use the **TUNING** buttons to set the desired alarm minute.
- Confirm Alarm Minute:** Short press the **TIME/AL** button.
- Select Alarm Source:** Use the **TUNING** buttons to choose between FM, AM, or Bluetooth as the alarm sound source.
- Confirm Alarm Source:** Short press the **TIME/AL** button to save the alarm settings.
- Activate/Deactivate Alarm:** Short press the **TIME/AL** button to toggle the alarm on or off. The alarm icon will appear/disappear.

Alarm Clock

5 minutes intervals of snooze time



Sleep Timer

15-30-60-90min auto shutdown



Image: The Jazmm AM01 radio is depicted on a bedside table, illustrating its alarm clock function waking a person, and its sleep timer function for falling asleep.

Your browser does not support the video tag.

Video: This video demonstrates the steps to set the alarm clock function on the Jazmm AM01 radio.

Setting the Sleep Timer

1. **Activate Sleep Timer:** Long press the **MEM/SLEEP** button. The display will show "15" (minutes).
2. **Adjust Duration:** Use the **M+/M-** buttons to select the desired sleep timer duration (15, 30, 60, 90 minutes, or OFF).
3. **Confirm Setting:** The selected duration will flash for a few seconds and then stop, indicating the sleep timer is set. The radio will automatically turn off after the set time.

Your browser does not support the video tag.

Video: This video demonstrates how to set the sleep timer function on the Jazmm AM01 radio, allowing it to automatically shut off after a set duration.

Flashlight Function

The radio includes a built-in LED flashlight. Locate the flashlight button (often integrated with the lock button or a dedicated button on the top/side) and press it to turn the flashlight on or off.

Back Clip & Wrist Strap

Easy to carry outside



Image: The Jazmm AM01 radio is shown emitting light from its built-in LED flashlight in a dark outdoor environment.

Lock Function

To prevent accidental button presses, short press the **LOCK/ST.** button. A lock icon will appear on the display. Press it again to unlock.



Image: A close-up view of the top buttons of the Jazmm AM01 radio, highlighting the 'LOCK/ST.' button and its corresponding lock icon.

MAINTENANCE

- Keep the device dry. Avoid exposure to water or high humidity.
- Clean the radio with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- Store the radio in a cool, dry place when not in use for extended periods.
- Avoid dropping the radio or subjecting it to strong impacts.

TROUBLESHOOTING

Problem	Possible Cause	Solution
No power/Won't turn on	Low battery; Power button not pressed correctly.	Charge the radio fully. Press and hold the power button for a few seconds.
Poor radio reception	Antenna not extended; Weak signal area; Interference.	Fully extend the telescopic antenna. Move to an area with better signal. Avoid electronic devices causing interference.
Bluetooth not connecting	Radio not in Bluetooth mode; Device too far; Already connected to another device.	Ensure radio is in "bt" mode. Keep devices within 10 meters. Disconnect from other devices.
No sound from speaker/earphones	Volume too low; Mute activated; Faulty earphones.	Increase volume using the slider. Check if earphones are properly plugged in. Try different earphones.
Alarm not sounding	Alarm not activated; Alarm time incorrect; Volume too low.	Ensure alarm icon is visible. Verify alarm time settings. Increase volume.

SPECIFICATIONS

- Model Number:** AM01
- Brand:** Jazmm
- Product Dimensions:** 1.4 x 4.7 x 2.7 inches
- Item Weight:** 5.9 ounces
- Battery:** 2000mAh Rechargeable (Nonstandard Battery)
- Charging Time:** Approximately 2.5-3 hours
- Playtime:** Up to 30 hours (varies by usage)
- Tuner Technology:** AM/FM Digital Tuning
- Radio Bands Supported:** 2-Band (AM, FM)
- Connectivity:** Bluetooth 5.0
- Special Features:** Built-in Flashlight, LCD Screen, Earphone Jack, Sleep Timer, Alarm Clock, 20 Preset Stations.

WARRANTY AND SUPPORT

The Jazmm AM01 radio comes with a 12-month warranty from the date of purchase. For warranty claims, technical support, or any

inquiries, please contact Jazmm customer service through the retailer where the product was purchased or visit the official Jazmm store online.

Jazmm Store: [Visit the Jazmm Store](#)

