

EFFORTWAY F-500A

EFFORTWAY F-500A 500W Power Inverter User Manual

Model: F-500A | Brand: EFFORTWAY

INTRODUCTION

Thank you for choosing the EFFORTWAY F-500A 500W Power Inverter. This device converts 12V DC power from your vehicle's battery into 110V AC household power, allowing you to operate various electronic devices on the go. It is designed for convenience and safety during road trips, camping, business travel, or in emergency situations. Please read this manual thoroughly before using the inverter to ensure safe and optimal operation.

WHAT'S IN THE BOX

- 1 x EFFORTWAY F-500A 500W Power Inverter
- 1 x Cigarette Lighter Adapter Cable
- 1 x Pair of Alligator Battery Clamps
- 1 x User Manual

SAFETY INSTRUCTIONS

WARNING: Failure to follow these safety instructions may result in property damage, personal injury, or death.

- **Ventilation:** Ensure adequate ventilation around the inverter. Do not cover the cooling fan or vents.
- **Environment:** Keep the inverter away from water, moisture, flammable materials, and direct sunlight. Operate in a cool, dry environment.
- **Power Limits:** Do not exceed the inverter's continuous power rating (500W) or peak power rating (1000W). Overloading can cause damage to the inverter and connected devices.
- **Cigarette Lighter Limit:** Car cigarette lighter sockets typically output a maximum of 150W. For power demands exceeding 150W, connect the inverter directly to the 12V battery using the provided alligator clamps.
- **Polarity:** Always connect the positive (+) terminal of the inverter to the positive (+) terminal of the battery and the negative (-) terminal of the inverter to the negative (-) terminal of the battery. Reverse polarity connection will trigger

protection and prevent damage.

- **Protection Features:** The inverter includes built-in protections against overload, short circuit, over-voltage, under-voltage, over-temperature, and reverse polarity. If a fault occurs, the inverter will automatically shut off.
- **Modified Sine Wave:** This inverter produces a modified sine wave output. It is suitable for most electronic devices but may not be ideal for sensitive electronics or devices with AC motors (e.g., some medical equipment, power tools with variable speed controls). Consult your device's manual for compatibility.
- **Children:** Keep the inverter out of reach of children.

SETUP

Connecting to a 12V Car Battery (for >150W loads)

1. Ensure the inverter's power switch is in the OFF position.
2. Connect the red alligator clamp cable to the positive (+) terminal of the inverter.
3. Connect the black alligator clamp cable to the negative (-) terminal of the inverter.
4. Connect the red alligator clamp to the positive (+) terminal of your 12V vehicle battery.
5. Connect the black alligator clamp to the negative (-) terminal of your 12V vehicle battery.
6. Ensure all connections are secure and tight.

Connecting to a Car Cigarette Lighter Socket (for <150W loads)

1. Ensure the inverter's power switch is in the OFF position.
2. Connect the cigarette lighter adapter cable to the DC 12V input port on the inverter.
3. Insert the cigarette lighter plug firmly into your vehicle's 12V cigarette lighter socket.



Image: The EFFORTWAY 500W Power Inverter demonstrating dual power modes: connecting via car cigarette lighter for loads under 150W and directly to a 12V battery for loads exceeding 150W.

OPERATING INSTRUCTIONS

1. After making the appropriate power connection (battery or cigarette lighter), turn the inverter's power switch to the ON position. The power indicator light should turn green.
2. Plug your AC-powered devices into the 110V AC outlets.
3. Plug your USB-powered devices into the 5V USB port.
4. Monitor the power consumption of your devices to ensure it does not exceed the inverter's capacity.
5. When finished, turn off the inverter's power switch and disconnect all devices.

500w Fast Charger

Dual independent charging - maximize charging efficiency



USB-A 5V



Outlet plug 110V

Image: Front view of the EFFORTWAY 500W Power Inverter highlighting the USB-A 5V port and the 110V AC outlet for connecting various devices.

Your browser does not support the video tag.

Video: Official product video demonstrating the EFFORTWAY 500W Power Inverter's features and usage, including its DC 12V to AC 110V conversion capabilities.

MAINTENANCE

- **Cleaning:** Keep the inverter clean and free from dust and debris. Use a dry cloth to wipe the exterior.
- **Ventilation:** Regularly check that the cooling fan and vents are clear of obstructions to ensure proper airflow.
- **Connections:** Periodically inspect all connections (battery clamps, cigarette lighter plug) for tightness and corrosion. Clean if necessary.
- **Storage:** Store the inverter in a cool, dry place when not in use.

Inverter Not Powering On

- Check battery connections for tightness and correct polarity.
- Ensure the vehicle's 12V battery has sufficient charge (above 11V).
- Verify the inverter's power switch is in the ON position.

Inverter Shuts Down During Operation

- **Overload Protection:** The connected device(s) may be drawing too much power. Reduce the load to below 500W continuous.
- **Over-Temperature Protection:** The inverter may be overheating due to excessive load or poor ventilation. Allow it to cool down and ensure vents are clear.
- **Under-Voltage Protection:** The input voltage from the battery may have dropped too low. Recharge your vehicle's battery.
- **Short Circuit Protection:** A short circuit may have occurred in the connected device or wiring. Disconnect devices and check for faults.

Multiple Protection

Safeguards your battery and devices so they run securely



overheat protection



under voltage protection



overload protection



over voltage protection



short circuit protection



If your appliance exceeds 150W, please connect the inverter to 12v battery directly. Car cigarette lighter sockets typically only output 150W.

Image: Diagram illustrating the comprehensive safety features of the EFFORTWAY 500W Power Inverter, including overheat, under-voltage, overload, over-voltage, and short circuit protection.

SPECIFICATIONS

Feature	Specification
Brand	EFFORTWAY
Model Number	F-500A
Input Voltage	12 Volts (DC)
Output Voltage	110 Volts (AC)
Continuous Output Power	500 Watts

Peak Output Power	1000 Watts
Electrical Output Waveform	Modified Sine Wave
USB Port	5V, 2.1A
AC Outlets	2
Item Dimensions (L x W x H)	7"L x 4"W x 2"H
Item Weight	0.68 Kilograms
Color	Black

WARRANTY AND SUPPORT

This product comes with a limited warranty. Please refer to the product packaging or contact EFFORTWAY customer support for detailed warranty information and assistance.

For technical support or inquiries, please visit the [EFFORTWAY Store on Amazon](#) or refer to the contact information provided in your product packaging.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Email

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Details

Submit question

