

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Moman](#) /

› [Moman CPX Motorcycle Mesh Intercom User Manual](#)

Moman CPX

Moman CPX Motorcycle Mesh Intercom User Manual

Model: CPX

INTRODUCTION

The Moman CPX Motorcycle Group Mesh Intercom is designed to provide seamless communication and enhanced audio experience for motorcycle riders. This system supports up to 24 riders with dual-mode mesh technology, offering clear communication over a 2KM range. Equipped with advanced AI noise reduction, Bluetooth 5.4, and a durable waterproof design, the CPX ensures a reliable and enjoyable riding experience.

WHAT'S IN THE BOX

Verify that all components are present in your package:

- CPX Mesh Intercom Unit
- Changeable Microphone Speakers (Boom Mic for open-face helmets, Soft Mic for full-face helmets)
- Back Clip (for helmet mounting)
- Back Clip (Stick Style)
- Interchangeable Shells (2 extra colors)
- Charging Cable (USB-C)
- Tape Kit
- Hexagon Key
- User Manual



Image: All components included in the Moman CPX package.

SETUP AND INSTALLATION

Follow these steps to properly install your Moman CPX intercom system onto your helmet.

1. Speaker and Microphone Installation

First, remove the inner lining of your helmet to access the speaker pockets. Securely attach the speaker Velcro pads inside the helmet, ensuring they align with your ears. Repeat this process for both sides. Then, connect the appropriate microphone (boom mic for open-face helmets, soft mic for full-face helmets) to the main unit and position it near the corner of your mouth for clear communication.

Your browser does not support the video tag.

Video: Detailed operating instructions for the Moman CPX, including speaker and microphone installation.

2. Mounting the Main Unit

Choose your preferred mounting method: the clip-on bracket or the adhesive stick-on bracket. Attach the chosen bracket to the side of your helmet. Once the bracket is secure, slide the main CPX intercom unit onto the bracket until it clicks into place. Ensure all cables are neatly tucked away within the helmet lining to avoid discomfort or interference.



Image: Moman CPX intercom unit securely attached to a helmet.

OPERATING INSTRUCTIONS

Power On/Off and Pairing

To power on the device, press and hold the power button for 3 seconds. The device will enter pairing mode, indicated by flashing red and blue lights. To pair with your phone, enable Bluetooth on your phone and select "Moman CPX" from the available devices. Once connected, the blue light will flash slowly.

Intercom Communication (Mesh Technology)

The Moman CPX features dual-mode mesh intercom:

- **Open Mesh Mode:** Connects up to 24 riders seamlessly within a 2KM range.
- **Group Mesh Mode:** Allows for 6 private groups with up to 24 riders each.

One-touch pairing simplifies connecting with other CPX devices. The system supports auto-reconnection if a connection is temporarily lost.



Image: Multiple riders communicating using the Moman CPX mesh intercom system.

Audio Multitasking and Adaptive Volume

The CPX supports simultaneous processing of music playback, navigation prompts, voice assistant, and intercom communication. The exclusive "Intercom Priority" adaptive volume system automatically lowers music levels when intercom is active and restores them afterward, ensuring critical communication is not missed.



Image: Visual representation of audio multitasking and adaptive volume features.

Intuitive Control and Voice Assistant

The glove-friendly oversized knob allows for precise control over music, calls, and voice assistant activation. A built-in FM radio is also available. Activate your phone's voice assistant (e.g., Siri) with a dedicated button press for hands-free control.

Glove-Friendly Knob for Easy & Safe Operation



Image: Close-up of the Moman CPX's large control knob and voice assistant functionality.

KEY FEATURES

Quad AI Noise Cancellation & Hi-Fi Sound

The CPX helmet headset features 40mm high-fidelity speakers for immersive audio. Its four-layer intelligent AI noise reduction system (DSP, CVC, ENC, and a wind-proof microphone) eliminates up to 98% of ambient noise, ensuring crystal-clear audio quality even at speeds of 120 km/h.

AI Noise Reduction & Immersive Hi-Fi

Crystal-clear audio quality even at 120km/h

98%
↓




Image: Illustration of the Moman CPX's quad AI noise cancellation and high-fidelity sound features.

Bluetooth 5.4 Technology

Equipped with BT5.4 technology, the CPX delivers significantly improved pairing efficiency and connection stability, minimizing intercom disconnection issues. This advanced Bluetooth version ensures a smooth and seamless experience throughout your ride.

1s Instant Connect

One-Touch Pairing



Stability Enhance

60% 



Energy Consumption Reduce

80% 



Transmission Rate Increase

100% 



Image: Moman CPX highlighting 1-second instant connect and BT5.4 benefits.

Long-Lasting Battery & IP65 Waterproof

Powered by a 1000mAh high-capacity battery, the CPX provides up to 28 hours of continuous use. With an IP65-rated waterproof and dustproof design, it performs reliably in all weather conditions, standing up to rain, dust, and rugged use.



Image: Moman CPX battery life and IP65 waterproof rating.

MAINTENANCE

To ensure the longevity and optimal performance of your Moman CPX intercom, follow these maintenance guidelines:

- **Cleaning:** Use a soft, damp cloth to wipe the exterior of the intercom unit. Avoid using harsh chemicals or abrasive cleaners.
- **Charging:** Always use the provided USB-C charging cable. Do not use damaged cables or chargers. Ensure the charging port cover is securely closed when not charging to maintain waterproofing.
- **Storage:** Store the device in a cool, dry place away from direct sunlight and extreme temperatures. If storing for extended periods, ensure the battery is partially charged (around 50%) to prevent degradation.
- **Waterproofing:** While IP65 rated, avoid prolonged submersion in water. Ensure all ports and covers are sealed before exposure to water or dust.

TROUBLESHOOTING

If you encounter issues with your Moman CPX, try the following solutions:

- **No Power:** Ensure the device is fully charged. Connect it to the charger and check if the charging indicator light appears.

- **Pairing Issues:**

- Ensure both the CPX and your phone's Bluetooth are enabled and in pairing mode.
- Clear previous Bluetooth pairing records on both devices and attempt to pair again.
- Ensure only CPX devices are being paired together for intercom functionality.

- **Poor Audio Quality:**

- Check microphone and speaker placement inside the helmet to ensure they are correctly positioned.
- Verify that the microphone is not obstructed.
- Adjust volume levels using the control knob.

- **Intercom Disconnection:** Ensure devices are within the 2KM range. The BT5.4 technology provides improved stability, but extreme distances or obstacles can affect connection.

SPECIFICATIONS

Feature	Detail
Model Name	Moman CPX
Connectivity Technology	Wireless (Bluetooth 5.4)
Intercom Type	Group Mesh Intercom (24 Riders, 2KM range)
Noise Control	Quad AI Noise Cancellation (DSP, CVC, ENC)
Audio Driver Type	Dynamic Driver (40mm Hi-Fi Speakers)
Battery Life	Up to 28 Hours
Water Resistance Level	IP65 Waterproof
Control Method	Push Button (Glove-friendly oversized knob)
Item Weight	9.1 ounces
Package Dimensions	7.32 x 4.88 x 1.54 inches

WARRANTY AND SUPPORT

For warranty information, technical support, or service inquiries, please refer to the contact details provided in the included User Manual or visit the official Moman website. Keep your purchase receipt as proof of purchase for warranty claims.