

[Manuals.plus](#) /

› [Savoy House](#) /

› Savoy House Castello Chandelier (Model 1-1237-6-89) Instruction Manual

Savoy House 1-1237-6-89

Savoy House Castello Chandelier Instruction Manual

Model: 1-1237-6-89

1. IMPORTANT SAFETY INFORMATION

Please read and understand all instructions before beginning installation. Failure to follow these instructions may result in electric shock, fire, or other hazards that could cause injury or property damage.

- **Disconnect Power:** Always disconnect power at the main circuit breaker or fuse box before installation, servicing, or cleaning the fixture.
- **Qualified Electrician:** All electrical connections must be made by a qualified, licensed electrician in accordance with local codes, ordinances, and the National Electric Code (NEC).
- **Grounding:** Ensure the fixture is properly grounded to avoid potential electrical shock.
- **Dry Locations Only:** This fixture is ETL/CETL approved for dry locations only. Do not install in damp or wet environments.
- **Handle with Care:** The fixture contains glass components. Handle with care to prevent breakage and injury.
- **Integrated LED:** This fixture uses integrated LED light sources. Do not attempt to replace individual LED components.

2. PACKAGE CONTENTS

Verify that all components are present and undamaged before proceeding with installation. If any parts are missing or damaged, do not attempt to install the fixture. Contact customer support for assistance.

- Chandelier Frame with Integrated LED Lights
- Clear Hammered Glass Shades (6 pieces)
- Ceiling Canopy Assembly
- Mounting Hardware Kit
- Instruction Manual



Figure 1: Overview of the Savoy House Castello Chandelier.

3. SETUP AND INSTALLATION

Professional installation is recommended for this fixture. Ensure power is disconnected at the circuit breaker before starting.

3.1 Preparing for Installation

1. Unpack all components carefully and place them on a clean, soft surface to prevent scratches.
2. Review the parts list to ensure all components are present.
3. Turn off the electricity at the main fuse box or circuit breaker.

3.2 Mounting the Ceiling Canopy

The ceiling canopy provides the structural support and electrical connection point for the chandelier.

1. Attach the mounting bracket to the junction box in the ceiling using the provided screws. Ensure it is securely fastened.
2. Feed the electrical wires from the junction box through the center hole of the mounting bracket.



Figure 2: Detail of the ceiling canopy connection point.

3.3 Electrical Connections

Connect the fixture's wires to the house wires according to standard electrical codes.

1. Connect the **black** wire from the fixture to the **black** (hot) wire from the junction box.
2. Connect the **white** wire from the fixture to the **white** (neutral) wire from the junction box.
3. Connect the **ground** wire from the fixture to the **ground** wire from the junction box (usually bare copper or green).
4. Secure all connections with approved wire connectors.

3.4 Adjusting Hanging Height and Attaching Fixture

The chandelier's height is adjustable from 6 inches to 126 inches.

1. Carefully adjust the length of the hanging cords to achieve the desired height for the chandelier. Ensure all cords are of equal length for a level fixture.
2. Once wiring is complete and cords are adjusted, carefully lift the chandelier frame and secure the ceiling canopy to the mounting bracket using the provided screws.

3.5 Attaching Glass Shades

The clear hammered glass shades are the final components to be installed.

1. Carefully attach each clear hammered glass shade to its designated light source on the chandelier frame. Ensure they are securely fastened but do not overtighten.



Figure 3: Detail of the clear hammered glass shade.

4. OPERATING INSTRUCTIONS

Once installed, the Castello Chandelier is ready for operation.

- **Power On/Off:** Restore power at the main circuit breaker. Operate the chandelier using a standard wall switch connected to the fixture's circuit.
- **Dimming Functionality:** This fixture is dimmable. For optimal performance, use a compatible LED dimmer switch. Consult a qualified electrician if you are unsure about dimmer compatibility.

5. MAINTENANCE

Regular cleaning will help maintain the appearance and performance of your chandelier.

- **Cleaning Glass Shades:** To clean the clear hammered glass shades, turn off the power and allow the fixture to cool. Gently wipe the glass with a soft, damp cloth. Avoid abrasive cleaners or harsh chemicals, as these can damage the finish or glass.
- **Cleaning Metal Finish:** For the Matte Black finish, use a soft, dry cloth to wipe away dust. Do not use liquid or abrasive cleaners.

- **Integrated LED:** The LED light sources are integrated and do not require bulb replacement. If the LEDs malfunction, contact customer support.

6. TROUBLESHOOTING

If you experience issues with your chandelier, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Fixture does not light	No power to fixture; Loose wiring connection; Faulty wall switch.	Check circuit breaker/fuse; Verify all wire connections are secure; Test or replace wall switch.
Lights flicker or dim incorrectly	Incompatible dimmer switch; Loose wiring.	Ensure an LED-compatible dimmer is used; Check wiring connections.
Glass shade is loose	Shade not tightened sufficiently.	Gently tighten the glass shade until secure. Do not overtighten.

7. SPECIFICATIONS

Detailed technical specifications for the Castello Chandelier.



Figure 4: Chandelier dimensions.

Feature	Detail
Model Number	1-1237-6-89
Brand	Savoy House
Dimensions (Fixture)	6" High (Adjustable Height: 6" - 126") x 26.5" Wide
Ceiling Canopy	5.9" x 5.9" x 1.47"
Weight	11.44 lbs.
Number of Lights	6
Bulb Type	Integrated LED
Max Watts Per Bulb	24 Watt
Total Watts	144 Watts
Voltage	120V

Feature	Detail
Color Temperature (K)	3000K
Color Rendering Index (CRI)	90+
Lumens (Source/Delivered)	2400/1990
Dimmable	Yes
Materials	Metal, Clear Hammered Glass
Finish	Matte Black
Safety Rating	ETL/CETL Approved for DRY Locations
UPC	822920318801

8. WARRANTY AND SUPPORT

This Savoy House Castello Chandelier (Model 1-1237-6-89) is covered by a manufacturer's warranty. For specific details regarding warranty coverage, duration, and terms, please refer to the warranty card included with your product or visit the official Savoy House website.

For technical assistance, missing parts, or warranty claims, please contact Savoy House customer support. Have your model number (1-1237-6-89) and proof of purchase ready when contacting support.

Savoy House Customer Support:

Please visit the [Savoy House Store on Amazon](#) or their official website for contact information.