

## YTBDDHYUE 20251208

# YTBDDHYUE Replacement Incandescent Light Fixture

Model: 20251208

Compatible with Globe Electric 44263 (60W, Natural Bronze Vintage Wolfe)

## INTRODUCTION

---

This manual provides essential instructions for the safe installation, operation, and maintenance of your YTBDDHYUE Replacement Incandescent Light Fixture, Model 20251208. Please read this manual thoroughly before installation and retain it for future reference. This product is designed as a replacement for Globe Electric 44263 60W Natural Bronze Vintage Wolfe Incandescent Light Fixtures.

## IMPORTANT SAFETY INSTRUCTIONS

---

**WARNING: Risk of electric shock. Disconnect power at the fuse box or circuit breaker before installation or servicing.**

- Always turn off the main power supply before beginning any electrical work.
- Installation should be performed by a qualified electrician or a person with experience in electrical wiring.
- Ensure all electrical connections are secure and comply with local electrical codes.
- Do not exceed the maximum wattage specified for the light fixture.
- Handle glass components with care to prevent breakage.
- This fixture is intended for indoor use only unless otherwise specified.

## SETUP AND INSTALLATION

---

### 1. Unpacking

Carefully remove all components from the packaging. Inspect the fixture for any damage. Retain packaging materials until you are satisfied with the product.

## 2. Tools Required (Not Included)

- Screwdriver (Phillips and/or Flathead)
- Wire strippers
- Electrical tape
- Pliers
- Voltage tester

## 3. Installation Steps

1. **Turn off Power:** Locate the circuit breaker or fuse box controlling the power to the installation location and turn off the power. Verify power is off using a voltage tester.
2. **Remove Old Fixture:** Carefully disconnect and remove the existing light fixture. Note the wiring connections (typically black to black, white to white, ground to ground).
3. **Mount Mounting Bracket:** Attach the new mounting bracket (if supplied) to the junction box using the provided screws. Ensure it is securely fastened.
4. **Wire Connections:**
  - Connect the **ground wire** (bare copper or green) from the fixture to the ground wire from the junction box.
  - Connect the **white wire** (neutral) from the fixture to the white wire from the junction box.
  - Connect the **black wire** (hot) from the fixture to the black wire from the junction box.
  - Secure all connections with wire nuts and electrical tape.
5. **Attach Fixture:** Carefully tuck the wires into the junction box. Align the fixture with the mounting bracket and secure it with the provided screws or nuts.
6. **Install Bulb:** Screw in an incandescent bulb (max 60W) into the socket. Do not overtighten.
7. **Restore Power:** Turn the power back on at the circuit breaker or fuse box.
8. **Test Fixture:** Turn on the light switch to ensure the fixture is operating correctly.

## OPERATING INSTRUCTIONS

---

Once installed, the light fixture operates via a standard wall switch. Ensure the correct type and wattage of bulb is installed for optimal performance and safety.

### Bulb Replacement

1. **Turn off Power:** Always turn off the power to the fixture at the wall switch and the circuit breaker before replacing a bulb.
2. **Allow to Cool:** Allow the old bulb to cool completely before touching it.
3. **Remove Old Bulb:** Unscrew the old bulb counter-clockwise.
4. **Install New Bulb:** Screw in a new incandescent bulb (max 60W) clockwise until snug. Do not overtighten.
5. **Restore Power:** Turn the power back on at the circuit breaker and wall switch.

## MAINTENANCE

---

### Cleaning

To clean the fixture, ensure the power is off and the fixture is cool. Wipe with a soft, dry or slightly damp

cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.

## Inspection

Periodically inspect the fixture for any signs of wear, loose connections, or damage. If any issues are found, disconnect power and consult a qualified electrician.

## TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on.	No power to the fixture. Loose wire connection. Defective bulb. Faulty wall switch.	Check circuit breaker/fuse. Verify all wire connections are secure (power off). Replace bulb with a known good one. Test wall switch or consult electrician.
Light flickers.	Loose bulb. Loose wire connection. Incorrect bulb type/wattage.	Tighten bulb. Check wire connections (power off). Ensure bulb is incandescent and within 60W limit.
Bulb burns out quickly.	Incorrect bulb wattage (too high). Voltage fluctuations.	Use a bulb within the specified 60W limit. Consult an electrician to check household voltage.

## SPECIFICATIONS

- **Model Number:** 20251208
- **Brand:** YTBDDHYUE
- **Compatibility:** Replacement for Globe Electric 44263
- **Maximum Wattage:** 60W Incandescent
- **Fixture Type:** Incandescent Light Fixture
- **Color/Finish:** Natural Bronze Vintage Wolfe (as per compatible model)
- **Manufacturer:** YTBDDHYUE

## WARRANTY AND SUPPORT

For warranty information or technical support, please contact the manufacturer, YTBDDHYUE, directly. Refer to your purchase documentation for specific contact details or visit the manufacturer's official website. Please have your model number (20251208) and purchase date available when contacting support.