Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

KOVE 812485028659

KOVE Kasita Split Bluetooth Speaker System User Manual

Model: 812485028659

1. Introduction

Welcome to the KOVE Kasita Split Bluetooth Speaker System. This manual provides detailed instructions to help you set up, operate, and maintain your speaker system, ensuring optimal performance and longevity. The Kasita system features dual detachable speakers, offering versatile audio experiences from true stereo separation to immersive 360° surround sound.



Image: The KOVE Kasita speaker system shown in its combined, single unit form.

2. What's Included

Please check the package contents to ensure all items are present:

- Split Speaker (Dual Units)
- Metal Clip
- USB-C to USB-C Charging Cable
- User Manual (this document)
- Speaker Base (for combined unit)
- Carrier Strap



Image: A visual representation of all items included in the KOVE Kasita package, such as the speaker, base, carrier strap, and charging cables.

3. Product Overview

3.1 Speaker Modes

The KOVE Kasita offers two primary configurations:

- **Combined Mode:** The two speaker units are magnetically connected to form a single unit, providing 360° immersive sound.
- **Separated Mode:** The two speaker units are detached, allowing for true left/right stereo separation and wider sound coverage.



Image: The KOVE Kasita speaker system illustrating its ability to function as two separate units for stereo sound or as a single combined unit for 360-degree audio.

3.2 Controls and Ports

Each speaker unit features intuitive controls and essential ports:

- **Power Button:** Press and hold to power on/off.
- **Bluetooth Pairing Button:** Initiates Bluetooth pairing mode.
- **Volume Up/Down Buttons:** Adjusts audio volume.
- **Play/Pause Button:** Controls media playback.
- **LED Light Button:** Toggles or changes LED light effects.
- **USB-C Port:** For charging the speaker.
- **AUX-In Port:** For wired audio connection.
- **Built-in Microphone:** For hands-free calls.

Note: Specific button layouts may vary slightly between units. Refer to the physical product for exact button locations.

4. Setup

4.1 Charging the Speakers

1. Connect the provided USB-C charging cable to the USB-C port on each speaker unit.
2. Connect the other end of the cable to a compatible USB power adapter (not included).
3. The LED indicator will show charging status and turn off when fully charged. A full charge takes approximately 4 hours.

4.2 Powering On/Off

- To power on, press and hold the Power button on each speaker until the LED indicator lights up.
- To power off, press and hold the Power button on each speaker until the LED indicator turns off.

4.3 Bluetooth Pairing

1. Ensure both speaker units are powered on and detached from each other.
2. On one speaker, press and hold the Bluetooth pairing button until the LED indicator flashes rapidly, indicating pairing mode.
3. On your device (smartphone, tablet, etc.), enable Bluetooth and search for "KOVE Kasita".
4. Select "KOVE Kasita" from the list of available devices to connect.
5. Once connected, the LED indicator on the speaker will stop flashing and remain solid.
6. The second speaker will automatically connect to the first speaker, establishing a stereo pair.

Note: For optimal stereo sound, place the two speakers within 30 meters (66 feet) of each other and your Bluetooth device.

5. Operating Instructions

5.1 Audio Playback

- **Play/Pause:** Press the Play/Pause button once.
- **Volume Control:** Use the Volume Up (+) and Volume Down (-) buttons.
- **Next Track:** Double-press the Volume Up (+) button.
- **Previous Track:** Double-press the Volume Down (-) button.

5.2 Hands-Free Calling

When connected via Bluetooth, the built-in microphone allows for hands-free calls.

- **Answer Call:** Press the Play/Pause button once.
- **End Call:** Press the Play/Pause button once during a call.
- **Reject Call:** Press and hold the Play/Pause button.

5.3 LED Light Effects

The Kasita speaker features colorful LED light effects to enhance your listening experience.

- Press the LED Light button to cycle through different light modes or turn them off.

5.4 AUX Input

For wired audio connection, use a 3.5mm AUX cable (not included) to connect your device to the AUX-In port on one of the speakers. The speaker will automatically switch to AUX mode.

5.5 USB Playback

Insert a USB drive with audio files into the USB port for direct playback. The speaker will automatically detect and play the audio files.



Image: The KOVE Kasita speaker highlighting its versatile features including AUX input, USB playback, built-in microphone, LED light effects, and voice assistant compatibility.

6. Multi-Speaker Synchronization

The KOVE Kasita system supports syncing up to 100 KOVE Bluetooth speakers for an expansive audio experience. This feature is ideal for large gatherings or multi-room audio setups.

1. Ensure all KOVE speakers you wish to sync are powered on and within range.
2. Pair your primary Kasita speaker (or one of the two units) with your Bluetooth device as described in Section 4.3.
3. On the primary speaker, initiate the multi-sync mode (refer to specific button combination in your quick start

guide, typically a dedicated sync button or a long press of the Bluetooth button after initial pairing).

4. On each additional KOVE speaker, activate its multi-sync mode. The speakers will automatically detect and connect to the primary speaker.
5. Once connected, all synced speakers will play audio from your device simultaneously.



Image: An illustration demonstrating the multi-room speaker system capability, where multiple KOVE Kasita speakers can be wirelessly synced for expanded audio coverage.

Your browser does not support the video tag.

Video: Official product video demonstrating the features and usage of the KOVE Kasita Split Bluetooth Speaker System, including its multi-speaker connection capabilities.

7. Maintenance

7.1 Cleaning

- Wipe the speaker's exterior with a soft, damp cloth.
- Do not use abrasive cleaners, alcohol, or chemical solvents.

- Ensure all ports are dry before charging or connecting cables.

7.2 Water Resistance (IPX6)

The KOVE Kasita speaker is IPX6 water-resistant, meaning it can withstand powerful water jets. It is suitable for use near pools or in rainy conditions, but it is not designed to be submerged in water.

- Do not submerge the speaker in water.
- Ensure the charging port cover is securely closed when exposed to water.
- If the speaker gets wet, dry it thoroughly before charging.



Image: The KOVE Kasita speaker on a surfboard, illustrating its splash-proof and adventure-ready design with IPX6 water resistance.

8. Troubleshooting

Problem	Possible Cause	Solution

Problem	Possible Cause	Solution
Speaker does not power on.	Low battery; Power button not held long enough.	Charge the speaker for at least 30 minutes. Press and hold the Power button for 3-5 seconds.
Cannot pair via Bluetooth.	Speaker not in pairing mode; Device Bluetooth off; Too far from device.	Ensure speaker LED is flashing rapidly. Turn Bluetooth off/on on your device. Move speaker closer to device (within 30m).
No sound or low volume.	Volume too low on speaker or device; Speaker not connected.	Increase volume on both speaker and connected device. Re-establish Bluetooth connection.
Speakers not syncing in stereo mode.	One speaker not in pairing mode; Speakers too far apart.	Ensure both speakers are powered on and detached. Follow Bluetooth pairing steps carefully to ensure they connect as a stereo pair. Move speakers closer.
Multi-speaker sync not working.	Incorrect sync procedure; Speakers out of range.	Review Section 6 for multi-speaker sync instructions. Ensure all speakers are within effective range of the primary speaker.

9. Specifications

Feature	Detail
Brand	KOVE
Model Name	Kasita
Model Number	812485028659
Speaker Maximum Output Power	70 watts (25W x2 + 10W x2)
Frequency Response	20 KHz (upper limit, typical for full range)
Connectivity Technology	Bluetooth 5.4
Audio Output Mode	Stereo, Surround
Speaker Type	Split, Surround
Color	Concrete
Water Resistance	IPX6
Maximum Bluetooth Range	30 meters (66 feet)
Control Method	Touch, Voice (Voice Assistant Compatible)
Specific Uses For Product	Outdoor, Travel, Home Audio, Parties
Battery Average Life	Up to 9 hours (at 50% volume)
Battery Capacity	Dual 4000 mAh rechargeable batteries
Battery Charge Time	Approximately 4 hours

Feature	Detail
Item Dimensions (D x W x H)	12"D x 6"W x 6"H (combined)
Compatible Devices	Smartphone, Tablet, other Bluetooth-enabled devices
Power Source	Battery Powered
Audio Driver Type	Dynamic Driver
Built-In Media	AUX, USB Playback, Microphone
Number of Audio Channels	2 (for stereo separation)

10. Warranty & Support

10.1 Product Warranty

The KOVE Kasita Split Bluetooth Speaker System comes with a**one-year limited warranty** from the date of purchase. This warranty covers manufacturing defects in materials and workmanship under normal use. It does not cover damage caused by misuse, accidents, unauthorized modifications, or normal wear and tear.
For warranty claims, please retain your proof of purchase.

10.2 Customer Support

If you encounter any issues or have questions not addressed in this manual, please contact KOVE customer support. You can typically find contact information on the KOVE official website or through your retailer's support channels.
For further assistance, please visit the KOVE Store on Amazon.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0GBTFZ392

More documents and user manuals: **https://manuals.plus/**