



Manuals.plus /

- › Bextgoo /
- › Bextgoo SW06B3XL 4K Mini Security Camera User Manual

## Bextgoo SW06B3XL

# Bextgoo 4K Mini Security Camera

MODEL: SW06B3XL USER MANUAL

|          |          |       |           |                |                 |             |          |  |
|----------|----------|-------|-----------|----------------|-----------------|-------------|----------|--|
|          |          |       |           | Introduction   | Package         |             |          |  |
| Contents | Features | Setup | Operation | Specifications | Troubleshooting | Maintenance | Warranty |  |
|          |          |       |           | & Support      |                 |             |          |  |

## 1. Introduction

Thank you for choosing the Bextgoo SW06B3XL 4K Mini Security Camera. This compact and versatile camera is designed for various surveillance needs, offering 4K video resolution, advanced night vision, and flexible connectivity options. Please read this manual carefully before use to ensure proper setup and operation.

## 2. Package Contents

Verify that all items are present in your package:

- 1 x Bextgoo SW06B3XL Mini Security Camera
- 1 x 64GB TF Memory Card (pre-installed)
- 1 x Adjustable Mounting Bracket
- 1 x USB Charging Cable
- 1 x User Manual
- Adhesive Pads (for mounting)

## 3. Product Features

- **Flexible 3-Way Connection Modes:** Supports WiFi for remote viewing, Hotspot for direct local connection without internet, and Offline recording to the SD card.

- **4K Ultra HD Video:** Captures clear and detailed 4K resolution video with a 150° wide-angle lens, minimizing blind spots.
- **Superior Night Vision:** Equipped with 5 invisible 940nm infrared lights, providing clear night vision up to 10 meters in complete darkness without a visible red glow.
- **Motion Detection & Alerts:** Sends instant motion detection notifications to your phone in WiFi mode, enhancing security.
- **Long-Lasting Battery & Storage:** Features a 1500mAh rechargeable battery for up to 6 hours of use, capable of recording while charging. Includes a pre-installed 64GB TF card, expandable up to 128GB.
- **Compact & Lightweight Design:** Small dimensions (5cm x 5cm x 2.8cm) make it easy to conceal and carry.
- **Versatile Mounting Options:** Can be placed on a desk or mounted on walls, ceilings, or flat surfaces using the included adjustable bracket or adhesive pads.
- **All-in-One App Control:** Manage video recording, screenshots, night vision settings, motion detection, real-time notifications, and multi-user access directly from your smartphone app.

## 4. Product Overview

---

Familiarize yourself with the camera's components and features.



Image: The Bextgoo SW06B3XL camera, highlighting its compact dimensions of 5cm length, 5cm width, and 2.8cm height, demonstrating its mini size compared to a human hand.



Image: The camera with a 64GB TF card inserted, illustrating its built-in storage and the option for cloud storage (optional) and expansion up to 128GB.

## 5. Setup Guide

---

### 5.1. Charging the Camera

Before first use, fully charge the camera. Connect the camera to a 5V/1A USB power adapter using the provided USB cable. The charging indicator light will show the charging status. A full charge typically takes 2-3 hours. The camera can operate while charging.



Image: Visual representation of the camera's 1500mAh battery capacity, emphasizing its suitability for long shifts and 24/7 surveillance by working while charging.

### 5.2. Inserting/Checking the TF Card

The camera comes with a 64GB TF card pre-installed. If you need to replace or upgrade it, ensure the camera is powered off. Gently insert or remove the TF card into the designated slot until it clicks into place. The camera supports up to 128GB TF cards.

### 5.3. Connection Modes

The Bextgoo SW06B3XL offers three flexible connection modes:

- **WiFi Mode:** For remote viewing via the dedicated app from anywhere with internet access. Ideal for

home security, baby, or pet surveillance.

- **Hotspot Mode:** Connect directly to the camera's built-in hotspot without an internet connection. Suitable for nearby viewing in garages, outdoor spots, or during travel.
- **Offline Mode:** Records directly to the SD card without any WiFi or internet connection. Perfect for remote areas or situations where network access is unavailable.

Refer to the app's instructions for detailed steps on connecting to WiFi or Hotspot modes.



Image: An infographic detailing the three smart connection modes: WiFi for remote viewing, Hotspot for direct connection, and Offline for SD card recording without internet.

## 6. Operation

---

### 6.1. App Control

Download the dedicated mobile application (refer to the manual for app name and QR code) to control your camera. The app allows you to:

- View live video feed
- Initiate video recording and take screenshots
- Enable/disable night vision
- Configure motion detection settings and receive real-time notifications
- Access recorded footage
- Manage multi-user access



Image: A smartphone displaying the camera's app interface, illustrating various control options such as video recording, screenshot, night vision, motion detection, real-time notifications, and multi-user access.

### 6.2. Video Recording

The camera records in 4K resolution. Recording can be initiated manually via the app or automatically triggered by motion detection. In Offline Mode, recording starts automatically when the camera is powered on.

### 6.3. Night Vision

The camera's invisible 940nm IR lights provide clear night vision up to 10 meters. Night vision can be activated automatically in low light conditions or manually through the app.



Image: A comparison demonstrating the superior clarity and invisibility of the Bextgoo camera's 940nm IR night vision compared to standard IR cameras, showing clear images in total darkness.

### 6.4. Motion Detection

When motion detection is enabled (in WiFi mode), the camera will automatically start recording and send instant notifications to your connected smartphone. Adjust sensitivity settings within the app.

## 7. Mounting Options

---

The Bextgoo SW06B3XL camera offers versatile mounting solutions:

- **Desktop Placement:** Simply place the camera on any flat surface.
- **Wall Mounting:** Use the adjustable bracket and screws (not included, but bracket is) or adhesive pads to secure it to a wall.
- **Ceiling Mounting:** Attach the camera to the ceiling using the adjustable bracket.
- **Adhesive Mounting:** Utilize the strong adhesive pads for quick and drill-free installation on various flat surfaces.



Image: A visual guide demonstrating four smart mounting options for the camera, including placement on a desk, wall, and ceiling, highlighting its adaptability without requiring drilling.

## 8. Specifications

|                         |  |
|-------------------------|--|
| <b>Model Number</b>     | SW06B3XL                                       |
| <b>Video Resolution</b> | 4K Ultra HD                                    |
| <b>Lens Angle</b>       | 150° Wide Angle                                |
| <b>Night Vision</b>     | 5 x 940nm Invisible IR LEDs, up to 10m         |
| <b>Battery Capacity</b> | 1500mAh Rechargeable Lithium Polymer           |
| <b>Battery Life</b>     | Up to 6 hours (continuous recording)           |
| <b>Storage</b>          | 64GB TF Card (integrated), expandable to 128GB |
| <b>Connectivity</b>     | WiFi, AP Hotspot, Offline Recording            |
| <b>Dimensions</b>       | Approx. 5cm x 5cm x 2.8cm                      |
| <b>Weight</b>           | Approx. 138g                                   |
| <b>Color</b>            | Grey   |

## 9. Troubleshooting

- **Camera not turning on:** Ensure the battery is charged. Connect to a power source and try again.
- **Cannot connect to WiFi/Hotspot:** Ensure the camera is within range. Double-check network credentials. Try resetting the camera and your router.
- **No recording:** Check if the TF card is properly inserted and has sufficient space. Ensure the camera is powered on and in a recording mode.
- **Poor video quality:** Ensure the lens is clean. Check lighting conditions. For 4K recording, ensure adequate light.
- **Night vision not working:** Ensure night vision is enabled in the app or that ambient light is low enough for automatic activation.
- **App issues:** Ensure your app is updated to the latest version. Restart the app or your phone.

## 10. Maintenance

- **Cleaning:** Use a soft, dry cloth to clean the camera lens and body. Avoid abrasive cleaners or

solvents.

- **Storage:** Store the camera in a cool, dry place away from direct sunlight and extreme temperatures.
- **Battery Care:** For optimal battery life, avoid fully discharging the battery frequently. Charge regularly, even if not in use for extended periods.
- **Firmware Updates:** Check the app periodically for any available firmware updates to ensure optimal performance and new features.

## 11. Warranty & Support

---

The Bextgoo SW06B3XL Mini Security Camera comes with a standard manufacturer's warranty. Please refer to the warranty card included in your package or contact Bextgoo customer support for specific details regarding warranty coverage and service.

For technical support, troubleshooting assistance, or any product-related inquiries, please contact Bextgoo customer service through the contact information provided on the product packaging or the official Bextgoo website.