

LEMEGA IR6

LEMEGA IR6 Internet Radio User Manual

Model: IR6 | Brand: LEMEGA

1. INTRODUCTION

The LEMEGA IR6 is a versatile internet radio designed to provide a rich audio experience. It features access to over 50,000 internet radio stations and podcasts, FM radio, Bluetooth streaming, and an alarm clock function. Its premium wooden cabinet, dual speakers, and rechargeable battery offer both quality sound and portability for use in various settings.

2. WHAT'S IN THE BOX

- LEMEGA IR6 Internet Radio Unit
- Owner's Manual
- Power Adapter

3. PRODUCT OVERVIEW

Familiarize yourself with the main components and controls of your LEMEGA IR6 Internet Radio.



Figure 3.1: Front view of the LEMEGA IR6 Internet Radio.

The front panel features a color display, control knobs, and buttons for navigation and function selection. The unit is equipped with dual speakers for stereo sound and an extendable antenna for FM reception. A sturdy aluminum handle allows for easy portability.



Figure 3.2: Close-up of the control panel and display.

4. SETUP

4.1 Powering On

Connect the provided power adapter to the DC IN port on the back of the radio and plug it into a wall outlet. Alternatively, the built-in rechargeable battery provides over 10 hours of playtime for portable use. Press the Power button to turn the unit on.

4.2 Initial Setup Wizard

Upon first use, the radio will guide you through an initial setup wizard:

1. **Language Selection:** Use the navigation knob to select your preferred language and press the knob to confirm.
2. **Time and Date:** Set the current time and date. This can often be automatically updated via the internet connection.

3. **Network Connection (Wi-Fi):** The radio requires a Wi-Fi connection for Internet Radio and Podcast features.

4.3 Wi-Fi Connection

To connect to your Wi-Fi network:

1. Select 'Network Wizard' from the menu or during initial setup.
2. The radio will scan for available Wi-Fi networks.
3. Select your network from the list.
4. Enter your Wi-Fi password using the navigation knob to select characters and confirm.
5. Once connected, the Wi-Fi icon will appear on the display.

5. OPERATING INSTRUCTIONS

5.1 Mode Selection

Press the **Mode** button to cycle through available modes: Internet Radio, FM Radio, Bluetooth Audio, and AUX-In.

5.2 Internet Radio & Podcasts

Access thousands of global radio stations and podcasts.



Figure 5.1: Internet Radio mode in a kitchen setting.

In Internet Radio mode, you can browse stations by country, genre, or popularity. Use the navigation knob to scroll through lists and press to select. For podcasts, navigate to the podcast section to search and play episodes.

Your browser does not support the video tag.

Video 5.1: An overview of the LEMEGA IR6 Internet Radio's features and functionality.

5.3 FM Radio

For local and national broadcasts, switch to FM Radio mode. Extend the telescopic antenna for optimal reception.

- **Auto Scan:** Press the 'Scan' button (if available) or navigate through the menu to perform an auto scan for available FM stations.
- **Manual Tuning:** Use the navigation knob to manually tune to specific frequencies.

5.4 Presets

The IR6 supports up to 150 presets across all radio modes. To save a station, tune to the desired station, then press

and hold the 'Presets' button until the 'Save Preset' option appears. Select a preset number and confirm. To recall a preset, briefly press the 'Presets' button and select from your saved list.

5.5 Bluetooth Streaming

Stream audio wirelessly from your smartphone, tablet, or other Bluetooth-enabled devices.

- Switch the radio to Bluetooth mode. The display will show 'Bluetooth Pairing'.
- On your device, enable Bluetooth and search for 'LEMEGA IR6'.
- Select 'LEMEGA IR6' to pair. Once connected, you can play audio from your device through the radio.

5.6 AUX-In

Connect external audio sources like MP3 players or older devices using a 3.5mm audio cable (not included) to the AUX-In port.

- Switch the radio to AUX-In mode.
- Connect your external device to the AUX-In port.
- Control playback from your external device.

5.7 Alarm Clock & Sleep Timer

The IR6 includes an alarm clock and sleep timer function.



Figure 5.2: Alarm clock function on the LEMEGA IR6.

- **Setting Alarms:** Press the 'Alarm' button to access alarm settings. You can set multiple alarms, choosing to wake to Internet Radio, FM, or a buzzer.
- **Snooze:** When an alarm sounds, press any button (except Power) to activate snooze.
- **Sleep Timer:** Press the 'Sleep' button to set a timer for the radio to automatically turn off after a specified duration.

5.8 Sound Settings

The LEMEGA IR6 features true 2.0 stereo sound with dual speakers, delivering clear vocals and balanced audio. While specific bass/treble controls are not detailed, general volume is adjusted via the main knob.



Figure 5.3: Internal speaker components illustrating 2.0 stereo sound.

6. MAINTENANCE

6.1 Cleaning

To clean the radio, use a soft, dry cloth. Do not use abrasive cleaners, waxes, or solvents as they may damage the finish. Ensure the unit is powered off and unplugged before cleaning.

6.2 Battery Care

The IR6 features a built-in rechargeable lithium battery. For optimal battery life:

- Avoid fully discharging the battery frequently.
- Charge the battery using the provided USB-C port and power adapter.
- If storing the unit for an extended period, charge the battery to approximately 50% and store in a cool, dry place.

7. TROUBLESHOOTING

If you encounter issues with your LEMEGA IR6, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
No power	Power adapter not connected, battery drained.	Ensure power adapter is securely connected and plugged in. Charge the battery if using portable mode.
No sound	Volume too low, mute activated, incorrect mode.	Increase volume. Check if mute is active. Ensure correct mode (Internet Radio, FM, Bluetooth, AUX-In) is selected.
Cannot connect to Wi-Fi	Incorrect password, out of range, network issue.	Verify Wi-Fi password. Move radio closer to router. Restart router.
Poor FM reception	Antenna not extended, weak signal.	Fully extend the telescopic antenna. Reposition the radio for better signal.
Bluetooth pairing issues	Device not in pairing mode, radio not discoverable.	Ensure both devices are in pairing mode. Check if the radio is in Bluetooth mode. Forget previous pairings on your device and try again.

If the problem persists after trying these solutions, please contact customer support.

8. SPECIFICATIONS

Feature	Detail
Brand	LEMEGA
Model Number	IR6
Product Dimensions (L x W x H)	10.2" x 4" x 5.5"
Connectivity Technology	Auxiliary, Bluetooth, Wi-Fi
Tuner Technology	Internet Radio, FM
Power Source	Battery Powered and Mains
Radio Bands Supported	3-Band (Internet, FM, DAB+)
Audio Output Mode	Stereo
Special Feature	Rechargeable Battery, Podcasts, Alarm Clock, 150 Presets, Premium Wooden Cabinet
Display Type	Color Display

9. WARRANTY INFORMATION

The LEMEGA IR6 Internet Radio comes with a Limited Warranty. For detailed information regarding the terms and conditions of your warranty, please refer to the warranty card included with your product packaging or visit the official LEMEGA website.

10. CUSTOMER SUPPORT

For further assistance, technical support, or inquiries not covered in this manual, please contact LEMEGA customer support through their official website or the contact information provided in your product documentation.

© 2026 LEMEGA. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question