

adorcam G3

adorcam Wireless Window Camera G3 Instruction Manual

Model: G3

1. INTRODUCTION

The adorcaml Wireless Window Camera G3 is designed for indoor security monitoring, offering a wire-free solution with a long-lasting battery and easy installation. This manual provides detailed instructions for setting up, operating, and maintaining your camera.

1.1 What's in the Box

- 1 x adorcaml Wireless Window Camera
- 1 x USB-C Charging Cable
- 2 x Magnetic Mounts with Washable Adhesive
- 1 x Quick Start Guide

1.2 Key Features

- **4MP Ultra HD Resolution:** Provides clear video footage.
- **45-Day Battery Life:** Integrated 4000mAh battery for extended wireless operation.
- **105° Wide-Angle View:** Captures a broad area with reduced glare.
- **Full-Color Night Vision:** Offers clear visibility in low-light conditions.
- **AI Person Detection:** Minimizes false alerts by focusing on human movement.
- **Two-Way Audio:** Allows for communication through the camera.
- **Dual Storage:** Supports local microSD card (up to 256GB) and optional cloud storage.
- **Magnetic Mount:** Tool-free installation on glass surfaces.

#1 Wireless Window Camera **Adorcam**

Wireless Peace of Mind for Every Renter.



1s
1s Magnetic Mount | 0 Drill Holes
Secure Your Deposit

+4000
45-Day Battery (4000mAh)
No Outlet, No Mess

105°
105° View | 90% Less Glare
See Wider & Clearer

4MP
4MP Full-Color Night Vision
Clear, Day & Night

AI Person Detection
80% Less False Alerts

Dual Storage | 256GB Local
+ 30-Day Free Cloud
Evidence is 100% Secure

Image 1.1: The adorcam Wireless Window Camera G3 highlighting its main features.

2. SETUP

2.1 Charging the Camera

Before initial use, fully charge the camera using the provided USB-C cable and a standard 5V/1A USB power adapter (not included). The charging indicator light will show the charging status.

2.2 App Download and Account Creation

Download the 'Adorbee' app from the Apple App Store (for iOS devices) or Google Play Store (for Android devices). Follow the in-app instructions to create an account and log in.

2.3 Camera Pairing

1. Open the 'Adorbee' app and tap 'Add Device' or the '+' icon.

2. Select your camera model from the list.
3. Follow the on-screen prompts to connect the camera to your 2.4GHz Wi-Fi network. Ensure your phone is connected to the same 2.4GHz Wi-Fi network during setup.
4. Scan the QR code displayed on your phone screen with the camera lens. A voice prompt will confirm successful pairing.

2.4 Installation

The adorcam G3 features a magnetic mount for easy, drill-free installation on windows or glass surfaces.

1. **Clean:** Wipe the window glass thoroughly to ensure it is clean and dry.
2. **Stick:** Peel the protective film from the adhesive side of the magnetic mount and press it firmly onto the desired location on the window.
3. **Snap:** Attach the camera magnetically to the mount. Ensure the camera lens faces outwards for optimal viewing.

INSTALLS IN JUST 1 MINUTE



**STEP 1:
CLEAN**
Wipe window
glass



**STEP 2:
STICK**
Press mount
firmly



**STEP 3:
SNAP**
Camera attaches
magnetically

0:00 → 0:20 → 0:40 → 1:00

#1
Wireless
Window
Camera



 **Strong Magnetic Mount**
Secure hold.

 **45-Day Wireless**
4000mAh battery.

 **Share with 4 Users**
Family access.

 **Washable Sticker**
No residue.

 **One-Tap Bluetooth**
Easy setup.

**No tools. No drilling. No wires.
Perfect for renters & easy DIY.**

 10,000+ Happy Customers

Image 2.1: Visual guide for the 3-step installation process.

Traditional Wired Cameras: Risks & Inconvenience



- ⚠️ **Tripping Hazard** - Pets & kids can easily trip over wires
- ⚠️ **Messy Wires** - Exposed wires look messy and collect dust
- ⚠️ **Installation Hassle** - Requires outlet, limited placement



From Problem → To Solution

**Why Risk It?
Choose Safe & Wireless.**

Adorcam Wireless Window Camera: Safe Home Monitoring



- ✅ **Safe & Tidy** - No wires, eliminates tripping risks
- ✅ **Easy Peel & Stick** - Install in 1 minute, no tools needed
- ✅ **Perfect Placement** - Mounts high on glass, out of reach

Ideal for:
Pet Owners, Families with Kids, Elderly Care

Adorcam Window Camera Features:

- 🔋 45-Day Wireless
- 🌀 Easy Window Mount
- 📱 Remote Monitoring
- 👁️ Discreet Design

adorcam | True Wireless Window Camera, Safe for Every Family Member

Image 2.2: Comparison of a wireless window camera setup versus a traditional wired camera setup.

3. OPERATING INSTRUCTIONS

Once installed and paired, you can access and control your adorcam G3 through the 'Adorbee' app.

3.1 Live View

Open the 'Adorbee' app and select your camera from the device list to access the live video feed. You can view real-time footage from your window.

3.2 Motion Detection and Alerts

The camera utilizes AI Person Detection to identify human figures, reducing false alarms from pets or environmental factors. When motion is detected, the camera records a video clip and sends an instant alert to your smartphone. You can adjust motion sensitivity and detection zones within the app settings.

3.3 Night Vision

The adorcam G3 features 4MP Full-Color Night Vision, providing clear and detailed images even in low-light conditions without visible infrared LEDs.

3.4 Two-Way Audio

Use the two-way audio feature in the app to listen to the environment around the camera or speak through the camera's built-in speaker.

3.5 Storage Options

The camera supports two storage methods for recorded events:

- **Local Storage:** Insert a microSD card (up to 256GB, sold separately) into the camera's slot for local recording. This option does not require a subscription.
- **Cloud Storage:** A 30-day free trial of cloud storage is included. After the trial, a subscription is required for cloud backup. Cloud storage ensures your video evidence is secure even if the camera is physically compromised.

Why Choose Adorcam Wireless Window Camera?

A Visual Comparison of Core Advantages



Traditional Indoor Wired Camera	Adorcam Wireless Window
 1080P or lower Blurry details	 4MP Ultra HD 4X Clearer details
 Must be wired Limited by outlets	 45 Days Wireless 0 Wires, Free installation
 B&W Night Vision Visible IR LEDs	 Color Night Vision Non-intrusive, no red glow
 Ordinary Motion Detection Frequent false alarms	 AI Human Detection Up to 80% Less false alerts
 Drill Fixing Damages walls	 1-Second Magnetic 0 Damage, Reusable, washable
 Single Storage Risk of data loss	 Dual Backup Local + 30-Day Free Cloud

✔ 4X Clearer | ✔ 45-Day Wireless | ✔ 80% Less False Alerts

✔ 0 Wires | ✔ 0 Damage | ✔ Dual Backup

Designed for: Renters • Families • Nature Lovers • Privacy Advocates

adorcam

Adorcam Wireless Window Camera.
The Clear & Considerate Upgrade.

Image 3.1: The Adorbee app interface displaying live camera feed and control options.

BEFORE



One Copy, One Point of Failure.

Risk of data loss from
damage or theft.

AFTER



Dual Storage Insurance. Your Evidence is Always Safe.



Local SD Card Backup

256GB Support

Card not included



Cloud Backup Encrypted Storage

30-Day Free Trial

Image 3.2: Explanation of the dual storage feature, combining local microSD and cloud backup.

Your Window to Wonder.



Plant Watch
Wireless. Limitless.
Observe growth, anywhere.



Baby Watch
Gentle Nights. Full Color.
Watch them sleep, undisturbed.



Bird Watch
Secret & Silent.
Capture wild moments.

Designed for the Curious & Kind.



Easy On & Off
No tools. No trace.



Truly Wireless
45-day power. Go anywhere.



Respectful Vision
No-IR night mode. Full color.

Adorcam. More Than Security. | Adorcam True Wireless Window Camera | Discover the unseen life at your window.

Image 3.3: Examples of camera usage for monitoring plants, babies, and outdoor wildlife.

4. MAINTENANCE

4.1 Battery Charging

The camera's 4000mAh battery provides approximately 45 days of usage based on 100 events per day. When the battery level is low, the app will notify you. Recharge the camera using the provided USB-C cable.

4.2 Cleaning

To maintain optimal performance, periodically clean the camera lens and body with a soft, dry cloth. Avoid using harsh chemicals or abrasive materials.

4.3 Magnetic Mount Care

The washable adhesive on the magnetic mount can be cleaned with water to restore its stickiness if it becomes dirty. Ensure it is completely dry before re-applying.

5. TROUBLESHOOTING

5.1 Common Issues and Solutions

- **Camera not connecting to Wi-Fi:**
 - Ensure your Wi-Fi network is 2.4GHz. The camera does not support 5GHz Wi-Fi.
 - Verify the Wi-Fi password is correct.
 - Move the camera closer to your Wi-Fi router during setup.
 - Reset the camera (refer to the Quick Start Guide for reset instructions) and attempt pairing again.
- **Short battery life:**
 - Frequent motion detection events or continuous live viewing can reduce battery life. Adjust motion sensitivity settings in the app.
 - Ensure the camera is fully charged.
- **False motion alerts:**
 - Adjust the motion detection sensitivity in the app.
 - Define specific detection zones to exclude areas with frequent non-human movement.
- **Poor image quality:**
 - Ensure the camera lens and the window glass are clean.
 - Check your Wi-Fi signal strength; a weak signal can affect streaming quality.

5.2 Why is the camera designed for indoor installation only?

The adorcam Wireless Window Camera is designed for indoor installation, looking outwards through a window. It is not weatherproof and should not be exposed to outdoor elements. Installing it indoors protects it from theft, weather damage, and potential privacy concerns with neighbors, while also preventing damage to exterior walls.

Why can't installed outdoors?



Image 5.1: Illustration of reasons for indoor-only installation.

6. SPECIFICATIONS

Feature	Specification
Model Name	Window Camera with Battery for Indoor (G3)
Resolution	4MP (2560x1440)
Field of View	105 Degrees
Battery Capacity	4000mAh
Battery Life	Up to 45 days (based on 100 events/day)
Connectivity	2.4GHz Wi-Fi

Feature	Specification
Night Vision	Full-Color Night Vision
Audio	Two-Way Audio
Storage	MicroSD card (up to 256GB), Cloud Storage (optional subscription)
Motion Detection	AI Person Detection
App Compatibility	Adorbee App (iOS/Android)
Mount Type	Magnetic Window Mount
Color	White
Dimensions	0.21 x 0.1 x 0.21 inches (approximate)
Weight	0.32 Pounds (approximate)

7. WARRANTY AND SUPPORT

7.1 Product Warranty

The adorcaml Wireless Window Camera G3 comes with a 2-year manufacturer's warranty. Please retain your proof of purchase for warranty claims.

7.2 Technical Support

For technical assistance, troubleshooting, or warranty inquiries, please contact adorcaml customer support through the contact information provided in your Quick Start Guide or on the official adorcaml website.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question