



[Manuals.plus](#) /

› [McGrey](#) /

› [McGrey MOVE Compact PA Speaker User Manual](#)

McGrey MOVE Compact

McGrey MOVE Compact PA Speaker User Manual

Model: MOVE Compact

INTRODUCTION

The McGrey MOVE Compact is an 8-inch battery-powered active PA speaker designed for versatile use in various settings such as events, parties, and presentations. It offers powerful sound, flexible connectivity, and portability. This manual provides essential information for the safe and efficient operation of your device.

SAFETY INSTRUCTIONS

- Read all instructions carefully before using the device.
- Keep this manual for future reference.
- Do not expose the device to rain or moisture to prevent fire or electric shock.
- Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
- Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
- Protect the power cord from being walked on or pinched, particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
- Only use attachments/accessories specified by the manufacturer.
- Unplug this apparatus during lightning storms or when unused for long periods of time.
- Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way.

PRODUCT OVERVIEW

The McGrey MOVE Compact speaker combines portability with powerful audio performance, making it suitable for a wide range of applications.

TRAGBAR & kraftvoll



Leistungsstarke
190W



Bluetooth



Lange Akku-
Laufzeit



48V Phantom-
Power



4 EQ
Presets



Eingebauter
Halleffekt

 MCGREY

This image illustrates the key features of the McGrey MOVE Compact speaker, emphasizing its portability and power. It shows a speaker with icons representing 190W peak power, Bluetooth connectivity, long battery life, 48V phantom power, 4 EQ presets, and built-in reverb effect.

Key Features:

- **Mobile & Independent:** Integrated lithium battery provides up to 8 hours of operation.
- **Powerful 2-Way Sound:** 8-inch woofer and 1-inch compression driver deliver 95 W RMS and up to 115 dB SPL.
- **Bluetooth & TWS:** Wireless streaming via Bluetooth 5.0. TWS function allows stereo pairing of two systems.
- **Professional Connections:** 2x XLR Line Combo inputs, Cinch, 3.5 mm AUX, and XLR output. Optional 48V phantom power.
- **Intelligent DSP:** Voicing Modes (Music, Speech, Monitor, Sub), Feedback Eliminator, and Talkover function.

Universell nutzbar

Auf Stativ
Für die Ferne

Aufrecht angewinkelt
Für die Nähe

Quer angewinkelt
Als Monitor



This image demonstrates the versatile placement options for the McGrey MOVE Compact speaker. It shows the speaker mounted on a stand for distance, angled upright for close proximity, and angled horizontally as a monitor.

SETUP

1. Charging the Battery

Before first use, fully charge the integrated lithium battery. Connect the power cable to the AC input on the rear panel and plug it into a suitable power outlet. The battery level indicator on the control panel will show the charging status. A full charge takes approximately 3 hours.

2. Placement

Position the speaker according to your needs. The MOVE Compact can be placed:

- **On a stand:** For wider sound dispersion over a distance.
- **Angled upright:** Ideal for close proximity listening or as a personal monitor.
- **Angled horizontally:** Suitable for use as a stage monitor.

3. Initial Power On

After charging, ensure all volume controls are set to minimum. Press the main power switch on the rear panel to turn on the speaker.

OPERATING

Die Schaltzentrale

- ❶ 2-Band-EQ je Eingangskanal
- ❷ Bass Boost (Loudness)
- ❸ Anti Feedback
- ❹ Halleffekt
- ❺ Talk Over
- ❻ 48V für Kondensator Mikrofone
- ❼ Battery Level Indicator



This image details the control panel of the McGrey MOVE Compact speaker. It highlights features such as 2-band EQ per input channel, Bass Boost (Loudness), Anti-Feedback, Reverb effect, Talk Over function, 48V for condenser microphones, and Battery Level Indicator.

1. Connecting Audio Sources

The MOVE Compact offers various input options:

- **XLR Line Combo Inputs (CH 1, CH 2):** Use these for microphones, instruments, or line-level signals. The input type (Mic/Line/Inst) is switchable.
- **Cinch (RCA) Stereo Input (CH 3):** Connect devices like CD players or DJ mixers.
- **3.5 mm AUX Input (CH 3):** For connecting smartphones, tablets, or other portable audio devices.
- **XLR Mix Out:** Use this output to send the mixed signal to other PA systems or recording devices.

Vielfältige Anschlüsse



- ① 2 x XLR - Klinkenbuchse (Mic/Line/Inst schaltbar)
- ② 2x Cinch (Stereo Input)
- ③ 1 x XLR Buchse (Mix Out)
- ④ Hauptschalter Ein/Aus



This image displays the various connection options available on the rear panel of the McGrey MOVE Compact speaker. It shows 2x XLR-Jack combo inputs (switchable Mic/Line/Inst), 2x Cinch (RCA) stereo input, 1x XLR Mix Out, and the main power switch.

2. Bluetooth Pairing & TWS Function

- **Bluetooth Pairing:** Activate Bluetooth on your smartphone or tablet. On the MOVE Compact, select the Bluetooth input. The speaker will appear as 'McGrey MOVE Compact' in your device's Bluetooth list. Select it to pair.
- **TWS (True Wireless Stereo) Function:** To achieve stereo sound with two MOVE Compact speakers, ensure both speakers are powered on and not connected to any other Bluetooth device. On one speaker, activate the TWS pairing mode (refer to the control panel for the specific button). The two speakers will automatically connect, with one acting as the left channel and the other as the right.

STEREO-KLANG

Einfache Kopplung per Bluetooth



Bluetooth



Ein Gerät koppeln, zwei Kanäle erleben
links und rechts perfekt getrennt
für echtes Stereo-Feeling



This image demonstrates the stereo sound capability of the McGrey MOVE Compact speaker through easy Bluetooth pairing. It shows two speakers connected wirelessly for a true stereo experience, with left and right channels perfectly separated.

3. Using DSP Modes & Effects

- **Voicing Modes:** Select from 'Music', 'Speech', 'Monitor', or 'Sub' to optimize the speaker's sound profile for your specific application.
- **Feedback Eliminator:** Activate this function to reduce unwanted audio feedback, especially when using microphones.
- **Talkover Function:** When activated, this feature automatically lowers the background music volume when a microphone signal is detected, ideal for announcements or presentations.
- **Reverb Effect:** Apply reverb to your audio signals for added depth and ambiance.
- **Bass Boost:** Engage this feature for enhanced low-frequency response.

4. Adjusting Volume and EQ

Use the individual volume controls for each channel to balance your audio sources. The 2-band EQ (Treble and Bass) for each input channel allows you to fine-tune the tone.

MAINTENANCE

1. Cleaning

Wipe the exterior of the speaker with a soft, dry cloth. Do not use abrasive cleaners, waxes, or solvents. Ensure no liquids enter the speaker grille or control panel.

2. Battery Care

To prolong battery life, avoid fully discharging the battery frequently. If storing the speaker for an extended period, charge the battery to approximately 50-70% and recharge it every few months.

3. Storage

Store the speaker in a cool, dry place away from direct sunlight and extreme temperatures. Protect it from dust and moisture.

TROUBLESHOOTING

- **No Sound:** Check power connection, ensure speaker is on, verify input source connections, check volume levels on both the speaker and the source device.
- **Distorted Sound:** Reduce input volume from the source device or the speaker's channel volume. Check for proper cable connections.
- **Bluetooth Pairing Issues:** Ensure the speaker is in Bluetooth pairing mode. Turn off and on Bluetooth on your source device. Make sure no other devices are connected to the speaker via Bluetooth.
- **Feedback:** Activate the Feedback Eliminator. Reduce microphone gain. Reposition the microphone or speaker.
- **Short Battery Life:** Ensure the battery is fully charged. Battery performance may decrease over time with usage.

SPECIFICATIONS

Feature	Specification
Brand	McGrey
Model	MOVE Compact
Output Power	95 Watt RMS (up to 190W Peak)
Loudness Level	115 Decibel
Connectivity Technology	XLR, RCA, AUX, Bluetooth 5.0
Audio Inputs	2x XLR/Jack Combo, Cinch (RCA), 3.5 mm AUX
Audio Output	1x XLR Mix Out
Number of Channels	4

Power Source	Battery Powered (Lithium Battery 11.1V 6600 mAh)
Battery Life	Up to 8 hours (at moderate volume)
Charging Time	Approx. 3 hours
Compatible Devices	Microphones, Musical Instruments, Mixers, Smartphones, Tablets
Color	Black
Material	Plastic
Item Dimensions (LxWxH)	39.5 x 27.0 x 28.0 cm (from description) / 35 x 40 x 70 cm (from specs) <i>Note: Discrepancy in source data, using description's compact dimensions.</i>
Item Weight	6.9 kg (from description) / 14.5 kg (from specs) <i>-Note: Discrepancy in source data, using description's lighter weight for portability.</i>
Manufacturer Item Number	00102639
ASIN	B0GPDCV3MN

WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the documentation provided with your purchase or contact McGrey customer service. Keep your proof of purchase for any warranty claims.