

[Manuals.plus](#) /

› [NKPU](#) /

› NKPU 33-inch Low Profile Ceiling Fan with Lights (Model: BR-SY33-36) - User Manual

NKPU BR-SY33-36

NKPU 33-inch Low Profile Ceiling Fan with Lights

Model: BR-SY33-36 - User Manual

1. INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your NKPU 33-inch Low Profile Ceiling Fan with Lights. Please read this manual thoroughly before installation and use, and retain it for future reference. This ceiling fan is designed for indoor and covered outdoor areas such as patios and porches, but should not be directly exposed to rain.

2. SAFETY INFORMATION

To reduce the risk of electric shock, fire, or personal injury, always follow these basic safety precautions:

- **Disconnect Power:** Always turn off the power at the circuit breaker or fuse box before beginning installation or performing any maintenance.
- **Qualified Electrician:** If you are unfamiliar with electrical wiring, consult a qualified electrician.
- **Mounting Structure:** Ensure the mounting structure (junction box) is securely attached to the building structure and can support the fan's weight (7.14 lbs).
- **Blade Clearance:** Maintain a minimum clearance of 7 feet from the floor to the fan blades. Ensure blades do not strike any objects.
- **Wiring:** All wiring must be in accordance with national and local electrical codes.
- **Fan Operation:** Do not insert objects into the path of the fan blades while the fan is operating.
- **Light Source:** Do not attempt to replace the LED light source; it is designed for long-term use. Contact customer support if the light fails.

3. PACKAGE CONTENTS

Carefully unpack your ceiling fan and ensure all items are present. If any parts are missing or damaged, contact customer

support immediately.

- Ceiling Fan Unit (Motor, Blades, Light Kit)
- Remote Control
- Mounting Hardware (screws, wire nuts, etc.)
- Instruction Manual (this document)

4. SPECIFICATIONS

Brand	NKPU
Model Name	BR-SY33-36
Size	33 inches
Color	Brown
Power Source	DC
Voltage	110 Volts
Wattage	60 watts
Mounting Type	Flush Mount
Number of Blades	5
Fan Speeds	6
Light Color Temperatures	3000K (Warm), 4500K (Natural), 6000K (White)
Dimmable Light	Yes (10%-100%)
Motor Type	Reversible DC Motor
Control Methods	Remote Control, App Control
Timer Function	2 Hours
Noise Level	Less than 30 dB
Material	Metal, ABS Blades
Item Weight	7.14 Pounds
Indoor/Outdoor Usage	Indoor, Covered Outdoor

5. SETUP AND INSTALLATION

Before starting installation, ensure the power is turned off at the circuit breaker. Follow the steps below for proper assembly and mounting.

5.1. Installation Overview

The NKPU 33-inch ceiling fan is designed for straightforward installation. The following images illustrate key components and the overall appearance.



Image: NKPU 33-inch Ceiling Fan installed in a bedroom, demonstrating its low-profile design and integrated light.



Image: Diagram illustrating the compact dimensions of the NKPU 33-inch low profile ceiling fan and a comparison to a standard ceiling fan for easy installation.

5.2. Detailed Installation Steps

For a comprehensive visual guide, please refer to the installation video below. It covers the entire process from mounting to final assembly.

Your browser does not support the video tag.

Video: This video demonstrates the step-by-step installation process for the NKPU 33-inch Low Profile Ceiling Fan with Lights.

1. **Turn Off Power:** Locate the circuit breaker for the room where the fan will be installed and turn off the power.
2. **Mounting Bracket:** Secure the mounting bracket to the ceiling junction box using the provided screws. Ensure it is firmly attached.
3. **Wiring Connections:** Connect the fan's electrical wires to the household wiring according to local electrical codes. Typically, this involves connecting live, neutral, and ground wires.
4. **Attach Fan Body:** Carefully lift the fan body and attach it to the mounting bracket. Secure it with the appropriate screws.
5. **Install Blades:** Attach the five fan blades to the motor housing. Ensure they are securely fastened.
6. **Install Light Kit:** Connect the light kit wiring and attach the light fixture to the fan body.
7. **Restore Power:** Once all connections are secure and the fan is fully assembled, restore power at the circuit breaker.



Image: Exploded view of the NKPU 33-inch ceiling fan, detailing the fan blades, lampshade, motor, and ceiling plate for assembly reference.

6. OPERATING INSTRUCTIONS

Your NKPU ceiling fan offers multiple control options for convenience and customization.

6.1. Remote Control

The included remote control allows full functionality of your ceiling fan and light.



Image: Overview of the remote control buttons and their corresponding functions for the NKPU 33-inch ceiling fan.

- **On/Off:** Turns the fan or light on/off.
- **All Off:** Turns both the fan and light off simultaneously.
- **Light On/Off:** Controls the light independently.
- **Color Temperature Switching:** Cycles through 3000K (Warm), 4500K (Natural), and 6000K (White) light settings.
- **Brightness +/-:** Adjusts the light brightness from 10% to 100%.
- **Fan Speed (1-6):** Selects one of six fan speeds. Speed 1 is the lowest, Speed 6 is the highest.
- **F/R (Forward/Reverse):** Changes the fan blade rotation direction for seasonal use.
- **2H Timer:** Sets the fan to turn off automatically after 2 hours.

6.2. App Control

Control your fan conveniently from your smartphone using the dedicated app. Scan the QR code on the product packaging or visit <https://www.jasonghost.com/fanlamppro/> to download the app.

Your browser does not support the video tag.

Video: This video guides you through connecting your NKPU 33-inch Ceiling Fan to the mobile application for smart control.

App Connection Steps:

1. Download and install the 'Fan Lamp Pro' app on your smartphone.
2. Ensure your fan is powered on.
3. Open the app and follow the on-screen instructions to add a new device.
4. The fan light will blink twice to indicate a successful connection.

6.3. Light Functions

The integrated LED light offers customizable illumination.



Image: Visual representation of the three adjustable color temperatures (3000K, 4500K, 6000K) and the dimming range (10%-100%) of the NKPU ceiling fan light.

- **3-Color Dimmable LED:** Choose between Warm Light (3000K), Natural Light (4500K), and White Light (6000K).
- **Brightness Adjustment:** Adjust the brightness from 10% to 100% to suit your preference.

6.4. Fan Speeds and Reversible Motor

The fan features 6 speeds and a reversible DC motor for year-round comfort.



Image: Illustration of the 6-speed settings, suggesting optimal speeds for sleeping (1-2), family activities (3-4), and summer cooling (5-6).

LED LIGHT WITH ACRYLIC SHADE

Brighter, more even lighting experience



Image: Diagram showing the reversible DC motor function, illustrating downward airflow for cooling in summer and upward airflow for heat distribution in winter.

- **6-Speed Wind:** Adjust the airflow from a gentle breeze (Speed 1-2 for sleep) to a powerful cooling effect (Speed 5-6 for summer).
- **Reversible DC Motor:** In summer, set the fan to rotate counter-clockwise for a cooling downdraft. In winter, set it to rotate clockwise to circulate warm air trapped near the ceiling.

6.5. Smart Memory Function

The fan remembers your last brightness and color temperature settings. If you turn off the light for at least 10 seconds, it will recall these settings when turned back on. If the light is turned on again within 10 seconds, the color temperature may switch.

Your browser does not support the video tag.

Video: This video illustrates the various lighting and fan speed functions of the NKPU 33-inch Ceiling Fan, including dimming and color temperature adjustments.

7. MAINTENANCE

Regular maintenance ensures optimal performance and longevity of your ceiling fan.

- **Cleaning:** Dust the fan blades and motor housing periodically with a soft, damp cloth. Do not use abrasive cleaners or solvents, as these can damage the finish.
- **Light Cover:** Gently wipe the light cover with a soft, dry cloth.
- **Tighten Screws:** Periodically check all screws and connections on the fan and mounting bracket to ensure they are secure.
- **No Lubrication:** The DC motor is permanently lubricated and does not require oiling.

8. TROUBLESHOOTING

If you encounter any issues with your fan, refer to the following troubleshooting guide before contacting customer support.

Problem	Possible Cause	Solution
Fan does not start	No power to the fan; Loose wire connections; Remote control battery low or not paired.	Check circuit breaker/fuse. Ensure all wire connections are secure. Replace remote battery or re-pair remote.
Light does not work	Loose wire connection to light kit; Light kit failure.	Check light kit wiring. If light kit is faulty, contact customer support.
Remote control not working	Battery depleted; Remote not paired with fan; Obstruction between remote and receiver.	Replace battery. Re-pair remote control (refer to remote pairing instructions in the app). Ensure clear line of sight.
Fan wobbles	Loose fan blades; Loose mounting bracket; Unbalanced blades.	Ensure all blade screws are tight. Verify mounting bracket is securely fastened to the ceiling. Check for bent blades or use a balancing kit if necessary.
Excessive noise	Loose screws; Motor housing rubbing; Blades hitting an obstruction.	Check and tighten all screws. Ensure no wires are rubbing against the motor housing. Verify blades have clear clearance.

9. WARRANTY AND SUPPORT

Your NKPU 33-inch Low Profile Ceiling Fan with Lights comes with a **1-year warranty** covering manufacturing defects. For any questions regarding installation, operation, or troubleshooting, please contact our **24-hour customer support**. Our team is available to assist you.

Contact information can typically be found on the product packaging or the retailer's website.