

[Manuals.plus](#) /

› [Maharaja Whiteline](#) /

› Maharaja Whiteline Odacio Desire 550W Juicer Mixer Grinder User Manual

Maharaja Whiteline Odacio Desire

Maharaja Whiteline Odacio Desire 550W Juicer Mixer Grinder

User Manual

1. INTRODUCTION

Thank you for choosing the Maharaja Whiteline Odacio Desire 550W Juicer Mixer Grinder. This appliance is designed to simplify your daily kitchen tasks, offering efficient juicing, mixing, and grinding capabilities. Please read this manual carefully before operating the appliance to ensure safe and optimal performance. Keep this manual for future reference.



Image 1.1: The Maharaja Whiteline Odacio Desire Juicer Mixer Grinder with its various components and prepared ingredients.

2. IMPORTANT SAFETY INSTRUCTIONS

Always follow basic safety precautions when using electrical appliances to reduce the risk of fire, electric shock, and injury.

- Read all instructions before use.
- Do not immerse the motor unit in water or any other liquid. Clean with a damp cloth only.
- Ensure the voltage indicated on the appliance matches your local mains voltage before connecting.
- Unplug from the outlet when not in use, before assembling or disassembling parts, and before cleaning.
- Avoid contact with moving parts. Never feed food by hand; always use the food pusher provided.
- Do not operate any appliance with a damaged cord or plug, or after the appliance malfunctions or has been

damaged in any manner.

- The use of attachments not recommended or sold by the manufacturer may cause fire, electric shock, or injury.
- Do not let the cord hang over the edge of a table or counter, or touch hot surfaces.
- This appliance is for household use only. Do not use outdoors.
- Keep hands and utensils out of the jar during operation to prevent injury and damage to the appliance.
- Ensure all parts are correctly assembled and locked before operating.

3. COMPONENTS OVERVIEW

The Maharaja Whiteline Odacio Desire Juicer Mixer Grinder comes with the following components:

- **Main Motor Unit:** The base unit housing the 550W motor and speed control knob.
- **Liquidizer Jar (1.5L):** For blending liquids, making milkshakes, and purees. Comes with a lid.
- **Grinder Jar (1L):** For wet and dry grinding, such as spices, nuts, and batters. Comes with a lid.
- **Chutney Jar (400ml):** Smaller jar for grinding small quantities of spices, chutneys, and pastes. Comes with a lid.
- **Spatula:** For mixing and scraping ingredients from the jars.
- **User Manual & Warranty Card:** This document and your warranty information.

Built to Crush BEYOND LIMITS

Mix & Grind SS Blade



Image 3.1: Overview of the three stainless steel jars included with the appliance.

4. SETUP AND ASSEMBLY

1. **Unpacking:** Carefully remove all components from the packaging. Retain the packaging for storage or future transport.
2. **Initial Cleaning:** Before first use, wash all removable parts (jars, lids, blades, spatula) with mild detergent and water. Rinse thoroughly and dry. Wipe the main motor unit with a damp cloth. Do not immerse the motor unit in water.
3. **Placement:** Place the main motor unit on a stable, flat, and dry surface, away from heat sources and direct sunlight. Ensure there is adequate ventilation around the unit.
4. **Jar Assembly:** Ensure the blade assembly is securely fitted into the bottom of the respective jar. Place the ingredients into the jar, then secure the lid firmly.
5. **Mounting the Jar:** Place the assembled jar onto the main motor unit. Turn it clockwise until it locks securely into

place. The appliance will not operate if the jar is not correctly locked.

5. OPERATING INSTRUCTIONS

General Operation

- Ensure the appliance is properly assembled and the jar is locked.
- Plug the power cord into a suitable electrical outlet.
- Turn the speed control knob to the desired speed setting (1, 2, or 3). For short bursts, use the 'Pulse' function.
- Do not operate continuously for more than 5 minutes. Allow a 2-minute rest period between cycles.
- After use, turn the knob to 'OFF' and unplug the appliance.

5.1. Juicing Function

Use the juicer attachment for extracting juice from fruits and vegetables.

1. Assemble the juicer jar with its mesh filter and lid.
2. Cut fruits or vegetables into small pieces that fit into the feeding chute.
3. Place a container under the juice spout to collect the juice.
4. Switch on the appliance and gradually push the ingredients into the chute using the food pusher.
5. Do not apply excessive force.

MAHARAJA
—WHITELINE—

Engineered to Perfection

ODACIO DESIRE

Juicer Mixer Grinder
550W



Image 5.1: The premium stainless steel juicer mesh ensures efficient juice extraction.



Image 5.2: The juicer function allows for quick preparation of fresh juices.

5.2. Grinding Function

Use the grinder jar for dry ingredients like spices or wet ingredients for pastes.

1. Place the desired ingredients into the grinder jar. Do not overfill.
2. Secure the lid firmly.
3. Mount the jar onto the motor unit and lock it.
4. Select the appropriate speed setting or use the 'Pulse' function for controlled grinding.
5. For coarse grinding, use shorter bursts. For fine grinding, operate for longer durations.

Sharp Cutting SMOOTH JUICING

- *Premium SS Juicer mesh*



Image 5.3: The robust stainless steel blades are designed for effective grinding of various ingredients.

5.3. Mixing/Blending Function

Use the liquidizer jar for blending, mixing, and making purees.

1. Add ingredients to the liquidizer jar. For liquids, ensure the level does not exceed the maximum fill line.
2. Secure the lid firmly.
3. Mount the jar onto the motor unit and lock it.
4. Start at a lower speed and gradually increase to the desired speed.
5. For best results, add liquids first, then solid ingredients.

6. MAINTENANCE AND CLEANING

Regular cleaning and maintenance will prolong the life of your appliance.

- **Always unplug the appliance before cleaning.**
- **Motor Unit:** Wipe the main motor unit with a soft, damp cloth. Do not use abrasive cleaners or immerse it in water.
- **Jars and Lids:** Wash the jars, lids, and blades immediately after use to prevent food from drying on them. Use warm water and mild dish soap. Rinse thoroughly and dry.
- **Blades:** Handle blades with extreme care as they are sharp. Use a brush for cleaning hard-to-reach areas around the blades.
- **Storage:** Store the appliance and its accessories in a clean, dry place when not in use.

7. TROUBLESHOOTING

If you encounter any issues, refer to the following table before contacting customer service.

Problem	Possible Cause	Solution
Appliance does not start.	Power cord not plugged in. Jar not locked correctly. Overload protector activated.	Plug in the power cord. Ensure the jar is securely locked onto the motor unit. Unplug, wait 2-3 minutes for the motor to cool, then restart. Reduce ingredients if overloaded.
Motor makes unusual noise.	Jar not properly seated. Ingredients too hard or too much.	Re-seat the jar. Reduce the quantity or cut hard ingredients into smaller pieces.
Leakage from jar.	Lid not properly closed. Gasket not fitted correctly. Jar overfilled.	Ensure the lid is tightly closed. Check and re-fit the rubber gasket. Do not fill above the maximum level.
Ineffective grinding/blending.	Insufficient liquid (for blending). Ingredients too large. Blades dull.	Add more liquid. Cut ingredients into smaller pieces. If blades are dull, contact customer service for replacement.

8. SPECIFICATIONS

Feature	Detail
Brand	Maharaja Whiteline
Model Name	Odacio Desire
Model Number	5210005369
Maximum Power	550 Watts
Voltage	230 Volts
Power Source Type	Corded Electric
Product Dimensions (D x W x H)	46D x 23.7W x 33H Centimeters
Item Weight	3750 Grams

Feature	Detail
Number of Jars	3 (1.5L Liquidizer, 1L Grinder, 400ml Chutney)
Product Care Instructions	Hand Wash Only

9. WARRANTY AND SUPPORT

Maharaja Whiteline provides comprehensive warranty coverage for your Odacio Desire Juicer Mixer Grinder.

- **Motor Warranty:** 5 Years coverage on the motor.
- **Product Warranty:** 2 Years coverage on the overall product.

Please retain your purchase receipt and warranty card for any warranty claims. The warranty covers manufacturing defects under normal household use. It does not cover damage due to misuse, neglect, unauthorized repairs, or normal wear and tear.

MAHARAJA
—WHITELINE—

Door step warranty

POWERFUL PERFORMANCE, ASSURED PROTECTION

5Year
Coverage
on Motor

2Year
Coverage
Product



Image 9.1: Details of the warranty coverage for the motor and the product.

Customer Support

For service, repairs, or any queries regarding your product, please contact Maharaja Whiteline customer support:

- **Manufacturer:** GROUPE SEB INDIA (P) LTD
- **Address:** C-67, 3rd Floor DDA, Sheds, OKHLA PHASE1, New Delhi-110020, INDIA
- Refer to your warranty card or the official Maharaja Whiteline website for the latest contact information and service center details.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question

and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question