

[Skip to content](#)

## Manuals+

User Manuals Simplified.



# CISCO 6823 IP DECT Handset User Guide

[Home](#) » [Cisco](#) » CISCO 6823 IP DECT Handset User Guide



Contents [hide](#)

[1 Cisco IP DECT 6823 Handset Quick Start Guide](#)

[2 Lock the Handset Keypad](#)

[3 Documents / Resources](#)

[4 Related Posts](#)

## Cisco IP DECT 6823 Handset Quick Start Guide

### Your Handset



### Legend

1. Indicator light (LED)
2. Headset port
3. Softkeys, phone control buttons (**Speaker**, **Menu**), Navigation cluster (Navigation ring and **Select** button, call control buttons (**Answer/Send**, **Power/End**))
4. Keypad
5. **Volume** and **Mute** buttons

### Turn On Your Handset


Press and hold **Power/End**  until the screen turns on.

### Turn Off Your Handset


Press and hold **Power/End**  until the screen turns off.

## Lock the Handset Keypad


You can lock the handset keypad to stop accidental dialing. When you lock the keypad, you can still dial emergency numbers. The softkey label doesn't display when you lock the keypad.

Press and hold **Zero (0)**  until the message “**Press and hold 0**” is displayed on the screen.

## Make a Call

1. When your handset is idle, enter the phone number with the keypad.
2. Press **Answer/Send** .

## Dial an Emergency Number

1. When your handset is idle, enter the emergency number with the keypad.
2. Press **Answer/Send** .

## Answer a Call

Press **Answer/Send** .


## Hold and Resume a Call

1. From an active call, press **Hold**.
2. Press **Resume** to pick the call back up.


## Mute Your Call

1. Press **Mute** .
2. To unmute yourself, press **Mute** again.

## Create a Conference Call

1. From an active call, press **More > Conference**.
2. Enter the coworker's number and press **Answer/Send** .
3. Press **Conf** after the coworker answers.


## Transfer a Call

1. From an active call, press **More > Transfer**.
2. Enter the coworker's number and press **Answer/Send** .
3. Press **Transfer** after the first ring tone or after your coworker answers.

## Add a Contact

1. Press **Recents** and highlight the recent caller.
2. Press **More**, highlight **Save as Contact**, and press **Select**.
3. Highlight the category, press **Select**, and press **Save** to save the number.
4. (Optional) Highlight a field to add or replace other information.
5. Press **Save** and press **Yes**.

## Call a Local Contact

1. Press **Contacts** and highlight an entry.
2. (Optional) Press the right on the Navigation ring  to select an alternate number.
3. Press **Call**.


## Call a Directory Contact

1. Press **Directory**.
2. Scroll down to highlight an entry or press **Search**, enter a name, and press **Search**.
3. Press Line and select a **line** to call on.
4. Press **Select**.


## View Your Recent Calls

1. Press **Recents**.
2. Press the Navigation ring  left or right to view different lists.

## Use Push to Talk

1. Press and hold **Mute** .
2. Talk when connected and release **Mute** at the end of your message.

## Assign a Speed-Dial Number

1. Press **Contacts**:
2. Highlight a contact.
3. Press **More** select **Speed Dial**.
4. To reuse an existing speed-dial index entry, highlight a number, press **Unassign**, and press **Yes**.
5. Highlight an empty speed-dial index and press Add.
6. Press **Power/End** .


## Access Your Voicemail

1. Press and hold One until you hear the ringtone.
2. Follow the voice prompts.


## Change the Volume on a Call

While on a call, press **Volume**  up or down.

## Set Do Not Disturb

1. Press **Menu** .
2. Select **Settings** > **Do not disturb**.
3. Select **Disabled** (default) to turn off DND or select **Enabled** to turn on DND.
4. Press **Select** to save the setting.

## Set the Coverage Warning

1. Press **Menu** .
2. Select **Settings** > **Audio Settings**.
3. Highlight **Coverage warning**.
4. Press **Off** to stop the tone or press **On** to play the tone.

## User Guide

View the full User Guide at <https://www.cisco.com/c/en/us/support/collaboration-endpoints/ip-dect-6800-seriesmultiplatform-firmware/products-user-guide-list.html>.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com/go/trademarks](http://www.cisco.com/go/trademarks). Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

## Documents / Resources



## [CISCO 6823 IP DECT Handset](#) [pdf] User Guide 6823, IP DECT Handset

**[Manuals+](#)**,

- [home](#)
- [privacy](#)