



Home » Cooper » COOPER Fuses Reducers for Class H, J, K, and R Fuses User Guide 🏗



COOPER Fuses Reducers for Class H, J, K, and R **Fuses User Guide**

July 13, 2025

Contents [hide]

- 1 Fuses Reducers for Class H, J, K, and R Fuses
 - 1.1 Fuses Reducers Class H, J, K, and R
 - 1.2 Fuses Reducers for Class H, J, K, & R Fuses
 - 1.3 Fuse Reducers for Class J Dimension Fuses- JDL, JFL, & CJ
 - 1.4 † Not for Bolt-on Applications. ** Product does not have UL or CSA certification.
 - 1.5 Fuse Reducers for Class H & K Dimension Fuses KON, ERN, PONC, CDNC; KOS, ERS, **CDSC**
 - 1.6 Fuse Reducers for Class R Dimension Fuses ECNR, LENRK, NCLR; ECSR, LESRK, & SCLR
 - 1.7 Fuse Reducers Class H, J, K, and R
 - 1.8 Fuses Reducers for Class H, J, K, & R Fuses
 - 1.9 Fuse Reducers for Class J Dimension Fuses- JDL, JFL, & CJ
 - 1.10 Fuse Reducers for Class H & K Dimension Fuses KON, ERN, PONC, CDNC; KOS, ERS, CDSC
 - 1.11 Fuse Reducers for Class R Dimension Fuses ECNR, LENRK, NCLR; ECSR, LESRK, & **SCLR**
- 2 Documents / Resources
 - 2.1 References

Fuses Reducers for Class H, J, K, and R Fuses

Fuses Reducers Class H, J, K, and R



Features:

Fuse reducers install on fuses and permit smaller size

fuses to be used in larger amp size switches and blocks.

 Reducers will fit into any panel or switch including the

dead-front type.

- Strong contact is maintained both mechanically and electrically.
- UL Listed.
- There are no reducers to go from 250V to 600V.
- There are no reducers for switching from one fuse class to another.
- There are no reducers for Class T or Class L fuses.

Fuses Reducers for Class H, J, K, & R Fuses

Agency Approvals: UL Listed,

Guide #IZZR, File #E12853

CSA Certified,

Class 6225-01, File 47235

Fuse Reducers for Class J Dimension Fuses- JDL, JFL, & CJ

Catalog No. (Pairs)

Fuse Size	Desired Size	Catalog No. (Pairs)
i use size	Desired Gize	Reducer No.
30A	60A	No. 263

30A	100A	No. 213
60A	100A	No. 216
60A	200A	No. 226
100A	200A	No. 2621
100A	400A	*No. 2641
200A	400A	No. 2642
200A	600A	*No. 2661
400A	600A	*No. 2662
	600A	*No. 2664

Fuse Reducers for Class H & K Dimension Fuses KON, ERN, PONC, CDNC; KOS, ERS, CDSC

Fuse Size	Desired Size	250V Reducer No.	Catalog No. (Pairs) 600V Reducer No.
30A	60A	No. 263	No. 663
30A	100A	No. 213	No. 216
60A	100A	No. 216	No. 616
60A	200A	No. 226	No. 626
100A	200A	No. 2621	No. 2621
100A	400A	*No. 2641	*No. 2641

[†] Not for Bolt-on Applications.

** Product does not have UL or CSA certification.

200A	400A	No. 2642	No. 2642
100A	600A	*No. 2661	*No. 2661
200A	600A	*No. 2662	*No. 2662
400A	600A	*No. 2664	*No. 2664

Fuse Reducers for Class R Dimension Fuses ECNR, LENRK, NCLR; ECSR, LESRK, & SCLR

Fuse Size	Fuse Size Desired Size 250V Reducer No		Catalog No. (Pairs	
			600V Reducer No.	
30A	60A	No. 263-R	No. 663-R	
30A	100A	No. 213-R	No. 216-R	
60A	100A	No. 216-R	No. 616-R	
60A	200A	No. 226-R	No. 626-R	
100A	200A	*No. 2621-R		
100A	400A	*No. 2	641-R	
200A	400A	*No. 242-R	*No. 642-R	
100A	600A	*No. 2661-R		
200A	600A	*No. 2662-R		
400A	600A	**No. 2664-R		

^{*} Product does not have CSA certification.

Note: Carton quantity - 10 pair.

^{**}Single reducer only (pair not required)

Fuse Reducers Class H, J, K, and R



Features:

Fuse reducers install on fuses and permit smaller size

fuses to be used in larger amp size switches and blocks.

 Reducers will fit into any panel or switch including the

dead-front type.

- Strong contact is maintained both mechanically and electrically.
- UL Listed.
- There are no reducers to go from 250V to 600V.
- There are no reducers for switching from one fuse class to another.
- There are no reducers for Class T or Class L fuses.

Fuses Reducers for Class H, J, K, & R Fuses

Agency Approvals: UL Listed,

Guide #IZZR, File #E12853

CSA Certified.

Class 6225-01, File 47235

Fuse Reducers for Class J Dimension Fuses- JDL, JFL, & CJ

Fuse Size	Desired Size	Catalog No. (Pairs)
i use size	Desired Size	Reducer No.
30A	60A	**J-63

30A	100A	**J-13
60A	100A	**J-16
60A	200A	**J-26
100A	200A	**J-21
100A	400A	**J-41
200A	400A	**J-42
200A	600A	**J-62
400A	600A	**J-64

[†] Not for Bolt-on Applications.

Fuse Reducers for Class H & K Dimension Fuses KON, ERN, PONC, CDNC; KOS, ERS, CDSC

Fuse Size	Desired Size 250V Reducer No.		Catalog No. (Pairs
			600V Reducer No.
30A	60A	No. 263	No. 663
30A	100A	No. 213	No. 216
60A	100A	No. 216	No. 616
60A	200A	No. 226	No. 626
100A	200A	No. 2621	No. 2621
100A	400A	*No. 2641	*No. 2641

^{**} Product does not have UL or CSA certification.

200A	400A	No. 2642	No. 2642
100A	600A	*No. 2661	*No. 2661
200A	600A	*No. 2662	*No. 2662
400A	600A	*No. 2664	*No. 2664

^{*} Product does not have CSA certification.

Fuse Reducers for Class R Dimension Fuses ECNR, LENRK, NCLR; ECSR, LESRK, & SCLR

Fuse Size	use Size Desired Size 250V Reducer No.		Catalog No. (Pairs	
			600V Reducer No.	
30A	60A	No. 263-R	No. 663-R	
30A	100A	No. 213-R	No. 216-R	
60A	100A	No. 216-R	No. 616-R	
60A	200A	No. 226-R	No. 626-R	
100A	200A	*No. 2621-R		
100A	400A	*No. 2	641-R	
200A	400A	*No. 242-R	*No. 642-R	
100A	600A	*No. 2661-R		
200A	600A	*No. 2662-R		
400A	600A	**No. 2664-R		

^{*} Product does not have CSA certification.

**Single reducer only (pair not required)

Note: Carton quantity - 10 pair.

Documents / Resources

ers, Reducers



COOPER Fuses Reducers for Class H, J, K, and R Fuses [pdf] User Guid

References

- User Manual
- Cooper
- ▶ 13-R, 216-R, 242-R, 2621-R, 263-R, 2641-R, 2661-R, 2662-R, 2664-R, 626-R, 642-R, 663-R, Class H J K and R Fuses, Cooper, Fuses Reducers, Fuses Reducers for Class H J K and R Fuses, Reducers, Reducers for Class H J K and R Fuses

Leave a comment

Your email address will not be published. Required fields are marked *

Comment *			
Name			

Email

Website		

Post Comment

Search:

e.g. whirlpool wrf535swhz

Search

Manuals+ | Upload | Deep Search | Privacy Policy | @manuals.plus | YouTube

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.