

electro-harmonix Satisfaction Vintage Fuzz Pedal User Manual

[Home](#) » [electro-harmonix](#) » electro-harmonix Satisfaction Vintage Fuzz Pedal User Manual 

Contents [[hide](#)]

- 1 [electro-harmonix Satisfaction Vintage Fuzz Pedal User Manual](#)
- 2 [SATISFACTION VINTAGE FUZZ](#)
- 3 – [CONTROLS](#)
 - 3.1 [ATTACK Knob](#)
 - 3.2 [VOL Knob](#)
 - 3.3 [FOOTSWITCH and LED](#)
 - 3.4 [AMP Jack](#)
 - 3.5 [9V Power Jack](#)
- 4 [CHANGING THE BATTERY](#)
- 5 [WARRANTY INFORMATION](#)
 - 5.1 [United States & Canada](#)
 - 5.2 [Europe](#)
- 6 [Read More About This Manual & Download PDF:](#)
- 7 [Documents / Resources](#)
 - 7.1 [References](#)
- 8 [Related Posts](#)

electro-harmonix Satisfaction Vintage Fuzz Pedal User Manual



SATISFACTION VINTAGE FUZZ

Congratulations on your purchase of the Satisfaction Fuzz, a modern recreation of the classic fuzz sounds of the 1960s. Updated with a compact nano chassis, the Satisfaction creates drive sounds ranging from crunchy breakup to intense fuzz. Attack and Volume controls put you in the mix, and true-bypass switching keeps your bypassed signal intact

– CONTROLS

ATTACK Knob

– Controls the amount of input gain and distortion. As you turn this knob clockwise, the SATISFACTION ranges from mild drive to saturated fuzz.

VOL Knob

Sets the output level of the SATISFACTION.

FOOTSWITCH and LED

The Footswitch selects whether the SATISFACTION is engaged or in true bypass mode. When the effect is engaged, the LED is lit.

INPUT Jack – This ¼” jack is the audio input for the SATISFACTION. The input impedance is 50k .

AMP Jack

This ¼” jack is the audio output from the SATISFACTION. The output impedance depends on the VOLUME setting, ranging from 100 to 25k .

9V Power Jack

The SATISFACTION can run off of a 9V battery or you can use an optional 9VDC AC Adapter capable of delivering at least 25mA to the 9V power jack. We recommend the EHX9.6DC-200. The AC Adapter must have a center negative plug. The battery may be left in or taken out when using an AC Adapter. The SATISFACTION draws 1.5mA at 9VDC. The maximum voltage that may be connected to the 9V Power Jack is 10VDC.

CHANGING THE BATTERY

To change the battery, remove the four screws on the bottom of the SATISFACTION and take off the bottom plate. The battery clip is in the bottom of the unit. Take care not to touch the circuit board while changing the battery in order to avoid damaging a component.

WARRANTY INFORMATION

Please register online at <http://www.ehx.com/product-registration> or complete and return the enclosed warranty card within 10 days of purchase. Electro-Harmonix will repair or replace, at its discretion, a product that fails to operate due to defects in materials or workmanship for a period of one year from date of purchase. This applies only to original purchasers who have bought their product from an authorized Electro-Harmonix retailer. Repaired or replaced units will then be warranted for the unexpired portion of the original warranty term.

If you should need to return your unit for service within the warranty period, please contact the appropriate office listed below. Customers outside the regions listed below, please contact EHX Customer Service for information on warranty repairs at info@ehx.com or +1-718-937-8300. USA and Canadian customers: please obtain a Return Authorization Number (RA#) from EHX Customer Service before returning your product. Include with your returned unit: a written description of the problem as well as your name, address, telephone number, e-mail address, and RA#; and a copy of your receipt clearly showing the purchase date.

United States & Canada

EHX CUSTOMER SERVICE
ELECTRO-HARMONIX

c/o NEW SENSOR CORP.
47-50 33RD STREET
LONG ISLAND CITY, NY 11101
Tel: 718-937-8300
Email: info@ehx.com



Europe

JOHN WILLIAMS
ELECTRO-HARMONIX UK
13 CWMDONKIN TERRACE
SWANSEA SA2 0RQ
UNITED KINGDOM
Tel: +44 179 247 3258
Email: electroharmonixuk@virginmedia.com

This warranty gives a purchaser specific legal rights. A purchaser may have even greater rights depending upon the laws of the jurisdiction within which the product was purchased.
To hear demos on all EHX pedals visit us on the web at www.ehx.com
Email us at info@ehx.com

Read More About This Manual & Download PDF:

Documents / Resources

	<p>electro-harmonix Satisfaction Vintage Fuzz Pedal [pdf] User Manual Satisfaction, Vintage Fuzz Pedal, Satisfaction Vintage Fuzz Pedal</p>
	<p>electro-harmonix Satisfaction Vintage Fuzz Pedal [pdf] Instruction Manual Satisfaction Vintage Fuzz, Pedal, Satisfaction Vintage Fuzz Pedal</p>

References

- [Electro-Harmonix](#)
- [Support - Electro-Harmonix](#)

Related Posts

[electro-harmonix EHX Expression Pedal User Manual](#)



EHX Expression Congratulations on your purchase of the EHX Expression pedal! Built to be both versatile and...



[electro-harmonix Flatiron Fuzz Classic Op-Amp Powered Fuzz/Distortion Instruction Manual](#)

FLATIRON FUZZ Congratulations on your purchase of the Flatiron Fuzz, an extremely versatile, classic op-amp-powered pedal that can...



[electro-harmonix HOT TUBES Nano Overdrive Pedal User Manual](#)

HOT TUBES Congratulations on your purchase of the Hot Tubes overdrive, a faithful reissue of the original 1970s...



[electro-harmonix LPB-1 Linear Power Booster Pedal User Manual](#)

LPB-1 LINEAR POWER BOOSTER -DESCRIPTION- Congratulations! You have just purchased the LPB-1 Power Booster, a reissue of the...