



# EWIN T3 Bluetooth Transceiver Receiver Instruction Manual

[Home](#) » [EWIN](#) » EWIN T3 Bluetooth Transceiver Receiver Instruction Manual 

## Contents

- [1 EWIN T3 Bluetooth Transceiver Receiver](#)
- [2 OverView](#)
- [3 Schematic illustration](#)
- [4 Product features](#)
- [5 Operating instructions](#)
- [6 Technology Specs](#)
- [7 Troubleshooting](#)
- [8 Warm tips](#)
- [9 Packaging](#)
- [10 FCC Statement](#)
- [11 Documents / Resources](#)
- [12 Related Posts](#)

# EWIN


## EWIN T3 Bluetooth Transceiver Receiver



## OverView

Thank you for purchasing our Bluetooth transceiver! This product has the characteristics of low distortion, low power consumption, low delay, high fidelity, stereo and so on.

## Schematic illustration




## Product features


1. Bluetooth V5.0
2. The launch state supports two Bluetooth devices to connect and play at the same time
3. Support Bluetooth receiver/ transmitter
4. Clear all paired Bluetooth information
5. Automatically connect the paired Bluetooth device after power on
6. Five minutes no device connection, automatic shutdown
7. Music on full charge lasts about seven hours
8. Bluetooth support A2DP,AVRCP,HFP,HSP
9. Support Bluetooth DSP technology of stereo music
10. Aux audio input / output
11. Private answer

## Operating instructions

1. Launch mode TX, green light



2. Receive mode RX, blue light



3. Connect / Reset Bluetooth Pairing for the first time

4. Long press " " 3 seconds, Lights flashing (To reset Bluetooth, double-click " " to clear Bluetooth pairing information)

5. Double-click the " " key, Turn on Bluetooth search and flash the light

6. Mobile phone search Bluetooth pairing name: "T3", after the pairing is successful, prompt Bluetooth connection is successful, the light is always on.

7. Automatic connection after use again

8. Connect two mobile phones. If you want to connect the second device, double-click the " " button and repeat the connection steps.

### Answering the call

9. On the status of Bluetooth, To answer the incoming call, press " " to answer, Press again " " to hang up.

### Private answer

10. When you want to use your own phone to answer a call, long press the " " button for 2 seconds to switch between the phone and Bluetooth 5Siri/Voice assistant function. When using Siri/Voice assistant after Bluetooth pairing, long press the " " button for 3 seconds to activate it. (supported mobile phone brands are: Apple mobile phone, Samsung mobile phone, native Android system mobile phone) Note: This feature is not supported on some phones.
11. **Automatic shutdown** Bluetooth player (RX mode or TX mode) will shut down automatically without any device connection or other key operation for 5 minutes.
12. **Charge** The red light is always on when charging under the state of shutdown. Under the starting state, the red light of RX mode charging is always on, and the blue indicator is also on. Under the starting state, the red light of TX mode charging is always on, and the green indicator is also on. The red light goes out when it is fully charged.
13. **Low voltage alarm** When the battery power is too low, the red light flashes and the voice prompts "low power" and other working lights go off.

Technology Specs

Charging voltage	5V
Charging current	150mA
Working current	35mA
Shut off current	41uA
Charging time	About 2H
Working time	About 7H
Battery capacity	280mAh
Bluetooth Ver.	Version 5.0

Bluetooth audio processing	DSP and A2DP(Advance Audio Distribution Profile)
Bluetooth frequency	2.402-2.480GHz
Bluetooth transmission distance	10M
Bluetooth MIC effective distance	0.5~2M
Bluetooth transmission output power	6dbm

## Troubleshooting

No response on power	<p>.Toggle the RX-TX key and long press the power button again</p> <p>.Plug in the charging cable to charge the Bluetooth player for 5 minutes before turning it on</p>
----------------------	---

Can't play	<ul style="list-style-type: none"> <li>. Make sure the connected device is working properly</li> <li>.Clear bluetooth pairing and repair Bluetooth</li> <li>.Is the audio cable plugged in properly</li> </ul>
Can't charge	<ul style="list-style-type: none"> <li>. Please unplug the charging cable and re-insert it</li> <li>. Try switching to another charger</li> </ul>
No reaction on and off	<p>Long press the “on/off” button for 8 seconds to resume factory Settings and start up again</p>

## Warm tips

- Do not use this product in a dusty and humid environment with extreme ly high and low temperatures.
- Do not drop the product to avoid surface damage or breakdown.
- Do not disassemble the product,if you have any questions, please contact your dealer
- Due to continuous improvement and enhancement of technology,changes in product performance and functionality are subject to change without notice.

## Packaging

1. Manual
2. Main device

- 3. Audio line
- 4. Micro-USB Charging line


FCC Statement

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance could void the user’s authority to operate the equipment. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Documents / Resources

	<a href="#">EWIN T3 Bluetooth Transceiver Receiver</a> [pdf] Instruction Manual T3, 2ATZS-T3, 2ATZST3, T3 Bluetooth Transceiver Receiver, Bluetooth Transceiver Receiver
---	---