

# EZVIZ LT70 Smart Lock User Manual

## Contents

- [1 EZVIZ LT70 Smart Lock](#)
- [2 Product Information](#)
- [3 Product Usage Instructions](#)
- [4 Instruction](#)
- [5 Packing List](#)
- [6 Overview](#)
- [7 Lock Using](#)
- [8 Operation and Management](#)
- [9 Documents / Resources](#)
  - [9.1 References](#)
- [10 Related Posts](#)

## EZVIZ LT70 Smart Lock

### Product Information

The product described in this user manual is manufactured by Hangzhou EZVIZ Software Co., Ltd. (hereinafter referred to as EZVIZ). The manual provides instructions for using and managing the product. The information contained in the manual is subject to change without notice due to firmware updates or other reasons.

TM, TM, and other EZVIZ's trademarks and logos mentioned in this manual are the properties of EZVIZ in various jurisdictions. Other trademarks and logos mentioned may be the properties of their respective owners.

EZVIZ provides the product "as is," with all faults and errors, and makes no warranties, express or implied, including without limitation, merchantability, satisfactory quality, fitness for a particular purpose, and non-infringement of third party. EZVIZ shall not be liable for any special, consequential, incidental, or indirect damages arising from the use of this product.

EZVIZ does not undertake any liability for personal injury or property damage resulting from product interruption or service termination caused by improper installation or usage other than as requested, the protection of national or public interests, force majeure, yourself or the third party using any third party's products, software, applications, and others.

The use of the product with internet access is at your own risks. EZVIZ shall not be responsible for abnormal operation, privacy leakage, or other damages resulting from cyber attacks, hacker attacks, virus inspection, or other internet security risks. However, EZVIZ will provide timely technical support if required. Please check all relevant laws in your jurisdiction before using this product to ensure compliance with applicable laws.

### Product Usage Instructions

1. Read the user manual carefully before using the product.
2. Ensure proper installation of the product according to the provided instructions.

3. Refer to the manual for instructions on how to use and manage the product.
4. Keep the product firmware up to date by checking for updates on the EZVIZ website ( <http://www.ezviz.com> ).
5. Use the product in accordance with the applicable laws and regulations in your jurisdiction.
6. Be aware of the risks associated with using the product with internet access, such as cyber attacks and privacy leakage.
7. Contact EZVIZ for technical support if needed.

COPYRIGHT © Hangzhou EZVIZ Software Co., Ltd.. ALL RIGHTS RESERVED.

Any and all information, including, among others, wordings, pictures, graphs are the properties of Hangzhou EZVIZ Software Co., Ltd. (hereinafter referred to as “EZVIZ”). This user manual (hereinafter referred to as “the Manual”) cannot be reproduced, changed, translated, or distributed, partially or wholly, by any means, without the prior written permission of EZVIZ. Unless otherwise stipulated, EZVIZ does not make any warranties, guarantees or representations, express or implied, regarding to the Manual.

## **About this Manual**

The Manual includes instructions for using and managing the product. Pictures, charts, images and all other information hereinafter are for description and explanation only. The information contained in the Manual is subject to change, without notice, due to firmware updates or other reasons. Please find the latest version in the <sup>TM</sup> website (<http://www.ezviz.com>).

Revision Record New release – January, 2023 Trademarks Acknowledgement <sup>TM</sup>, <sup>TM</sup>, and other EZVIZ's trademarks and logos are the properties of EZVIZ in various jurisdictions. Other trademarks and logos mentioned below are the properties of their respective owners.

## **Legal Disclaimer**

TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, THE PRODUCT DESCRIBED, WITH ITS HARDWARE, SOFTWARE AND FIRMWARE, IS PROVIDED “AS IS”, WITH ALL FAULTS AND ERRORS, AND EZVIZ MAKES NO WARRANTIES, EXPRESS OR IMPLIED, INCLUDING WITHOUT LIMITATION, MERCHANTABILITY, SATISFACTORY QUALITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF THIRD PARTY. IN NO EVENT WILL EZVIZ, ITS DIRECTORS, OFFICERS, EMPLOYEES, OR AGENTS BE LIABLE TO YOU FOR ANY SPECIAL, CONSEQUENTIAL, INCIDENTAL, OR INDIRECT DAMAGES, INCLUDING, AMONG OTHERS, DAMAGES FOR LOSS OF BUSINESS PROFITS, BUSINESS INTERRUPTION, OR LOSS OF DATA OR DOCUMENTATION, IN CONNECTION WITH THE USE OF THIS PRODUCT, EVEN IF EZVIZ HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, IN NO EVENT SHALL EZVIZ'S TOTAL LIABILITY FOR ALL DAMAGES EXCEED THE ORIGINAL PURCHASE PRICE OF THE PRODUCT.

EZVIZ DOES NOT UNDERTAKE ANY LIABILITY FOR PERSONAL INJURY OR PROPERTY DAMAGE AS THE RESULT OF PRODUCT INTERRUPTION OR SERVICE TERMINATION CAUSED BY: A) IMPROPER INSTALLATION OR USAGE OTHER THAN AS REQUESTED; B) THE PROTECTION OF NATIONAL OR PUBLIC INTERESTS; C) FORCE MAJEURE; D) YOURSELF OR THE THIRD PARTY, INCLUDING WITHOUT LIMITATION, USING ANY THIRD PARTY'S PRODUCTS, SOFTWARE, APPLICATIONS, AND AMONG OTHERS.

REGARDING TO THE PRODUCT WITH INTERNET ACCESS, THE USE OF PRODUCT SHALL BE WHOLLY AT YOUR OWN RISKS. EZVIZ SHALL NOT TAKE ANY RESPONSIBILITIES FOR ABNORMAL OPERATION, PRIVACY LEAKAGE OR OTHER DAMAGES RESULTING FROM CYBER ATTACK, HACKER ATTACK, VIRUS INSPECTION, OR OTHER INTERNET SECURITY RISKS; HOWEVER, EZVIZ WILL PROVIDE TIMELY TECHNICAL SUPPORT IF REQUIRED. SURVEILLANCE LAWS AND DATA PROTECTION LAWS VARY BY JURISDICTION. PLEASE CHECK ALL RELEVANT LAWS IN YOUR JURISDICTION BEFORE USING THIS PRODUCT IN ORDER TO ENSURE THAT YOUR USE CONFORMS TO THE APPLICABLE LAW. EZVIZ SHALL

NOT BE LIABLE IN THE EVENT THAT THIS PRODUCT IS USED WITH ILLEGITIMATE PURPOSES. IN THE EVENT OF ANY CONFLICTS BETWEEN THE ABOVE AND THE APPLICABLE LAW, THE LATTER PREVAILS.

## **Instruction**

- The installation of EZVIZ Smart Fingerprint Lock (hereinafter referred as to “lock”) impacts its normal operation and service life. It is recommended to let professionals install, and drill hole for lock set in accordance with hole templet in appendix.
- It is recommended to remove the lock if your house is under decoration, and reinstall it after decoration in case of lock damage and service life reduction.
- Please note that disinfectant may cause damage to the lock body.
- Once initialized completed, the lock will clear all user information. After lock installation and configuration, please add fingerprint, passcode or card as needed.
- When battery voltage is low after using for a while, low voltage alarm alerts. Replace battery timely and pay attention to positive and negative poles.
- If you leave home or do not use lock for a long time, keep mechanical key with you, and do not leave it indoors. You should take battery out to ensure lock service life.
- Considering that the lock is put in an open environment, we suggest you pay attention to the safety in use, including keep properly small parts like the mechanical key or the sensing card. You should check the surrounding environment before unlocking and updating your passcode and sensing card settings on time as well in case of any danger of illegal stealing or copying of your unlocking information.
- For users with flat or thin fingerprint, it is recommended to use thumb to register fingerprint for inceasing success rate, and register more than one fingerprint with the same user. the same user supports a maximum of 5 fingerprints.
- The lock accommodates up to 100 fingerprints, 100 passcodes and 100 cards.

## **Packing List**

### **Overview**

### **Installation**

Please tap to watch the installation video.

### **Get the EZVIZ App**

1. Connect your mobile phone to 2.4GHz Wi-Fi (suggested).
2. Download and install the EZVIZ app by searching for “EZVIZ” in the App Store or Google PlayTM.
3. Launch the app and register an EZVIZ user account.

If you have already used the app, please make sure that it is the latest version. To find out if an update is available, go to the app store and search for “EZVIZ”.

### **Add the Lock to EZVIZ**

The app interface may be different due to version update, and the interface of the app you installed on your phone

shall prevail. Please add lock to EZVIZ by following steps:

1. Log in to your EZVIZ app account.
2. On the Home screen, tap “+” on the upper-right corner to go to the Scan QR Code interface.
3. Scan the QR code on the battery slot.
4. Follow the EZVIZ app wizard to add the lock to EZVIZ app account.

## **Lock Settings**

After installation, remove back cover of battery slot and install 8\*AA-sized batteries. Then you can set the lock as needed.

- Please remove protective film from lock before the first use.
- Please note that disinfectant may cause damage to the lock body.

## **Keypad**

### **Enter Menu**

Please follow these steps for settings.

In initial state, follow these steps for settings.

1. Press the SET button. or touch the keypad area to activate the lock.
2. “\*” “#” on keypad light up.
  - Press “\*” to exit.
  - Press “#” add an administrator.
3. 1 “2” “3” “\*” on keypad light up.
  - Press “1” to add a fingerprint.
  - Press “2” to add a passcode.
  - Press “3” to add a card.
  - Press “\*” to exit/ return.

In non-initial state, follow these steps for settings.

1. Press the SET button.
2. Verify with administrator’s fingerprint, passcode or card.
3. “1” “2” “3” “4” “\*” on keypad light up.

## **Menu Index**

The menu here is for reference only.

### **Add Administrators/Users**

1. Enter the menu.(For detailed operations, please refer to “Enter Menu”)

2. Press “1” to add an administrator, or press “2” to add a user.

Ordinary users can only unlock the door after entering the opening method; the administrator can not only unlock the door, but also log in to the menu to add and delete users and operate other settings.

When you add an administrator or a user, the figures corresponded to the user number will light up from 001 by default ( for example, to user number 001, the three numbers 001 will slow-flash once in sequence).

### **Delete Administrators/Users**

1. Enter the menu.(For detailed operations, please refer to “Enter Menu”)
2. Press “3” to delete an administrator/a user.
3. Enter the user number and press #.
  - If you pressed a wrong user number, the number “1, 3, 5, 7, 9” (seems like a X ) on the keypad will light up and flash 2 times, accompanied by a failure beep. Press “\*” to return to last step, or enter the user numbers to delete again.
  - When there is only one user left, and you operate to delete it, the number “1, 3, 5, 7, 9” (seems like a X ) on the keypad will light up and flash 2 times, accompanied by a failure beep.

### **Look Up to the System Information**

1. Enter the menu. (For detailed operations, please refer to “Enter Menu”)
2. Press “4” to look up to the system information of the lock.
3. The lock broadcast the system information.

The lock will broadcast the lock serial number, the current device version and verification code in English in turn, press \* to return to the previous level. Or the system will return to the previous level automatically after the successful broadcast.

### **Add Fingerprint**

1. Enter the menu.(For detailed operations, please refer to “Enter Menu”)
2. Press “1” to add an administrator, or press “2” to add a user.
3. Press “1” to add a fingerprint.
4. When “1” lights up, touch the fingerprint reader and repeat the operation 6 times, 1~6 light up one by one, accompanied by a success beep, the fingerprint is successfully added.
5. Press “1” to add fingerprints continuously.  
Press the \* key to return to the previous level.  
Press the SET button to exit.

### **Add Passcode**

1. Enter the menu.(For detailed operations, please refer to “Enter Menu”)
2. Press “1” to add an administrator, or press “2” to add a user.
3. Press “2” to add a passcode.

4. Enter the corresponding 6-10 digit valid passcode .when the passcode input key  $\geq 6$  digits, “#” lights up at this time, press “#” to confirm.
5. Repeat the passcode once again, press “#” to confirm, accompanied by a success beep, the passcode is successfully added.

### **Add Card**

1. Enter the menu.(For detailed operations, please refer to “Enter Menu”)
2. Press “1” to add an administrator, or press “2” to add a user.
3. Press “3” to add a card.
4. Place the unrecorded proximity card on the card swipping area.
5. Press # key to confirm.  
Press \* key to return to the previous level.

### **Finish the Wi-Fi Configuration**

- Press and hold the SET button for more than 3s. When “0” starts flashing accompanied by a beep, it means the Wi-Fi configuration mode is turned on.

Please follow the system guide to finish the Wi-Fi Configuration in 5minutes.

The system will exit the Wi-Fi configuration mode automatically after 5minutes.

### **Lock Using**

#### **Multiple Unlock Methods**

- When opening the door by mechanical key, rotate the key and down press the handle.
- Please touch the keypad area to activate the lock before opening the door by passcode.
- For your privacy security, it is recommended to change passcodes and clean keypad area regularly in case of remaining marks.

#### **Fingerprint Unlock**

- This product has security protection function, fingerprint recognition error number reaches 5 times continuously in 5minutes, the system will be locked forcibly for 3 minutes.
- The system will be unlocked automatically after 3 minutes.
- You can turn off this function in EZVIZ app.
  1. Put your finger on the fingerprint reader.
  2. When you hear the voice prompt, put down the handle to open the door.

#### **Passcode Unlock**

- This product has security protection function, passcode recognition error number reaches 5 times continuously in 5 minutes, the system will be locked forcibly for 3 minutes.

- The system will be unlocked automatically after 3 minutes.
- You can turn off this function in EZVIZ app.
- The product has protect with Anti-Peeping Passcodes. In case someone is watching you entering a passcode, you can add extra-long digits before or after your original code to make it complex, while still being able to unlock.
  1. Touch to wake up the keypad.
  2. Enter the passcode and press #.
  3. When you hear the voice prompt, put down the handle to open the door.

## Card Unlock

- This product has security protection function: card recognition error number reaches 5 times continuously in 5 minutes, the system will be locked forcibly for 3 minutes.
- The system will be unlocked automatically after 3 minutes.
- You can turn off this function in EZVIZ app.
  1. Place the recorded proximity card on the card swipping area.
  2. When you hear the voice prompt, put down the handle to open the door.

## Mechanical key Unlock

Please keep the mechanical key properly for further use.

1. Open the cover of the mechanical keyhole: Press the bottom of the cover and rotate it.
2. Insert the key and turn to unlock.

## Operation and Management

### Emergency Unlock

When battery is out of power, connect the emergency power supply interface of the front panel with power bank to charge the lock through micro-USB power cable and then unlock the door.

### Install Battery

1. Install battery: remove battery cover, install 8\*AA-sized batteries in battery slot, and tighten battery cover.
2. **Note:** Install correct batteries in case of explosion.
  - When not using batteries for a long time, remove them from battery slot.
  - Do not use new batteries with old ones.
  - Do not place battery with the (+) and (-) in the wrong way around.
  - Dispose used batteries according to the local environmental protection law.

## Alarms

### 1. Anti-tamper Alarm

Once being dismantled by force, the lock will send out alarm lasting about one minute.

