

FONESTAR PF-27TD Bidirectional Sound Projector User Guide

Home » Fonestar » FONESTAR PF-27TD Bidirectional Sound Projector User Guide The Projector User G



BIDIRECTIONAL SOUND PROJECTOR



QUICK START GUIDE

Contents

- 1 DESCRIPTION
- **2 CONNECTION EXAMPLE**
- **3 INSTALLATION**
- **4 TECHNICAL**
- **SPECIFICATIONS**
- 5 Documents / Resources
 - **5.1 References**

DESCRIPTION


- Bidirectional sound projector with great features, design and construction
- Its features make it suitable for indoor or outdoor public address installations, with IP55 protection
- For PA and background music in 100 V line installations in shopping centres, schools, hospitals, sports facilities, industrial warehouses, etc

IMPORTANT

• For proper functioning and performance, use appropriate power, impedance and frequency limits. Before connecting to other equipment, take into account the necessary conditions for a HIGH IMPEDANCE installation (100 V line).

Further information can be found at: fonestar.com/downloads/install_fonestar_en.pdf

CONNECTION EXAMPLE






Insulate any unused cables separately.

POWER		IMPEDANCE	CABLE
100 V	70 V	INIFEDANCE CABLE	
20 W	10 W	500 Ω	RED
10 W	5 W	1,000 Ω	GREEN
5 W	2.5 W	2,000 Ω	YELLOW
COM: BLUE	,		

INSTALLATION



TECHNICAL SPECIFICATIONS

POWER:	30 W maximum, 20 W RMS	
LOUDSPEAKERS:	2 x 5", varnished cardboard cone	
RESPONSE:	180-16,000 Hz	
IMPEDANCE:	20 W RMS@100V (500 Ω) 10 W RMS@100V (1.000 Ω) 5 W RMS@100V (2.000 Ω)	
SENSITIVITY:	86 dB at 1 W/1 m	
DISPERSION:	Bidirectional 170°@1kHz, 100°@2kHz, 60°@4kHz (-6dB)	
PROTECTION:	IP55 in compliance with EN 60529	
MATERIAL:	ABS. Hermetic casing Aluminium mount and grille Stainless steel screws	
TEMPERATURE RANGE:	-25°C ~ 55°C	
DIMENSIONS:	138 mm Ø x 200 mm depth	
ACCESSORIES:	Adjustable fixing mount	



Documents / Resources



FONESTAR PF-27TD Bidirectional Sound Projector [pdf] User Guide

PF-27TD Bidirectional Sound Projector, PF-27TD, Bidirectional Sound Projector, Sound Project or, Projector

References

- F Somos Fonestar Otra forma de entender la megafonía
- User Manual

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.