



# **gembird Bluetooth Keyboard TD-KBBT-DE User Manual**

[Home](#) » [GEMBIRD](#) » gembird Bluetooth Keyboard TD-KBBT-DE User Manual 

**gembird Bluetooth Keyboard TD-KBBT-DE**  
**User Manual**



# **gembird®**

## **USER MANUAL**

**TD-KBBT-DE**



## **BLUETOOTH KEYBOARD**

### **Features**

- Slimline Bluetooth keyboard
- Smooth keystroke for more comfortable typing
- Practical multimedia buttons
- Works with most smartphones, tablets and PC's
- Long battery life

### **Specifications**

- Interface: Bluetooth v.5.0
- Working distance: up to 10 m
- Battery: 2x replaceable AAA-battery
- Power consumption: 1.5 V DC up to 8 mA

- Dimensions: 287 x 137 x 20 mm
- Weight 300 g



## GETTING STARTED

### 1. BUTTONS

- On/Off slider switch: Turn the power on or off.
- Bluetooth connect button: When the unit is powered On, press the [connect] button, the keyboard is now ready to be connect to your device (e.g. computer, smartphone, tablet, game console, etc).

### 2. LED DISPLAY

The icon will flash blue ( $\pm 3$  min. long) after pressing the “connect” button until a BT connection is established. It disappears when connected.

Low power: The blue light will rapidly flash when the battery is weak and batteries need be replaced.

Power: The blue light will light up  $\pm 4$  seconds when the unit is turned on.

### 3. SYSTEM REQUIREMENTS

- iPad, iPhone – All versions
- Bluetooth-enabled PCs or Laptops with Windows XP ~10
- Bluetooth-enabled iMac / Macbooks with Mac OS X 10.2.8 or above (note that some exceptions may apply. This keyboard may not be compatible with the Mac mini.
- Smartphones or tablets with Android 3.0 and above (with Bluetooth HID profile)
- Windows Mobile 5.0 and above

### 4. PAIRING KEYBOARD METHODS

Pairing with an iPad/ iPhone

- Step 1: On the keyboard, slide the power button to on. The blue status light will illumination for 4 seconds and then turn off to save power.

Note: your keyboard is still on.

- Step 2: Press the [connect] button, the [Bluetooth] indicator light will be blinking blue.

- Step 3: On the iPad/iPhone, select: Setting- General- BluetoothOn.

- Step 4: The iPad/iPhone will display “Bluetooth keyboard” as an available device.

- Step 5: Select “Bluetooth keyboard”; the iPad/iPhone will display a code.

- Step 6: Type the code on the keyboard and press enter; keyboard will now be paired to the iPad/iPhone. Pairing with Tablets Smartphones, Laptop and Desktop computers, etc.

- Step 1: On the keyboard, slide the power button to on. The blue status light will illumination for 4 seconds and then turn off to save power.

Note: your keyboard is still on.

- Step 2: Press the [connect] button, the [Bluetooth] indicator light will be blinking blue.

- Step 3: Go to your “settings” screen on your tablet, laptop, smartphone or other Bluetooth – enabled devices and go to the Bluetooth setting menu and activate its Bluetooth function and search for the keyboard.
- Step 4: Once the Bluetooth keyboard has been found, select its name to connect.
- Step 5: Enter the password code as displayed on the screen.
- Step 6: Once the Bluetooth keyboard has successfully been connected to your device, the Bluetooth indicator will turn off.















**NOTE:**

- Only one device can be actively paired at one time.
- After pairing for the first time, your device will connect to the keyboard automatically when switching on the keyboard.
- In case of connection failure, delete the pairing record from your device, and try the above pairing procedures again.

**POWER SAVING MODE**

The keyboard will enter into the sleep mode after being idle for 15 minutes. To activate the keyboard, press any key and wait 3 seconds.

**5. FUNCTIONAL KEYS**

Keys	Fn on Android	For All w/o Fn	Fn on Windows	Fn on iOS
	Home	ESC		Home
	Return	F1		Brightness down
	Email	F2		Brightness up
	Menu	F3		Virtual Keyboard
	Media player	F4		Screen Capture
	Search	F5	Search	Search
	Language exchange	F6		Language exchange
	Previous track	F7	Previous track	Previous track
	Play/pause	F8	Play/pause	Play/pause
	Next track	F9	Next track	Next track
	Mute	F10	Mute	Mute
	Volume down	F11	Volume down	Volume down
	Volume up	F12	Volume up	Volume up
	Screen Lock	Delete		Screen Lock

#### NOTE:

Press Fn and Q (iOS), W (Android) or E (Windows) keys together to shift between Android, Windows or iOS systems after connected successfully with a corresponding device. Otherwise the keyboard's function key will only be partial valid. For IOS system, the Language Exchange function does not work below version 9.2, you can press "command + Space" keys to exchange language.

## Declaration of conformity

This product is tested and complies with the essential requirements of the laws of member states concerning RED (2014/53/EU), RoHS (2011/65/EU). The CE declaration can be found under [www.gembird.eu](http://www.gembird.eu)

## Waste disposal:

Do not deposit this equipment with the household waste. Improper disposal can harm both the environment and human health. For information about waste collection facilities for used electrical and electronic devices, please contact your city council or an authorized company for the disposal of electrical and electronic equipment.

## WARRANTY CONDITIONS

The receipt must clearly list the date of purchase and the part number, in addition it should be printed. Keep the receipt for the entire warranty period since it is required for all warranty claims. During the warranty period the defective items will be credited, repaired or replaced at the manufacturer's expense. Work carried out under the warranty neither extends the warranty period nor starts a new warranty period. The manufacturer reserves the right to void any warranty claim for damages or defects due to misuse, abuse or external impact (falling down, impact, ingress of water, dust, contamination or break). Wearing parts (e.g. rechargeable batteries) are excluded from the warranty. Upon receipt of the RMA goods, Gembird Europe B.V. reserves the right to choose between replacement of defective goods or issuing a credit note. The credit note amount will always be calculated on the basis of the current market value of the defective products. Gembird Europe B.V. Wittevrouwen 56, 1358CD Almere, The Netherlands [www.gembird.nl/service\\_support@gmb.nl](http://www.gembird.nl/service_support@gmb.nl)


**GEMBIRD EUROPE B.V.** <http://www.gembird.eu>

All brands and logos are registered trademarks of their respective owners

### Contents

- [1 Documents / Resources](#)
- [2 Related Posts](#)

## Documents / Resources

	<a href="#">gembird Bluetooth Keyboard TD-KBBT-DE</a> [pdf] User Manual gembird, TD-KBBT-DE, Bluetooth, Keyboard
---	---