



Contents [[hide](#)]

- [1 hager 75144860 Touch Sensor](#)
- [2 Specifications](#)
- [3 Product Usage Instruction](#)
- [4 Use Conditions](#)
- [5 Dimensions](#)
- [6 Accessories](#)
- [7 Additional Features](#)
- [8 FAQ](#)
- [9 Documents / Resources](#)
 - [9.1 References](#)

hager

hager 75144860 Touch Sensor



Specifications

- Product Code: 75144860
- Type: Touch sensor, 4-gang comfintg bus coupling unit, KNX – R.1, glass p. white
- Installation: Flush mounting
- Operating Temperature: Temperature
- Power Consumption: 12.50 mA
- Built-in Depth: 12.90 mm
- Built-in Depth for Flush-mounted Boxes: 16 mm
- Dimensions: Height – 152 mm, Width – 81 mm, Depth – 23 mm
- Number of Actuation Points: 8
- Controls and Indicators: LED indication
- Material: Glass with glossy finish
- Accessories: Labelling field
- Screen: With display

Product Usage Instruction

Touch sensor, 4-gang comf, intg bus coupling unit, KNX – R.1, glass p. white

Technical characteristics

Installation and Mounting:

- Mount the touch sensor on a flush-mounted box using the provided instructions. Ensure proper installation for optimal performance.
- Mounting on Flush mounting

Use Conditions

- Operate the touch sensor within the specified temperature range for efficient functionality.
- Operating temperature -5 – 45 °C

Functions:

- The touch sensor is designed to work with a room temperature controller for enhanced control and automation.
- With room temperature controller Yes

Power Consumption:

- The touch sensor has a current consumption of 12.50 mA.
- Current consumption 12.50 mA

Dimensions

- Built-in depth 12.90 mm
- Built-in depth flush-mounted boxes 16 mm
- Height 152 mm
- Width 81 mm
- Depth 23 mm

Equipment

- Number of actuation points 8

Controls and indicators

- With LED indication Yes

Materials

- Colour Polar white
- RAL code 9010
- Material Glass
- Surface finish Glossy

Accessories

- Has labelling field No
- Screen With display Yes

Texts

- Function For switch, push-button, dimmer and shutter functions, Blocking function for sensor surface e.g. for cleaning the glass surface
- Installation mode For vertical mounting

Temperature

Additional connection for external temperature sensor, Integrated temperature sensor for operation as controller extension unit, Temperature measurement via internal Temperature sensor or external communication object

Additional Features

- Supports switch, push-button, dimmer, and shutter functions
- Blocking function available for sensor surface cleaning
- Suitable for vertical mounting

FAQ

- **Q: Can the touch sensor be used outdoors?**

A: No, the touch sensor is designed for indoor use only.


- **Q: How do I reset the touch sensor?**

A: To reset the touch sensor, refer to the user manual for specific instructions on resetting or recalibrating the device.

• **Q: Is the touch sensor compatible with all types of lighting systems?**

A: The touch sensor is compatible with most standard lighting systems, but it is recommended to check compatibility with specific systems before use.

Documents / Resources





[hager 75144860 Touch Sensor \[pdf\]](#) User Guide

75144860, 75144860 Touch Sensor, 75144860, Touch Sensor, Sensor

References

- [User Manual](#)

 75144860, 75144860 Touch Sensor, hager, Sensor, Touch

 hager Sensor

Leave a comment

Your email address will not be published. Required fields are marked *

Comment *

Name

Email

Website

☐ Save my name, email, and website in this browser for the next time I comment.

Post Comment

Search:

e.g. whirlpool wrf535swhz

Search

[Manuals+](#) | [Upload](#) | [Deep Search](#) | [Privacy Policy](#) | [@manuals.plus](#) | [YouTube](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.