



InWin Chopin MAX Mini ITX Tower User Manual

[Home](#) » [InWin](#) » InWin Chopin MAX Mini ITX Tower User Manual 



Contents

- [1 Product Video Information](#)
- [2 Product Story](#)
- [3 Specifications](#)
- [4 Package Contents](#)
- [5 Accessories Bag](#)
- [6 Case Structure](#)
- [7 Connection Cables](#)
- [8 Notices and Warranty](#)
- [9 Documents / Resources](#)
 - [9.1 References](#)
- [10 Related Posts](#)

Product Video Information

Chopin MAX Product Video	Chopin MAX Installation Guide Video
	
https://youtu.be/0uTF3Pt7Dig	https://youtu.be/9B5LO5S2uNw

Product Story

Luxe Little Legend

The Chopin MAX is an ultra slim form factor case designed with the intention of being a multifaceted PC case with a small footprint. Uncompromised quality and functionality developed in a 3.3-liter chassis. Chopin MAX features a 4 mm brushed aluminium shell that completes a clean and sleek chassis frontal.



Specifications

InWin Chopin MAX Chassis

Model	Chopin MAX
Model Number	IW-CS-CHOPINMAXGRE-PS200W IW-CS-CHOPINMAXBLK-PS200W IW-CS-CHOPINMAXSIL-PS200W
Colors	Titanium Grey, Black, Silver
Case Type	Mini-ITX Tower
Materials	Aluminium, SECC
M/B Compatibility	Mini-ITX
I/O Ports	1 x USB 3.2 Gen 2x2 Type-C 2 x USB 3.2 Gen 1 HD Audio
CPU Heatsink Height	Up to 54 mm
Internal Drive Bays	2 x 2.5" (H 9.5 mm Max.)
Power Supply Compatibility	InWin 200W 80 PLUS Gold PSU Included
Product Dimensions (L x W x H)	217 x 84 x 244 mm 8.54 x 3.3 x 9.6"
Package Dimensions (L x W x H)	270 x 120 x 276 mm 10.6 x 4.72 x 10.8"
Net Weight	2.2 kg / 4.85 lbs
Gross Weight	2.5 kg / 5.5 lbs

* InWin's products comply with RoHS regulations.

* Specifications may vary based on different regions.



InWin 200W 80PLUS GOLD PSU

Model	IP-AD200C7-2
Total Power	200W
Material	SECC
Type	ITX
PFC	Active PFC
Efficiency	80 PLUS Gold
MTBF (Hours)	> 100,000
AC Input	100 – 240 Vac. 50-60Hz
Operating Temperature Range(° C)	0~40° C
Full Protection	OVP / UVP / SCP / OPP
Safety Certifications	TUV / cTUVus / BSMI / CB / CE / FCC / EAC / RCM / CCC
Dimensions (L x W x H)	52 x 40 x 170 mm 2.05 x 1. x 6.7"
Warranty	3 Years
Connectors	20+4 Pin Motherboard 1 8 (4+4) Pin CPU 1 8 (6+2) Pin PCI-E 0 4 Pin Peripheral 0 SATA (90 Degree) 1 Floppy 0

* InWin's products comply with RoHS regulations.

* Specifications may vary based on different regions.

Package Contents




<https://www.in-win.com/en/manual/gaming-chassis/c>

Accessories Bag

Hexagon Head Screw x 5	2.5" SSD Screws x 8
	
SATA Power Y Splitter Cable x 1	Side Panel Mylar (Red, Green, Blue, Orange) x 4 Set
	


Case Structure




1. 2.5" Drive Bay
2. Motherboard Mounting Area
3. 200W 80 PLUS Gold PSU Included
4. Power Button
5. USB 3.2 Gen 2x2 Type-C
6. USB 3.2 Gen 1
7. Audio Ports (Earphone and Microphone)
8. Power Indicator
9. HDD Indicator
10. M.2 SSD Installation Cut-Out Hole

Connection Cables


I/O Wires x1




HD Audio Header x1



USB 3.2 Gen 1 x1



USB 3.2 Gen 2x2 Type-C x1



Notices and Warranty

Notices

1. Please follow the user manual for installation guidelines.
2. When installing computer components, please use the antistatic precautions to prevent ESD (electrostatic discharge) damage. This can cause injury to the installer and/or damage to the machine. Incorrect installation may burn your motherboard and other system components.
3. To avoid any damages, please do not use this product for any other purpose than its intended use.
4. Any modifications may damage the product.
5. Please remove all internal devices before shipping or moving. (Including power supply, hard drives, CD-ROM, motherboard and CPU, etc)
6. When storing the case, please keep this product away from high temperatures.
Keep away from machines such as heaters that might cause high temperatures.
7. For more technical support, please visit the InWin Forum at <https://forum.in-win.com/>

Warranty

1. For more detailed warranty information, please visit the InWin retail website at www.in-win.com
2. The actual product is subject to change without prior notice.
In Win Development Inc. reserves the right to make any final modifications.




CONTEMPRARY & INNOVATIVE

www.in-win.com

Copyright © 2022 In Win Development Inc. All Rights Reserved.

Documents / Resources



[InWin Chopin MAX Mini ITX Tower](#) [pdf] User Manual

Chopin MAX, Mini ITX Tower, Chopin MAX Mini ITX Tower, ITX Tower, Tower, IW-CS-CHOPIN MAXGRE-PS200W, IW-CS-CHOPINMAXBLK-PS200W, IW-CS-CHOPINMAXSIL-PS200W

References

- in-win.com
- forum.in-win.com/

