

IP VOICE IPV79P,IPV59R Dect IP Phone



IP VOICE IPV79P,IPV59R Dect IP Phone User Guide

[Home](#) » [IP VOICE](#) » IP VOICE IPV79P,IPV59R Dect IP Phone User Guide 

Contents

- [1 IP VOICE IPV79P,IPV59R Dect IP Phone](#)
- [2 OVERVIEW](#)
- [3 Basic Operations](#)
- [4 Put a Call on Hold](#)
- [5 Listen to Your Voice Messages](#)
- [6 Documents / Resources](#)
 - [6.1 References](#)

IP VOICE

IP VOICE IPV79P,IPV59R Dect IP Phone





OVERVIEW





Basic Operations



Turning Handset On/Off:

- Press  then the LCD screen lights up.
- Place the Handset in the charger cradle to turn on automatically.
- Long press  again to turn the Handset off.






Locking/Unlocking keypad:

- Long press  when the Handset is idle to lock the keypad.
- Long press  again to unlock the keypad.




Switching Silent Mode On/Off:

- Long press  when the Handset is idle to lock the keypad.
- Long press  again to unlock the keypad.

Make a Call

- Enter the desired number when the handset, then press .
 - To place a call from the local directory
1. Press  when the handset is idle.
 2. Select the directory.
 - Internal use directory
 - External use LDAP
 - Press  or  to highlight the desired entry, and then then press .



Answer a Call, do one of the following:

- Press the Accept soft key.
- Alternatively, press ,  or .

Put a Call on Hold

1. Press the Options soft key during a call, and then select Hold.
2. To resume the call, press the Resume soft key.


Access the Directory

- Press the  key to enter the main menu, and then select Directory OR
- When the Handset is idle press .



Transfer a Call to Another Person

1. Press the Options soft key during the call, and then select Transfer.
2. Enter the number you want to transfer the call to.
3. Press the Transfer soft key.

Make a Call with the Speakerphone

- Enter a number using the keypad.
- Press Speakerphone 

Mute Your Audio

1. Press  during a call to mute the call.
2. Press  again to turn the mute off.



To end a Call

- Press  .

Listen to Your Voice Messages

- Press the Messages keys and follow the voice prompts. To check messages for a specific line, press the line button first.

Adjust the Volume in a Call

- Whilst on call, press  or 




Adjust the Ringtone Volume

- Whilst on call, press 4 or *




Call Pickup

- Dial *88

View Call History

1. Press History
2. Press  or  highlight the desired entry, and then press  .

Redial

- 1. Press the green call button.
- 2. Press  or  highlight the desired entry, and then then press  .

Documents / Resources



[IP VOICE IPV79P,IPV59R Dect IP Phone](#) [pdf] User Guide
IPV79P IPV59R, IPV79P IPV59R Dect IP Phone, Dect IP Phone, IP Phone, Phone

References

- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.