

KOHLER 10RESV RESV Generators



KOHLER 10RESV RESV Generators Instructions

[Home](#) » [Kohler](#) » KOHLER 10RESV RESV Generators Instructions 

Contents

- [1 KOHLER 10RESV RESV Generators](#)
- [2 Product Usage Instructions](#)
- [3 INTRODUCTION](#)
- [4 SPECIFICATION](#)
- [5 Documents / Resources](#)
 - [5.1 References](#)

KOHLER®

KOHLER 10RESV RESV Generators



Product Usage Instructions

Installation:

Ensure the generator is placed on a level surface with proper ventilation according to NFPA-37 compliance.

Connection:

Connect the generator to your home's electrical system using a transfer switch installed by a certified electrician.

Fuel Source:

Ensure a steady supply of either LPG or NG fuel sources based on your generator model.

Monitoring:

Download and set up the Kohler mobile app to monitor your generator system remotely for peace of mind.

FAQ:

Q: What is the warranty coverage for the RESV generators?

A: The RESV generators come with a Five-Year Premium Limited Warranty covering parts, labor, and dealer travel for the full warranty period.

Q: Can the generator be placed close to structures?

A: Yes, the RESV generators have an 18-inch reduced setback requirement from any structure as per NFPA-37 compliance.

Q: How do I handle maintenance for the generator?

A: Regular maintenance tasks include checking fuel levels, oil changes, and air filter replacements as per the user manual instructions.

Reliable Home Standby Power

Our 10- and 12-kW generators offer quiet, reliable performance in a compact footprint that provides maximum flexibility for installation on smaller lots

INTRODUCTION

PowerBoost™ Technology

Only Kohler has PowerBoost technology, which enables our 10- and 12-kW generators to accept heavy loads (like air conditioning or sump pump) without dropping power to other loads in your home. In addition, KOHLER® generators will have your home powered within ten seconds of an outage.

Get Connected

Get your generator Internet-connected to get peace of mind in the palm of your hand. Whether you're home or on the go, Kohler's mobile app will let you monitor your generator system anytime from anywhere and get instant updates via text or email.

Commercial-Grade KOHLER Engine

Every KOHLER generator features a heavy-duty engine built to exceed the demands of standby power.

Premium Warranty

You get our 2,000-Hour Five-Year Premium Limited Warranty, covering parts, labor, and dealer travel for the full warranty period. Optional extended warranties are also available.

Compact Footprints

RESV generators offer smaller footprints and ample power for the necessities during an outage. They are also

NFPA-37 compliant to have an 18-inch setback from any structure.

SPECIFICATION


	10 kW	12 kW
Model Number	10RESV	12RESV
Rated Power LPG/NG	10/9	12/11
Voltage @ 60 Hz Single-Phase	120/240	120/240
Amps LPG/NG @ 240 V Single-Phase	41.7/37.5	50/45.8
Engine/Alternator RPM	3600	3600
Three-Phase Available	No	No
Engine	725 CC	725 CC
	21.4 HP	21.4 HP
	KOHLER 7000 Series OHV KT725	KOHLER 7000 Series OHV KT725
	V-Twin	V-Twin
	Solid Pushrods	Solid Pushrods
Peak Motor Starting kVA at 240 V (35 % Dip for Lower Voltages)	16.8	16.8
Fuel	LPG/NG	LPG/NG
Engine Cooling	Air-Cooled	Air-Cooled
Fuel Pressure Requirement (in H ₂ O)	NG 3.5-11	NG 3.5-11
	LP 7-11	LP 7-11
Enclosure	Powder-Coated Steel	Powder-Coated Steel
Single-Point Sound Output dBA at 23 Ft (During Exercise/ Normal Operation) *	64/69	64/69
Dimensions (Inches)	28 x 30 x 32	28 x 30 x 32
Digital Voltage Regulation	+/- 1.0%	+/- 1.0%
Excitation	PowerBoost—Brushed With Aux Winding	PowerBoost—Brushed With Aux Winding
Warranty	Five-Year Premium Limited	Five-Year Premium Limited
18-Inch Reduced Setback	Yes	Yes
Mossy Oak Patterns	No	No
Kohler Color Options	No	No

Single-point sound levels are the lowest of eight points measured around the generator. Sound levels are measured at the front of the generator.
Actual sound levels may vary based on installation parameters.

KohlerGenerators.com

PRINTED IN U.S.A WF441553 G12-435 11/23 © KOHLER CO.

Documents / Resources

	<p>KOHLER 10RESV RESV Generators [pdf] Instructions 10RESV, 12RESV, 10RESV RESV Generators, RESV Generators, Generators</p>
---	---

References

- [K Home Generators | KOHLER](#)
- [User Manual](#)

Manuals+. Privacy Policy

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.