

Linear Gate Openers CSI724 Ornamental Privacy Slats Instruction Manual

Home » Linear Gate Openers » Linear Gate Openers CSI724 Ornamental Privacy Slats Instruction Manual



Contents

- 1 Linear Gate Openers CSI724 Ornamental Privacy
- **2 Product Specifications**
- **3 Product Usage Instructions**
- 4 Installation
- **5 CAUTION**
- **6 CONTACT**
- 7 FAQs
- 8 Documents / Resources
 - 8.1 References
- 9 Related Posts

Linear Gate

Linear Gate Openers CSI724 Ornamental Privacy Slats



Product Specifications

· Material: Aluminum

• Usage: Provides 100% privacy or acts as a louver for airflow

• Tools Required: Miter saw or band saw, rubber mallet

Product Usage Instructions

Measurement:

Measure the area of the fence where you want to install the privacy slats. Measure from the bottom of the channel to the top of the channel for accurate dimensions. Cut the pickets 1/4 shorter than the measured length to allow for expansion.

Cutting and Installation:

Use a miter saw or band saw to cut the panels, extender clips, and locks to size. Snap the panels onto the fence by prying open the top and aligning with the picket. Ensure a secure fit all the way down.

Completing Installation:

Continue snapping on the privacy picket panels until the entire fence is covered. For permanent privacy, use the Hurricane U-Lock at the back of the panels. The U-Locks can be easily removed or added based on your privacy preferences.

Installation

Our aluminum fence slats can be used for either 100% privacy or as a louver in order to guide air into your fenced-in area.

Tools that will be needed to cut and install the privacy panels:



- 1. Miter saw or other kind of band saw.
 - 1. If using a miter saw, make sure to reverse the blade. This will ensure you give a smooth cut and not chip

the PVC.

- 2. Rubber mallet to tap with.
 - 1. Measure the area of the fence that you would like the privacy picket panels to cover (all manufacturers vary) so this is very important to measure the length of your pickets. Measure from the bottom of your channel to the top of your bottom channel This will give you the dimensions to start cutting your pickets. We recommend using your measurement and then cutting 1/4" shorter, allowing for expansion.
 - 2. Cut the panels, extender clips and lock to size and start snapping them onto the fence. Take your fingers and pry open the top of the privacy panels. Line up with the picket and simply snap on. Make sure it is secured all the way down.
 - 3. Continue to snap on all privacy picket panels until the entire fence is completed. If you want your fence to stay private at all times, use the Hurricane U-Lock to snap on the back of the privacy panels. The U-Locks can be removed or put on at any time, depending on the level of privacy you want or if you desire to have them open for a breeze or view.

CAUTION

IMPORTANT INSTALLATION INFORMATION:

- Do not store or leave exposed panels in direct sunlight.
- Keep privacy picket panels covered until you are ready to cut and attach to the fence pickets.
- Open the boxes from the side to avoid damaging the panels.
- Only install when above freezing.
- Cut panels and clips 1/4" shorter for expansion.

CONTACT

www.LinearGateOpeners.com | 800-878-7829 | Sales@LinearGateOpeners.com

FAQs

- Q: Can the privacy panels be easily removed?
 - **A:** Yes, the privacy panels can be easily removed by unsnapping them from the fence.
- Q: How do I clean the aluminum fence slats?
 - A: Use a mild detergent and water solution to clean the slats.
 Avoid using abrasive cleaners that may damage the finish.

Documents / Resources



<u>Linear Gate Openers CSI724 Ornamental Privacy Slats</u> [pdf] Instruction Manual CSI724 Ornamental Privacy Slats, CSI724, Ornamental Privacy Slats, Privacy Slats

References

- Index of /
- User Manual

Manuals+, Privacy Policy

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.