



# LogiLink SH0108 Wireless Smart Door Window Sensor Owner's Manual

[Home](#) » [LogiLink](#) » LogiLink SH0108 Wireless Smart Door Window Sensor Owner's Manual 

## Contents

- 1 SH0108 Wireless Smart Door Window Sensor
  - 1.1 Wireless Smart Door/Window Sensor
  - 1.2 Build Your Smart Home
  - 1.3 App Remote Monitor
  - 1.4 Security to Your Home or Warehouse
  - 1.5 Remote Monitor from Anywhere
  - 1.6 Security Automation
  - 1.7 Specifications:
  - 1.8 Package Contents:
  - 1.9 Package Information:
- 2 Documents / Resources
- 3 Related Posts

**SH0108 Wireless Smart Door Window Sensor**

## Wireless Smart Door/Window Sensor



Art. No.: SH0108

### Build Your Smart Home

Detect whether a door, window, cabinet or garage door is opened or closed and notify you via free smartphone app using Wi-Fi connection.



### App Remote Monitor



Smart Door/Window Sensor can be monitored through your existing Wi-Fi network via the free Smart Life or Megos Smart Home app.



### Smart Life Megos Smart Home

Download the free APP from the App Store or Google Play store.



Wi-Fi  
2.4 GHz



Security  
System



Contact  
Sensor



Push  
Notification



Easy  
Installation



2x AAA  
Batteries

\*The specifications and pictures are subject to change without prior notice.



### Security to Your Home or Warehouse

Detects open/close of door, window, cabinet, garage door and send instant alert notification to your smartphone.



### Remote Monitor from Anywhere

Monitor your house from anywhere with your phone via the app, even if you're not at home.



### Security Automation

Connect with other LogiLink Smart products like Siren Alarm (SH0110) and IP Camera (SH0117) in automations to create a safer home.

### Specifications:

**Wireless Standard** IEEE 802.11b/g/n

**Wireless Frequency Range** 2,412–2,472 MHz

**Max. Transmission Power** 39.811 mW

**Max. Transmit Antenna Gain** 2.2 dBi

**Rated Voltage DC** 2.6–3.3 V

**Power By** 2x AAA batteries

**Max. Power Consumption** 0.5 W

**Operation Distance (In Open Area)** 50 m

**Sensor Detection Distance** ≤15 mm

**Protection Class** IP30

**Operating Temperature** -10–50°C

**Operating Humidity** 5–95% RH (non-condensing)

**Color** White

**Product Dimension** 7 x 2.5 x 1.9 cm (Host) 3.25 x 0.9 x 1.9 cm (Sensor)

**Weight** 24 g

**System Requirements** Android 5 or above / iOS 11 or above

**Mounting Method** Fix with nails or double sided tapes

**Package Contents:**

- » 1x Wi-Fi Smart Door/Window Sensor
- » 2x AAA Batteries
- » 2x Double Sided Tapes
- » 1x User Manual

**Package Information:**

- » Packing Dimension: 91 x 71 x 23 mm
- » Packing Weight: 0.085 kg
- » Carton Dimension: 260 x 250 x 195 mm
- » Carton Q'ty: 50 pcs
- » Carton Weight: 4.5 kg

\* The specifications and pictures are subject to change without prior notice.

\* All trade names referenced are the registered trademarks of their respective owners.



**Documents / Resources**



[LogiLink SH0108 Wireless Smart Door Window Sensor](#) [pdf] Owner's Manual  
SH0108, SH0108 Wireless Smart Door Window Sensor, Wireless Smart Door Window Sensor,  
Smart Door Window Sensor, Window Sensor