

Lorex 4k Ultra HD Smart Network Video Recorder With Fusion **Specifications Manual**

Home » Lorex » Lorex 4k Ultra HD Smart Network Video Recorder With Fusion Specifications Manual



Contents

- 1 Lorex 4k Ultra HD Smart Network Video Recorder With **Fusion**
 - 1.1 Features
 - 1.2 Product Specifications
 - 1.3 Model Information
 - 1.4 Dimensions
 - 1.5 Back Panel
 - 1.6 What's in the box
- **2 Related Posts**

Lorex 4k Ultra HD Smart Network Video Recorder With Fusion



4K Quality with Extensive Storage and Lorex Fusion Compatibility

Record and view impressive 4K video resolution with a heightened level of detail and definition. As part of the Lorex Fusion™ collection you can tailor your security system to your needs, by pairing with both wired and Wi-Fi cameras of your choice, such as video doorbells, floodlights and sensors. Only receive the most important alerts, thanks to Smart Motion Detection, which can differentiate motion generated from either a person or a vehicle and not for things like weather or swaying branches.

Be confident that your security footage is private and secure with the built-in security grade hard drive – with no hidden monthly fees. Expand your storage, using the dual hard drive bays. With 4K resolution, Fusion™ capabilities, smart home compatibility, expandable storage, and support for Smart Motion Detection – this NVR is designed for your security needs.

Features







Supports Person and Vehicle Detection



Supports Active Deterrence



No Hidden Cloud Fees



Smart Home/Voice Control Compatible



Fusion[™] Capabilities

Picture Perfect

See more and know more with superior definition and detail

- Record and view video in up to 4K (8MP) Ultra HD Resolution on all cameras ¹
- View live footage in up to 15fps and digitally zoom in on distant objects for better clarity ²

Expand your system with Lorex Fusion™

Tailor your security system to your needs

- Expand your system with up to two Lorex Fusion[™] compatible Wi-Fi products such as Wi-Fi cameras,
 Doorbells, Floodlights, and more³
- Stream and record continuous video from your Wi-Fi cameras on your recorder with Lorex Fusion™
- Increase the limited Wi-Fi SD-Card storage capacity of pair cameras by taking advantage of recording directly to the NVRs built-in HDD

Smart Person and Vehicle Detection

Always know when a person or vehicle is on your property

- Reduce unnecessary alerts and false alarms with Smart motion detection 5
- Get push notifications when motion from a person or vehicle is detected⁷
- Use Smart Search to filter motion events for reviewing footage quickly and easily

Local Storage – No Monthly Fees

- 2 bay hard drive with up to $2 \times 8TB$ of storage space with no hidden monthly fees
- · Local built-in security-grade hard drive
- Heavy-duty hard drive designed for advanced processing and the workload of 24/7 monitoring

Home is where the smart is

Enjoy the convenience and control of smart home compatibility and voice control features*

- Quickly access your live footage with simple voice commands (compatible with Amazon Alexa and Google Assistant)⁴
- View live or recorded video directly on your TV with smart home compatibility (Compatible with: Apple TV and Chromecast)
- * Not compatible with PAL version.



Product Specifications

General

Video Transmission

Technology

ΙP

Channels 16 Channels

Inputs/Outputs

Video Input 16 x PoE

Video Outputs 7 1 × VGA/1 × HDMI Audio Input 1 ch: RCA type Audio Output 1 ch: RCA type

Alarm IN 4 channels
Alarm OUT 2 channels

Display

Display Output Resolution Up to 4K UHD, Auto Detect

Live Display 1,4,8, 9,16

Live Display Speed (Max) up to 4ch 4K@15fps

OSD On/Off

System Navigation USB Mouse

Recording

Recording Resolution 4K (8MP)/5MP/3MP/ 1080p/720p

Recording Frame Rate 4K@15fps; 5MP@30fps;

1080p@30fps;720p@30fps

Recording Schedule Schedule recordings through

Continuous, Motion, Smart Motion (Person and Vehicle), Face Detection, Alarm, Day, Hour per

channel

Back-up File Format DAV/ASF/AVI/MP4

Video Compression H.265/H.264

Playback

Simultaneous Playback Up to 4ch@4K15fps

Playback Speed Variable Max 8×

Search By Time/Date, All Motion Events or

Smart Motion (Person/Vehicle⁵),

Area Search

Storage

Hard Drive Bays 2 Bays

Hard Drive Capacity Up to 2 x 8TB (SATA)

Backup Media USB Flash Drive & USB HDD

Special Features

Smart Motion Detection Yes: Person & Vehicle Motion

Detection⁵

Face Detection Support

Yes 6

Active Deterrence Support

Yes 6

Panic Button

Yes 6

Smart Search

Yes

Wired/Wireless Fusion™

supported

Yes³

Sensor Fusion™

support

Yes

Smart Home⁴

Voice Control Amazon Alexa™, Google Assistant™

Streaming Options Chromecast™, Apple TV™, Amazon

Echo Show™, Google Home Hub™,

Lenovo Smart Display™

Connectivity

Mobile Viewing Android, iOS

Compatible APP Lorex Home™

PC/Mac Remote Viewing Yes/Lorex Cloud™

Email Notification Text and Snapshot

Network Interface 1000 Base-TX, RJ45

Network Bit Rate 200 Mbps total
DDNS Yes (Optional)
USB interface USB 2.0 × 2

Additional Specifications

FW Upgrade USB/Network

Watchdog Function Yes

Power Consumption Approx. 13.2W (no HDD included)
Supply Voltage 100VAC-240VAC, 50/60hz, DC48V/2A

Total PoE Power Output PoE: Max 25.5W for single port,

130W total9

Unit Dimensions $14.7 \times 12.9 \times 2.1$ " / $(W \times D \times H)$ $375 \times 327 \times 53 \text{ mm}$

Unit Weight 5.8 lbs / 2.6 kg (excl. HDD) Operating Temperature $14^{\circ} \sim 131^{\circ}\text{F} / -10^{\circ} \sim 55^{\circ}\text{C}$

Humidity $10 \sim 90\% \text{ RH}$

Model Information

N862A63B 16-channel 4K NVR with 6-95529-02901-6

3TB HDD

N862A64B 16-channel 4K NVR with 6-95529-02900-9

4TB HDD

Dimensions

Package Plain Box

Package Weight 11.02lb / 4.9kg

Package Dimensions $21.1 \times 16.3 \times 6.7$ " / $(W \times D \times H)$ $538 \times 414 \times 170$ mm

Package Cube 0.06cbf / 0.001cbm

Back Panel







What's in the box



1 × 4K Ultra HD Smart Network Video Recorder with Fusion™



1 × Ethernet cable



1 × Power Adapte



1 × HDMI Cable



1 × USB Mouse



Quick Setup Guide

Disclaimers:

- 1. 4K (8MP) IP cameras are required to take advantage of 4K recording.
- 2. Recording time may vary based on recording resolution and quality, lighting conditions and movement in the scene.
- 3. Fusion™ capabilities are limited to 2 wireless devices per system. Wireless devices require an available channel on the NVR as well as a sufficient signal strength between the device(s) and your Wi-Fi router for video streaming. For full details on Wi-Fi cameras compatibility and instructions, visit www.lorex.com/pages/fusion
- 4. Controlling certain features in your security system requires a compatible smart device. Availability and performance of certain features and services are smart device dependent and may not be available in all areas or networks. For compatibility, features, and instructions visit www.lorex.com/smarthome
- 5. Accuracy of Smart Motion Detection will be influenced by multiple factors, such as the object's distance from the camera, the size of the object, and the height and angle of the camera. Night vision will also impact the accuracy of detection. Compatible with certain Lorex IP cameras only.
- 6. Compatible with certain Lorex IP and select wireless cameras only. For a list of compatible cameras please visit www.lorex.com/compatibility
- 7. Accessing your security system remotely requires a high-speed Internet connection. Ensure your NVR has a wired connection to a router (not included). A minimum upload speed of 5Mbps is recommended for reasonable video performance. Up to 3 devices may connect to the system at the same time. For the latest list

- of supported apps and devices, please visit www.lorex.com/compatibility
- 8. HDMI output supports 4K HD for high definition multi-channel live or recorded video viewing. Image quality and resolution is dependent on the type of camera connected to the NVR, as well as TV/monitor resolution.
- 9. NVR has a total PoE power output of 130w. Different IP cameras have different wattage specifications. Please double check your camera specifications for power consumption (Wattage) requirements in order to not exceed the NVRs power output availability of the recorder when adding cameras. To learn more, please visit www.lorex.com/compatibilitydisclaimer 9: NVR has a total PoE power output of 130w. Different IP cameras have different wattage specifications. Please double check your camera specifications for power consumption (Wattage) requirements in order to not exceed the NVRs power output availability of the recorder when adding cameras. To learn more please visit www.lorex.com/compatibility

Lorex 4k Ultra HD Smart Network Video Recorder With Fusion Specifications Manual – Optimized PDF Lorex 4k Ultra HD Smart Network Video Recorder With Fusion Specifications Manual – Original PDF

Manuals+,