



LUMINOX Flashlight Light Capsule For 0 29-32in Bandwidth User Manual

[Home](#) » [LUMINOX](#) » LUMINOX Flashlight Light Capsule For 0 29-32in Bandwidth User Manual 

LUMINOX Flashlight Light Capsule For 0 29-32in Bandwidth User Manual



Thank you for using our Luminox Light Capsule! The Luminox Light Capsule is a reliable, durable, and easy to carry lighting solution ready for adventure.

Contents

- [1 Product features](#)
- [2 Product specifications](#)
- [3 Extent of delivery](#)
- [4 How to install the batteries](#)
- [5 How to operate](#)
- [6 Documents / Resources](#)
 - [6.1 References](#)
- [7 Related Posts](#)

Product features

Compact and simple design, weatherproof and convenient to carry. Single brightness mode, suitable for outdoor, camping or daily use.

Product specifications

Luminosity of light: 60LM

Run time: 60 minutes

Light range: 10 meters

Service life of LED: up to 50'000 hours

Water resistant: IPX-8

Shockproof: 1,5 meters

Dimension of light capsule: 40 x 11.5/14.50mm

Weight of light capsule: 9 grams (incl. batteries)

Dimension of holder: 32 x 14.50mm

Weight of holder: 4 grams

Batteries: 3 x 1.5V LR754 button batteries

Remark: This data is from laboratory tests, actual use will vary depending on the environment or battery type.

Extent of delivery



- On/off button
- Light capsule head
- O-Ring gasket
- Batteries
- PLight capsule body
- Light capsule holder

How to install the batteries

1. Screw off the orange head.

2. Place the 3 batteries in the orange head (order does not matter).

The protective film shall be removed before installing the batteries.

3. Screw the orange head back into the black body of the light capsule.

How to operate

Once the batteries are in, press the on/off button once to turn the light capsule on. Press the on/off button a second time to turn the light off.

Maintenance and precautions

- When replacing the batteries, it is recommend to use high quality batteries to preserve the life of your light capsule.
- Do not point the light directly in the eyes to avoid injury.
- Keep the light capsule out of direct sunlight, water, chemicals or corrosive gas for extended periods of time to avoid damages.
- It is recommended to lubricate the threads 2-3 times a year to ensure smooth screwing and unscrewing of the orange head.
- To clean the light capsule, use a soft brush or towel.
- To avoid corrosion, it is recommended to remove the batteries when not in use for extended periods of time.
- Seek professional help when disassembling the contents beyond changing the batteries of light capsule to prevent damage.



facebook.com/Luminox




@luminoxworld



youtube.com/LuminoxWorld



Documents / Resources



[LUMINOX Flashlight Light Capsule For 0 29-32in Bandwidth](#) [pdf] User Manual
Flashlight Light Capsule For 0 29-32in Bandwidth

References

- [LuminoxWorld - YouTube](#)

