



 Bitte scannen Sie den QR-Code, um das deutsche Handbuch, das Installationsvideo und die Funktionseinführung zu erhalten

• Escanee el código QR para obtener el manual en español, el video de instalación y la introducción de la función

Veuillez scanner le code QR pour obtenir le manuel en français, la vidéo d'installation et l'introduction des fonctions

Отсканируйте QR-код, чтобы получить руководство на русском языке, видео по установке и описание функций

• Leia o código QR para obter o manual em português, o vídeo de instalação e a introdução das funções

Product Description

This newly designed wall socket is designed with WiFi protocol to replace the traditional wall socket. The APP has newly added new pairing mode with Bluetooth enabled, panel indicator mode and relay status setting (power on, power off, power off memory), switch log, child lock, current statistics, overcurrent protection, etc. Enter Smart Life/Tuya App, all control modes are effective without any interference. Its design is suitable for different decoration styles, which is really great value for money.

Safety Information

Risk of Electric Shock: Electricity can cause personal injury and property damage if handled improperly. If you are not sure about any part of these instructions, please seek professional assistance from a qualified electrician.

Technical Parameters:

Model: WK-EU(FR/UK)16M Voltage: 95~245V AC, 50/60Hz Wireless Protocol: WiFi 802.11 b/a/n 2.4GHz Max. Current(pure resistive load): 16A Max. Load Power: 3000W

Turn off the power at the circuit breaker and test that power is off before wiring.


Installation

- Note: Install the switch with electricity off
- Do not install in damp environment. Neutral wire in not required(single live line). Do not exceed the maximum load.
- Please follow instructions and properly install
- If you don't have any wiring experience, please call a professional electrician.

Turn off the circuit breaker and use the electrical tester to test the power. Ensure the switch is off before wiring.



Remove the old switch





Remove the switch and pull it away from the wall. Identify Line/Load Wire(Note:The color of your wire may be different from the color shown on the manual.)

Take pictures of the wiring


Follow the wiring diagram to connect the switch wires to

the wires in the wall box with the wire conductors.




Preparing to install wiring

A. Connect the live wire to the "L" terminal B. Connect the neutral wire to the "N" terminal



- Put the switch into switch box in the wall
- Mount the two side screws Install the glass panel (install from up above)



Add Devices

Download Smart Life App





Please scan the QR code or download Smart

Registration or Log in

- Download "Smart Life" Application
- Enter the Register/Login interface;tap "Register" to create an account by entering your phone number to get verification code and "Set password". Choose "Log in" if you already have a Smart Life account.

Configure the APP to the switch

 Preparation: Ensure the switch has been connected with electricity;ensure your phone has been connected to Wi-Fi and is able to connect to the Internet.

The switch only supports 2.4G network.If you have connected 5G network, please disconnect 5G network firstly and connect 2.4G network.

3.1 Wi-Fi link method:

Pair and clear up the WiFi code(New Updated)

1.Make sure your phone is connected to Wi-Fi and Bluetooth Long press the button for 6s until the blue indicator light flashed fast

2. Open Smart Life/Tuya App and Click"+",then the prompt page will automatically show on the screen. Click "Go to





4.Enter Wi-Fi Password and click "Confirm", waiting for completing the connection





Press and hold the button for about 6 seconds,until the blue indicator on the switch flash fast after 3 seconds.Reset/re-

Set your Echo speaker by Alexa APP

f) If you have finished installing Smart Life, just open Amazon Alexa App; log into your Alexa account with password.

Click the menu on the top left -click "settings",choose "Set up a new device" (choose a device like Echo)

When below page appears,long press the small dot on your Echo device until the light turns to yellow. Then click "Continue" on the App.

Attention: The mobile phone can not open a variety of

Choose your own Wi-Fi and wait for a few minutes. After watching an introduction video, click "next step", then it will enter Home page automatically.Now the Echo has been connected to Wi-Fi successfully.

Enter Smart Life Skill in Alexa APP

1. Complete product networking configuration in the App Complete the device's networking configuration according to the prompts in the App.

Note: In the App, change the name of the device to an easily identifiable name such as Alexa; names are usually in English, such as "bed light".

2. Configure the Amazon Echo device


(If you have already configured Amazon Echo, you can skip this step. The following instructions are based on the iOS client.)

•Make sure you Amazon Echo device is powered on and connected to a Wi-Fi network.

*Open the Alexa App on your phone. After successful login, tap on the menue in the upper left corner of the Home page, select "Settings" and tap "Set Up A New Device" to set up the Amazon Echo.

· Choose your Amazon Echo device type and language for connecting. Press and hold the small dot on the device until the light turns yellow. Then tap "Continue" to connect to the hotspot.

After connecting to the Amazon Echo hotspot, return to the page. At this point, the connection is successful





Tap "Continue" to proceed to the next step. Choose a Wi-Fi network to connect to. Amazon Echo will take a few minutes to try to connect to the network.

· After the network connection is successful, tap "Continue". An introduction video will appear. After the video ends, tap "Continue" to jump to the Alexa Home page. You have now completed the Amazon Echo's configuration process

3. Key step — Link Skill •Tap on "Skills" in the Alexa App menu.



•Enter the App account and password, then tap "Link Now" to link your App account to enable the Skill. Now you can start your smart home journey.





light)

Control the device via voice commands, now you can control your smart device with Echo. You can control your device (such as your bedroom light) with the following

Alexa, turn on/off bedroom light. (Turn on/off the light) Alexa, set bedroom light to 50 percent. (Set the light to any brightness)

Alexa, brighten/dim bedroom light. (Increase/weaken the brightness of the light) Alexa, set bedroom light to green. (Adjust the color of the

1. During the free warranty period, if the product breaks down during normal use, we will offer free maintenance for the

2.Natural disasters/man-made equipment failures, disassembly and repair without the permission of our company, no warranty vithin the scope of free warranty

3 Any commitment (oral or written) made by the third party including the dealer/service provider) to the user beyond the warranty scope shall be executed by the third party 4.Please keep this warranty card to ensure your rights

5.Our company may update or change the products without notice. Please refer to the official website for the updates.

RECYCLING INFORMATION All products marked with the symbol for separate collection

of waste electrical and electronic equipment (WEEE Directive 2012/19 / EU) must be disposed of separately from unsorted municipal waste. To protect your health and the environment, this equipment must be disposed of at designated collection points for electrical and electronic equipment designated by the government or local authorities. Correct disposal and recycling will help prevent potential negative consequences for the environment and human health. To find out where these collection points are and how they work, contact the installer or your local authority.

WARRANTY CARD

Product Information Product Name Product Type Purchase date Warranty Period_ Customer's Name Customer Phone_ Customer Address

Maintenance Records

ailure date	Cause Of Issue	Fault Content	Principal

Thank you for your support and purchase at we Moes,we are always here for your complete satisfaction, just feel free to share your great shopping experience with us.



If you have any other need, please do not hesitate to contact us first,we will try to meet your demand.

FOLOW US



@moes_smart @ @moes_smart @moes_smart

moes

www.moes.net

WENZHOU NOVA NEW ENERGY CO.,LTD Address: Power Science and Technology Innovation

Center, NO.238, Wei 11 Road, Yueging Economic Development Zone, Yueqing, Zhejiang, China Tel:+86-577-57186815



Laubenhof 23, 45326 Essen Made In China

