

User Manual

Introduction

Mic 2 is a dual channel wireless microphone system, including two transmitters and one receiver, which is able to record two sound sources simultaneously. The transmitter has a built-in omnidirectional microphone, supports the use of an external microphone, and can be clipped to clothing or any place close to a sound source. The charging case provided is able to charge the transmitters and receiver simultaneously and link them automatically.

Overview

DJI Mic 2 Transmitter

1. Recording Status LED

Indicates the record status of the transmitter.

Blinking Pattern	Descriptions
Solid red	Recording
Pulses red	Mute
Off	Not recording

2. Data Port (USB-C)

For copying audio or updating firmware after connecting to a computer. Can also be used for charging.

3. Record Button

Press once to start or stop recording.

4. 3.5 mm TRS Input

For connecting external microphone. DO NOT connect a microphone with a power supply of 24 V or 48 V.

5. System Status Indicator

Blinking Pattern	Descriptions
Battery Level Descriptions	
Solid red	Battery Level $\leq 20\%$
Noise Reduction	
Solid yellow	Noise reduction is enabled
Connection Status to the Receiver	
Solid green	Connected with the receiver
Blinks green slowly	Disconnected from the receiver

Blinks green quickly	Linking
Bluetooth Connection Status	
Solid blue	Connected with the Bluetooth device
Blinks blue slowly	Disconnected from the Bluetooth device
Blinks blue quickly	Linking
Battery Level During Charging	
Blinks green slowly	Battery level: 0~25%
Blinks green twice	Battery level: 26~50%
Blinks green three times	Battery level: 51~75%
Blinks green four times	Battery level: 76~100%
Off	Fully charged

6. Linking Button

Press and hold for 2 seconds to start linking to the receiver. Once the receiver is attached to a mobile phone and the receiver and transmitter are linked, press once to take a photo or start or stop recording on the mobile phone (only supports mobile phones where the volume button can be used to take a photo or start or stop a video).

7. Power Button

Press and hold for 2 seconds to power on or off. Press twice to mute.

8. Charging Pad

Charging will begin after connecting the transmitter to the charging pad of the charging case and the transmitter will automatically link with the receiver in the charging case.

Specifications

Name	DJI Mic 2 Transmitter
Model	DMT02
Dimensions	30×50×25 mm
Weight	25.2 g
Wireless Mode	GFSK 1 Mbps and 2 Mbps
Operating Frequency	2.4000-2.4835 GHz

Transmitter Power (EIRP)	< 20 dBm
Bluetooth Protocol	BR/EDR
Bluetooth Operating Frequency	2.4000-2.4835 GHz
Bluetooth Transmitter Power (EIRP)	< 20 dBm
Battery Type	LiPo 1S
Battery Capacity	360 mAh
Charging Temperature	5° to 45° C (41° to 113° F)
Operating Temperature	-10° to 45° C (14° to 113° F)