



Z-Wave Protocol Implementation Conformance Statement

Door/ Window Sensor 6

General Information

Product Identifier: ZW112-D
Brand Name: Aeotec
Product Version: HW: 112 FW: 1.03
Z-Wave Certification #: ZC10-17085746

Product Features

Supported Notification Types Access Control
Sensors Open/Closed (Binary)

Z-Wave Product Information

Supports Z-Wave Beaming Technology? No
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: Hong Kong
Z-Wave Product ID: 0x0070
Z-Wave Product Type: 0x0302
Z-Wave Hardware Platform: ZM5101
Z-Wave Development Kit Version: 6.51.09
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	Group 1 is assigned to the Lifeline association group and every device has 5 nodes to associate. The sensor binary report, basic set or notification report command can be sent in this group when the Sensor is triggered.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Door/ Window Sensor 6

Supported Command Classes (14):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Notification V4
Powerlevel	Security S0
Sensor Binary	Version V2
Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic
