

Source 180 TFMR-180

Low Voltage Transformer

Product Finishes: ■



Specifications:

Voltage: 120Vac

Wattage: 180

Volt Amps: 180

Wire Taps: 3

IP Rating (with cover): 23

Material: Polycarbonate

Cable Length: 36"

Warranty: 7-year comprehensive

Control: Touch Screen

L x W x H: 9.5 x 5.5 x 2.8 in

Installation Tips:

- At least 18" off the ground
- Mount with a drop loop
- Connect to a GFCI Outlet
- Indoor or outdoor use

Compatible With:

All BOLD standard lighting products. Please note that TrueSync fixtures will not have dimming or color-changing capabilities if connected to a standard transformer.



support@boldpros.com | 1-833-472-9960

boldpros.com