
iGPSPORT



USER MANUAL




ACCESSORY/STRUCTURE



HOW TO INSTALL





规格认证 CE F© € 🖟 RoHS 🕾

iGPSPORT

DEVICE INTRODUCTION

Button/Status indicator —	
Lamp —	
Charging port —————	Report .
Mounts —	1-11

LIGHT MODES

LIGHT MOD	LS				
Light Modes	Brightness (lumens)	Battery Life (hours)	Effective Range	Drop Resistence Height	Waterproof
Low Beam - Low Steady	300	12			
Low Beam - Medium Steady	450	6			
Low Beam - High Steady	900	3			
High Beam - Low Steady	600	6			
High Beam - Medium Steady	900	3	150m	1.2m	IPX6
High Beam - High Steady	1800	1.5	150111	1.2111	IFAO
High Brightness Flash	600	/			
Low Brightness Flash	200	/			
Custom 1/2/3	/	/			

Note: The above parameters are tested in the iGPSPORT laboratory at a temperature of 22±3°C and humidity of 30%-50%. Actual performance may vary slightly depending on the usage environment, low brightness flash, custom 1, custom 2, and custom 3 are disabled by default and need to be enabled in the iGPSPORT APP.

OPERATING PROCEDURES

OPERATING PROCEDURES

-Power on Jof

Long press the button for 2 seconds to power on Joft.

-Restore the default setting.

-Restore the default setting.

Long press the button for 5 seconds when it is powered off. The green LED indicator will

lash rapidly three times, and the front light will flash rapidly three times, indicating a

flash rapidly three times, and the second setting and data, so

please operate with caution.

- switch light mode

After powering on, click the button to cycle through the gears in the sequence of low bean

and low steady—low beam and medium steady—low beam and high steady;

After powering on, double-click the button to switch to high beam mode, with the default

setting being high beam and low steady—

- so and low steady—ligh beam and medium steady—ligh beam and low steady—ligh beam and low steady—ligh beam and medium steady—ligh beam and low steady—ligh beam and low steady—ligh beam and medium steady—ligh beam and high steady;

It can also be adjusted by iGSPSPORT bile computer and the APP.

- SOS mode

After powering on, triple-click the button to quickly enter SOS mode, and click the button

PERFORMANCE SPECIFICATIONS

Device size	110*44*29mm (excluding the mount and mounting bracket)	Max brightness	1800 l m
Device weight	About 194g	Battery capacity	6700mAh

SPECIAL FEATURES SPECIAL FEATURES

Auto-sleep/wake up:After stationary for 120s in the powered-on state, it will automatically enter sleep mode, with the main light and indicator light turning off. It will be avalaced when it detects motion or a button is pressed, and it will restore the light mode before entering sleep mode. The pressed was the sleep sleep

△ WARNING

1.The light will generate a significant amount of heat while using, resulting in high extern temperatures. Please use with caution to avoid burns. 2When placing this light in enclosed and flammable environments such as pockets or backpacks, please turn it off to prevent accidental activation and potential hazards. 3.Please do not illuminate flammable objects at close range with this light, as it may gen high temperatures that can cause damage and potential hazards. 4.Please do not illuminate this light directly into the eyes to prevent eye injury. 5.The waterproof rating of the device is IPNK, which makes it suitable for use in rainy day not put it in water for a long time and please lightly close the weather cap while using. 6.Please place this light in a location inaccessible to children to prevent their use.

CHARGING INSTRUCTIONS

CHARGING INSTRUCTION
When charging, please follow the steps below:
Litum of the bike light and remove the dust plug. Insert the charging cable into the USB
Type-C port.
2-After charging is finished, please disconnect the charging cable and securely close the dus
plug to maintain the waterproof performance and normal use of the bike light.
From completely deplease to full charge, it less approximately show it with W3 A.
From completely deplease to full charge, it less approximately show it with W3 A.

The procedure of state, long-pressing the button will not turn on the light.

Iong time to prevent battery ownwage.

BATTERY DISPLAY
In the power-off state, a single click of the power button will illuminate the battery indicator light for 3 seconds, displaying the remaining battery level. The different states corresponding to the remaining battery levels are as follows:

Charging

Using		Charging		
	battery level >30%	Green light slow flash	1% <battery level="" th="" ≤10%<=""><th>Red breathing light</th></battery>	Red breathing light
	10% <battery level="" th="" ≤30%<=""><th>Red and green lights alternative slow flash</th><th>battery level >10%</th><th>Green breathing light</th></battery>	Red and green lights alternative slow flash	battery level >10%	Green breathing light
	1% <battery level="" th="" ≤10%<=""><th>Red light slow flash</th><th>fully charged</th><th>Green light steady</th></battery>	Red light slow flash	fully charged	Green light steady
	Power	roff	Red light fast flash	for three seconds
	iGPSPORT /	ΔPD		(Average)

Download the APP

Pairing

rt. ng is complete, the bike light will be shown in the device list, indicating the sful. iring, the bike light and your phone will automatically connect v fails during the process, you can try restarting Bluetooth, the ap tempt the pairing again.

Unpairing

Firmware update are update can enhance the user experience of the bike light, including new ones, in provements to existing functions, or bug fixes. You will not lose any data du province to the control of the control

Available time

When the bike light is connected to the app, it estimates the remaining battery life based on the current mode and provides an update every minute. This allows you to plan your riding more effectively. Light modes



You can configure the bike light modes in the iGPSPORT app, which includes switt between different modes, enabling or disabling specific modes, adjusting the brig and lighting patterns for custom modes.

Intelligent functions configuration You can configure the intelligent functions of the lights in the iGPSPORT APP, including bill computer synchronized shutdown, smart light sensing, brightness change with speed, auto sleep and sleep waiting time, stationary low brightness and stationary waiting time.

设备简介

以田间川	
按键/状态指示灯————	
灯头 —————	
充电口 —————	Parosi
安装座	1

车灯模式

-F717X20					
车灯模式	亮度 (流明)	续航时间 (小时)	有效 射程	防跌落 高度	防水 等级
近光低常亮	300	12			
近光中常亮	450	6			
近光高常亮	900	3			
远光低常亮	600	6			
远光中常亮	900	3	150米	1.2米	IPX6
远光高常亮	1800	1.5	150%	1.2/	IFAO
高亮闪烁	600	/			
低亮闪烁	200	1			
自定义1/2/3	1	/			

注: 上述参数定任油度2213 (村油度307050700 实际表现随着使用环境的变化略有差异。 *高亮闪烁、低亮闪烁、自定义1、自定义2、自定义3

操作说明

- ·开机/关机 长按按键25开机,长按按键25关机。 •恢复出广设置 关机情况下长按按键55,LED指示订绿灯快闪三次,前灯快闪三次,表示重置成功,重置后: 清炀所有个人设置及数据,请谨慎操作。 •灯光模式切换
- **儿/在模式切探 开机后,对击按键,按照近光低常亮·近光中常亮·近光高常亮的档位 开机后,双击按键,切换为远光模式,默认远光低常亮档位; 远光模式下,单击按键,按照远光低常亮·远光中常亮·远光高常亮的 也可通过iGPSPORT码表和APP调节。
- SOS模式
- --三击按键,快速进入SOS模式。 开机后,三 •智能记忆 车灯会自动记忆!

	性能参数	X		
	主机尺寸	110*44*29mm	最大亮度	1800 l m
I	主机重量	约194g	电池容量	6700mAh

- 午色 5 分
 ●自动纬顺/南服: 开机状态下,车灯静雪1205后自动进入休眠状态,主灯及指示灯熄灭;车灯检测则运动或按下按键时换强,恢复休眠前的灯光模式。
 ●智能必悉: 通边车灯的分照传感播感知环境亮度,高类循环境下自动关闭主灯,低类旗时自动打开主灯。
 ●同步水航空第一次,12 接触码表面的关系。
 ●自部心患: 车灯存电路间的模式和电量估算可用绘就时间,并在码表/APP上显示。
 ●自动低策: 车灯在充电、反向充电、长时间静止、低电量等状态下,自动调低规度至低灰板、以确保用户使用安全。
 ●自部通往定: 第10 的温度大程使加到扩大内温度过高时。会逐步降低炭度,以确保用户安全。
 ●反应电: 可信等DPORT APP上编辑自定发现的效果。 秀灯方式等参数。
 ●车灯模式启停: 可在IGPSPORT APP上启用及停用车灯模式,停用后,APP及按键无法切换至该模式。

- 注意: 注意: "智能光感、同步关机默认关闭,需要在IGPSPORT APP中启用。 「同步关机业持部分码表,具体型导清咨询客限。 "反向充电线需要单独购买。
- △警告

- 充电说明
- 奔电時,起按如下步骤进行: 1.关闭车灯,揭开车灯防尘尾器,将充电线插入USB Type-C端口; 2.停止充电信。应波下充电线,将防尘尾器盖回按案,以保持车灯的防水性能和正常使用 注意:

- 注意: "从电量耗尽到完全充满,耗时约3小时(SV 2A)。 "关机状态下杂电、按按键据无法开机。 "并机状态下杂电,生打箱自动筛性力量低亮度排。充电时间将会延长。 "由于电池会缓慢地自放电,建议长时间不使用车灯时,仍然每六个月充电

- 电量显示
- 关机状态下,单击开关按键,电量指示灯会亮起3s,显示剩余电量,不同状态对应剩余电量状态如下:

使用中		充电	
电量>30%	绿灯慢闪	1%<电量≤10%	红色呼吸
10%<电量≤30%	红绿交替慢闪	电量>10%	绿色呼吸
1%<电量≤10%	红灯慢闪	充满电	绿色常亮
关机		红灯快闪三秒	

IGPSPORT APP

APP下载 请扫描二维码下载iGF

配对手机

- 1.在智能手机上,打开iGPSPORT应用并使用您的iGPSPORT账户登录。
 2.将车灯罩近手机,进入iGPSPORT应用中设备"设备管理"出去"添加设备"选择车灯产品
 手机会自动理影中灯"VSI800",选中并点击"连接"设备开始配对。
 3.当您的移动或备上显示"蓝牙起对诸索"的药板弹管时,请由危配对,接受蓝牙配对请求。
 4.配对完成后,车打将显示设备列表中,配对完成。
 5.手机配对成历点。车灯设备和平成为完成。
 5.手机配对成历。车灯设备和平成的工程,如果中途出现配对失败,可以尝重启手机蓝牙、APP或车灯进行重新配对。
- 解除绑定

- 如果您想要将车灯和其他智能手机配对,请先解除当前配求 1.前往设备详情页~解除绑定,点击解除配对按键确认解绑。 2.完成后,APP列表页将不再显示该设备。 注意:请勿频繁进行配对解绑操作。

固件更新

执行固件更新可以提高车灯的使用体验,包括全新功能、 会因为固件更新丢失任何数据。

可用时间

车灯与手机APP连 划骑行时间。

车灯模式

您可以在iGPSPORT APP中对车灯模式 调节自定义模式车灯亮度及亮灯模式。



智能功能配置

FCC Caution:

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. This device and its antenna(s) must not be co-located or operating in conjunction with any other antenna or transmitter.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- -- Reorient or relocate the receiving antenna.
- -- Increase the separation between the equipment and receiver.
- -- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected
- -- Consult the dealer or an experienced radio/TV technician for help.