

JOYO

MONOMYTH

REVOLUTION
SERIES
Bass Preamp

Specifications

Dimensions: 130*110*50mm
Weight: 442g
Input Impedance: 1MΩ

Output Impedance: 2KΩ
Current Consumption: > 200mA
Working Voltage: DC 9V (center minus)

Blend Control

Voice Control

Level Control

Drive Control

Treble Boost

Gain Boost

EQ Function Control

Overdrive Channel Indicator

Overdrive Channel Switch

Footswitch

Effects Indicator

DI Output Jack

Ground-Lift Switch

Cab Sim Switch

Input

Rear ambience LED light

Output

Headphone Output

DC Power Input

Direct Output

Front ambience LED light

Feet

Toggle SYNC: All the LEDs from both sides and the top are controlled by the Footswitch.

Toggle ALWAYS: The LEDs on both sides are on and not controlled by the Footswitch, while the LED from the top is controlled by the Footswitch.

Toggle OFF: The LEDs on both sides are off, the LED from the top is controlled by the Footswitch.

JOYO TECHNOLOGY CO., LTD

Address: 2/F, Lushi Industry Building, 28th District, Bao'an, Shenzhen, 518133 China.

Email: info@joyoaudio.com Tel: 0086-755-29765381 www.joyoaudio.com

MADE IN CHINA

JOYO

规格参数

尺寸: 130*110*50mm
重量: 442g
输入阻抗: 1MΩ

输出阻抗: 2KΩ
工作电流: > 200mA
工作电压: DC 9V (外正内负)

清音过载混合比控制

选频控制

音量控制

增益控制

高音激励

增益激励

EQ功能控制

过载通道指示灯

过载通道开关

脚踏开关

效果指示灯

DI 输出接口

浮地开关

箱体模拟开关

输入插座

后面氛围灯

输出插座

耳机输出插座

直流电源输入

直通输出插座

前面氛围灯

脚垫位置

档位SYNC: 两侧LED+顶部LED全部受控于脚踏开关

档位ALWAYS: 两侧LED常亮, 不受控于脚踏开关, 顶部LED受控于脚踏开关

档位OFF: 两侧LED不亮, 顶部LED受控于脚踏开关

卓乐产品服务政策

一、在正常使用产品过程中, 如果产品出现非人为损坏的性能故障, 自购买之日起, 消费者享有保修服务, 保修期为12个月。
二、有下列情况之一者, 消费者不能享受保修权益。
1、人为损坏; 2、超过保修期; 3、无保修卡及有效发票, 但能够证明产品在保修期内的除外;
4、保修卡与产品型号不符, 或保修卡被涂改; 5、未按说明书要求使用、维护、保养而造成产品损坏; 6、未经卓乐公司授权, 擅自拆卸、维修产品、或浸水、摔坏产品; 7、其他不可抗力造成的损坏。
三、卓乐服务信息:
消费者服务热线: 0755-29765390
更多信息请访问: www.joyochina.cn

卓乐产品保修卡

产品型号	购机日期	SN号码	
用户信息	电话	姓名	
	地址		
	发票号码		
销售单位信息	名称 (加盖公章)		
	地址		
	电话		

品牌: JOYO 名称: 效果器

执行标准: QB/T 4324-2012

制造商: 深圳市卓乐科技有限公司

地址: 广东省深圳市宝安28区新安三路

陆氏工业大厦2楼 邮编: 518133

售后服务热线: 0755-29765390

产品合格证

检验结论 合格

检验员号 QC 01

日期