

# Clanbro® STRONG-ARM



CAUTION: Do not keep the override keys inside the safe!

**DIGITAL SAFE**  
MODEL NO: CS400D  
PART NO: 7710185

## OPERATION & MAINTENANCE INSTRUCTIONS



DL321

---

## INTRODUCTION

---

Thank you for purchasing this CLARKE Digital Safe.

Before attempting to operate the safe, it is essential that you read this manual thoroughly and carefully follow all instructions given. In doing so you can look forward to the safe giving you long and satisfactory service.

---

## GUARANTEE

---

This CLARKE product is guaranteed against faulty manufacture for a period of 12 months from the date of purchase. Please keep your receipt as proof of purchase.

This guarantee is invalid if the product is found to have been abused or tampered with in any way, or not used for the purpose for which it was intended.

Faulty goods should be returned to their place of purchase, no product can be returned to us without prior permission.

This guarantee does not effect your statutory rights.

---

## SPECIFICATION

---

Dimensions (DxWxH)	266 x 350 x 250 mm
Weight	9.5 kg
Batteries	4 x AA (1.5V) batteries
Volume	16.3 L
Number of keys supplied	2

---

## REPLACEMENT OVERRIDE KEY

---

A small label is located on the front of each safe with a key number. The number will start with either the letter "J" or "G" followed by several digits. This number must be registered with us in the event you require a replacement key.

Please complete the registration form at the back of this manual and send it to the address stated with the form. If you fail to register the safe we will not be able to provide you with a replacement key.

We recommend that in addition to sending the completed form you remove the label from the safe and fix it to the space below. Please retain this document for future reference.


Fix or record the key number here

## BEFORE USE

### OPENING THE SAFE FOR THE FIRST TIME

1. Remove the small plastic cover (B) on the front panel.
2. Insert the override key into the key hole and turn it counterclockwise, at the same time, turn the doorknob (A) clockwise direction to open the safe.

**NOTE:** Never keep the override keys inside the safe itself.




3. Replace the small plastic cover (B) onto the front panel.

### INSTALLING THE SAFE

The safe should be secured vertically to a wall, shelf or to the floor using the expansion bolts (supplied).


- There are holes (8 mm) on the rear and bottom of the safe for securing to a wall or the floor.



### INSTALLING THE BATTERIES


The safe requires 4 x size "AA" (1.5V) batteries.

1. Open the safe.
2. Remove the battery cover plate on the back of the door and install the batteries.
3. Ensure the batteries are fitted with the correct polarity.
4. Use of alkaline batteries is recommended.



## PROGRAMMING THE CODE

1. With the safe door open and the batteries installed.
2. Press and release the red button on the rear of the lock housing.
  - you will hear two beeps.
  - The yellow light will be on at the same time.
3. Enter the code you want to use (3-8 digits) as a combination.
4. Confirm within 15 seconds by pressing the letter "A" or "B".
  - The safe "bleeps" twice and the yellow light will go off, your personal code is now set.
5. Test the safe using the new combination immediately.



---

## USING YOUR SAFE

---

### TO OPEN THE SAFE

1. Enter your personal code followed by the letter "A" or "B".
  - you will hear a beep and the green light on the front of the safe will light up.
2. Turn the doorknob in a clockwise direction to open the door within 5 seconds.
  - If you, or an intruder uses the incorrect group of numbers, it will not open, if the incorrect combination is used 3 times consecutively, you must wait for 20 seconds before trying again.
  - If the incorrect combination is selected a further 3 times, you must wait approximately 5 minutes before trying again.

### BATTERY REPLACEMENT WARNING

If the batteries are low, the red light (in the middle of the number panel) will illuminate.

### MANUAL OVERRIDE

- See "Opening the safe for the first time" on page 3.

# DECLARATION OF CONFORMITY



## DECLARATION OF CONFORMITY

This is an important document and should be retained.

We hereby declare that this product(s) complies with the following UK legislation:

*Electromagnetic Compatibility Regulations 2016.*

*The Restriction of the Use of Certain Hazardous Substances in Electrical and Electronic Equipment Regulations 2012.*

The following standards have been applied to the product(s):

*BS EN 61000-6-3:2007+A1:2011, BS EN 61000-6-1:2009.*

The technical documentation required to demonstrate that the product(s) meet(s) the requirement(s) of the aforementioned legislation has been compiled and is available for inspection by the relevant enforcement authorities.

This product was placed onto the market: 2009

Product Description:

Digital Safe

Model number(s):

CS300D, CS400D, CS600D

Serial / batch Number:

N/A

Date of issue:

09/03/2021

Signed:

J.A. Clarke  
Director

UKCA (10-0035) Digital Safe CS300D CS400D CS600D (v 0) N621-0028UK

Page 1 of 1



## DECLARATION OF CONFORMITY

This is an important document and should be retained.

We hereby declare that this product(s) complies with the following directive(s):

*2014/30/EU Electromagnetic Compatibility Directive.*

*2011/65/EU Restriction of Hazardous Substances, (amended by 2015/863).*

The following standards have been applied to the product(s):

*EN 61000-6-3:2007+A1:2011, EN 61000-6-1:2009.*

The technical documentation required to demonstrate that the product(s) meet(s) the requirement(s) of the aforementioned directive(s) has been compiled and is available for inspection by the relevant enforcement authorities.

The CE mark was first applied in: 2009

Product Description:

Digital Safe

Model number(s):

CS300D, CS400D, CS600D

Serial / batch Number:

N/A

Date of issue:

09/03/2021

Signed:

J.A. Clarke  
Director

D O C (10-0035) Digital Safe CS300D CS400D CS600D (v 0) N621-0028

Page 1 of 1

# A SELECTION FROM THE VAST RANGE OF

# Clarke®

## QUALITY PRODUCTS



**AIR COMPRESSORS**  
From DIY to industrial, Plus air tools, spray guns and accessories.

**GENERATORS**  
Prime duty or emergency standby for business, home and leisure.

**POWER WASHERS**  
Hot and cold, electric and engine driven - we have what you need

**WELDERS**  
Mig, Arc, Tig and Spot.  
From DIY to auto/industrial.

**METALWORKING**  
Drills, grinders and saws for DIY and professional use.

**WOODWORKING**  
Saws, sanders, lathes, mortisers and dust extraction.

**HYDRAULICS**  
Cranes, body repair kits, transmission jacks for all types of workshop use.

**WATER PUMPS**  
Submersible, electric and engine driven for DIY, agriculture and industry.

**POWERTOOLS**  
Angle grinders, cordless drill sets, saws and sanders.

**STARTERS/CHARGERS**  
All sizes for car and commercial use.



## PARTS & SERVICE:

## 0208 988 7400

**Parts Enquiries**  
[Parts@clarkeinternational.com](mailto:Parts@clarkeinternational.com)

**Servicing & Technical Enquiries**  
[Service@clarkeinternational.com](mailto:Service@clarkeinternational.com)

SALES: UK 01992 565333 or Export 00 44 (0)1992 565335

**Clarke® INTERNATIONAL** Hemnall Street, Epping, Essex CM16 4LG  
[www.clarkeinternational.com](http://www.clarkeinternational.com)

# **IMPORTANT**

**In order to be able to obtain a replacement key.  
Please detach and complete this safe registration  
form (see reverse), Then return it to:**

**Clarke International  
Product Registration Department  
Shrubland Road  
London  
E10 7RB**

# Safe Registration Form

PLEASE COMPLETE AND RETURN TO CLARKE INTERNATIONAL WITHIN 7 DAYS OF PURCHASE

# STRONG-ARM

## IMPORTANT!

PLEASE IDENTIFY THE KEY NUMBER BEFORE THE SAFE IS INSTALLED

If you fail to register and subsequently lose your key, we will be unable to provide you with a replacement. It is therefore in your own interest to register immediately.

### Model Number

Please tick the relevant box:

CS300D ☐

CS150F ☐

CS300K ☐

CS400D ☐

CS400FP ☐

CS600D ☐

CS490F ☐

### Registration Details

Name

Company

Address

Post Town

County

Post Code

Tel. No.

E-Mail

### Purchase Details

Date Purchased

Purchased From

Town of purchase

Receipt Number

### Security Details

Key Number

Registration  
Number

*For office use*

Parts & Service: 020 8988 7400 / E-mail: [Parts@clarkeinternational.com](mailto:Parts@clarkeinternational.com) or [Service@clarkeinternational.com](mailto:Service@clarkeinternational.com)