
INSTRUCTION MANUAL **Super Mini**

Wi-Fi Switch Module


QS-WIFI-S06-16A







TECHNICAL SPECIFICATIONS Product type Mini Wi-Fi Switch Module Voltage 100-250V AC Current: 16A 3680W/300W for LED Max. load Operation 2.4GHz~2.4835GHz frequency WiFi 802.11 b/q/n Operation temp. -10°C - +40°C Operation range ≤ 200 m Dims (WxDxH) 39X39X15 mm IP20 IP rating Warranty 1 years




Global international operation Whenever & Wherever You are All-in-one Mobile App









Inhouse local operation










INSTALLATION

environment

A Warnings:

- 1. Installation must be carried out by a qualified electrician in accordance with local regulations.
- 2. Keep the device out of reach of children. 3. Keep the device away from water , damp or hot
- 4. Install the device away from strong signal sources such as microwave oven that may cause signal interruption resulted to abnormal operation of the
- device. 5. Obstruction by concrete wall or metallic materials may reduce the effective operation range of the device and should be avoided.
- 6. Do NOT attempt to disassemble, repair or modify the device.





MANUAL OVERRIDE


The switch module terminal reserves the access of manual override function for the en d-user to switch on/off.

Switch on/off for permanent on/off function.

- 1) Both the adjustment on A pp and sw itch can overw rite each other, the last adjustment remains in memory.
- 2) The App control is synchronized with the manual switch.







Wiring Instructions and Diagrams

- 1.Turn off the power supply before carrying out any electrical installation work.
- 2.Connect wires according to the wiring diagram.
- 3.Insert the module into the junction box. 4.Turn on the power supply and follow switch module
- configuration instructions. Notes: Take your smartphone close to the switch module when you're configuring, and make sure you have min. 50% Wi-Fi signal.

FAQ

- Q1: What should I do if I can't configure the switch
- a. Please check whether device is powered on. b. Make sure your mobile and switch module
- are under the same 2.4 Ghz WIFI network.
- c. Whether it's in good internet conditions. d. Make sure the password entered in App is correct.
- e. Make sure the wiring is correct.

O2: What device can be connected to this Wi-Fi switch

Most of your household electrical appliances can be, such as lamps, laundry machine, coffe maker, etc.

Q3: What happens if the WIFI goes off?

You can still control the device connected the switch module with your traditional switch and once WIFI is active again the device connected to module will connect automatically to your WIFI network.

Q4: What should I do if I change the WIFI network or change the password?

You have to re-connect our Wi-Fi switch module to the new Wi-Fi network accordingly as per the App User Manual.

O5: How do I reset the device?

- 1. Turn on/off manual switch which is connected to the device until the indicator light flash quickly.
 - 2. Power on/off device for 5 times until the indicator light flash.
 - 3. Hold the reset button for 10 sec. until the light indicator flash.

APP USER MANUAL





IOS APP

Android APP




Scan the QR code to download Smart Life App. or you can also search keyword "Smart Life" at App Store or Google play to download App.



Smart Life - Smart Living



Log in or register your account with your mobile number or e-mail address. Type in the verification code sent to your mobile or mail box, then set your login password. Click "Create Family" to enter into the APP.



After the wiring of switch module is done, press the traditional switch to turn ON/OFF cycle for 5 times (keep time interval not too short) until the indicator light flash for pairing mode.

If the WIFI module is used only for a power outlet without a tradicional switch, you have to turn ON/OFF cycle the power braker for 5 times (keep time interval not too short)



Open the APP, selecting "+" on top right to add device. Choose the type of device, for example "Smart Lighting".



Make sure your smart phone and Wi-Fi switch module are under the same Wi-Fi network at 2.4GHz connection. Confirm when the indicator light flash for pairing mode.

G



The connecting will take about 10-120 seconds to complete depending on your network condition.




When pairing is done, the Wi-Fi switch will be shown on the App.

7

Now you can control your device with your smartphone



Connect to amazon alexa or Google Assistant for voice control, or share the devices with your families or friends.



Enjoy your smart life of home automation for lighting control by using our All-in-one mobile app wherever you are in the world or simply by voice control when you are sitting at home comfortably.