

**WE REALLY
APPRECIATE
YOUR PURCHASE**

~thank you~

Features

- Bus connector: PCI Express x1
- Compliant with PCI Express 1.1
- Baud rate (serial port): Up to 115.2 Kbps
- FIFO (serial port): 256 Bytes
- UART (serial port): 16C550

Package contents

- Serial Port / Parallel Port PCIe Card
- Quick Start Guide

System Requirements

1. An available PCIe slot
2. Windows® 11 / 10 / 8.1 / 7 (32-/64-bit)
3. Windows® Server 2019 / 2016 / 2012 R2
2012 / 2008 R2 / 2008 & 2003 (32-/64-bit)
4. Linux kernel 2.6 and later version

Driver Installation

If your system has the built-in driver can use directly. Driver install is not necessary.

1. Please go to SIIG website. Use product number "LB-xxxxxx-S1" to find & download the driver.
2. Click "Setup.exe" to install the driver
3. Follow the Installation steps to complete the driver Installation

Support

For more info or tech support
<http://www.siig.com/support>



Serial Port / Parallel Port PCIe Card

Quick Start Guide

- **LB-P00014-S1** Single Parallel port
- **LB-S00014-S1** Dual Serial port
- **LB-S00114-S1** Quad Serial port
- **LB-SP0014-S1** Single Serial port plus Single Parallel port
- **LB-SP0114-S1** Dual Serial port plus Single Parallel port

