

FOLLOW US

FACEBOOK • INSTAGRAM • TWITTER • YOUTUBE



Visit our **YouTube Channel: EPC Headsets** for videos about Pairing the Air Pro Wireless PTT Combo Kit.

EARPHONE
CONNECTION

888.372.1888

www.earphoneconnect.com

25139 Avenue Stanford
Valencia, CA 91355

TO CONNECT WIRED HEADSETS:

1. Make sure the Bluetooth microphones are off.

2. Hold the microphone cable above the arrow alignment mark.

3. Align with arrow on the adapter then click into place.

4. To remove, pull up on the spring-loaded cylindrical metal below the arrow on the cable.



► **Note:** When Bluetooth slide switch is in the “Off” position, no Bluetooth device can be used. This is effective if you want to use the radio with no microphone attached. In this state you can transmit and receive through the radio.

► Leave the Bluetooth switch in the “On” position to use the Wireless PTT unit.

Note: Not compatible with Motorola Radios using Built-In Bluetooth.

Note: When Bluetooth slide switch is in the off position no Bluetooth device can be used. This is effective if you want to use the radio with no microphone attached. In this state you can transmit and receive through the radio.

Leave the Bluetooth switch on to use the Wireless PTT unit.

MANUFACTURER’S LIMITED WARRANTY

Your Sales Receipt is required to validate & obtain warranty services.

Your EPC product is warranted against internal defects in material or workmanship. All of our earphones are warranted for 12 months. Hygiene restrictions prevent us from extending our limited warranty to wearable parts such as: Fin Ultra™ ear tips, earmolds, clear tubes & ear inserts.

The warranty is extended to the original purchaser only and does not cover the following:

- * Physical abuse
- * Improper maintenance of unit
- * Damage from tugging or pulling
- * Frayed, torn or exposed wires
- * Crushing or smashing in any way, shape or form

General misuse of the item such as: Excessive voltage, tampering with the unit or repairs attempted by someone other than the manufacturer will void the MANUFACTURER’S LIMITED WARRANTY.

The manufacturer reserves the right to evaluate & refuse warranty based on their evaluation. In order to obtain warranty services, proof of purchase must be returned along with the product.

For Returns Dept. & Return Authorization # Call Toll Free: (888) 372-1888.

After calling, send your return along with your name address & Return Authorization number to:

The Earphone Connection, Inc.

25139 Avenue Stanford

Valencia, CA 91355

Earphone Connection, Inc. products are designed to produce a specific audio output level at maximum rated power. Modifying these devices in any way including adding or removing components and accessories may change the audio output of the device and could result in PERMANENT HEARING DAMAGE.

Many countries have regulations defining the amount of noise that an individual can be subjected to during a normal workday. Compliance is application-dependent and standards vary. It is the SOLE RESPONSIBILITY of the end user to determine applicability and compliance to local hearing protection regulations.

Earphone Connection, Inc. strongly recommends that the radio is off before installation of audio accessory.

Once audio accessory is securely installed radio can be turned on. Radio volume switch is recommended to set at low position and adjusted once radio is turned on.

EARPHONE
CONNECTION

BLE

AIR PRO WIRELESS WIRELESS PTT COMBO KIT



Bluetooth™

Visit our **YouTube Channel: EPC Headsets** for videos about Pairing the Air Pro Wireless PTT Combo Kit.

www.earphoneconnect.com

**AIR PRO WIRELESS PTT COMBO KIT
FOR MOTOROLA APX INCLUDES:**

BTR REMOTE PTT SWITCH

CHARGING PORT

PTT/PAIRING

LED

EASY-CONNECT
CONNECTION FOR
WIRED HEADSETS

ON/OFF KILL SWITCH:
Turn ON & OFF Bluetooth
devices. ("OFF" mode
reverts radio to talk & listen).

BUMP-FREE
PAIRING/PTT BUTTON:
The pairing PTT button can be
used as a transmit button to the
external device.

**BTD BLUETOOTH ADAPTER
EP-BTD34EC-S BLE**

**USE WITH YOUR ALL YOUR FAVORITE
WIRELESS EARBUD BRANDS.**

Wireless Earbuds Not Included.



PAIRING BLUETOOTH DEVICES:

STEP 1. Attached BLE radio adapter to radio. Power up radio. Adapter will automatically enter pairing mode stated by BLUE/RED flash. Engage Bluetooth device into pairing mode. Refer to your manual for this action. When solid Blue LED appears on the BLE adapter, pairing is complete.

LINKING REMOTE PTT SWITCH:

STEP 2. Power up Remote PTT Switch by pressing on the PTT button until first LED appears then release. The Remote PTT switch will flash BLUE/RED, at this point press the PTT button twice, this will link the Switch to the adapter. Now the link is complete. You will need to follow this step every time the Switch is powered up.

To power OFF the BLE Adapter simply turn off the radio.

To power OFF the Remote PTT Switch, wait about 20 seconds after the radio is powered off then press the PTT Switch button for about 15 to 20 seconds until the LED flashes Red then release.

To charge the Remote PTT Switch, connect the USB cable to a wall charger and the other end to the Switch. 3 – 4 hours full charge. A full charge should last about 400 hours.

TO PAIR ADDITIONAL BLUETOOTH DEVICES:

You will need to manually pair the devices. Step 1: Hold down the PTT/Pairing button on the radio adapter with the tip of your finger and power up the radio at the same time. Keep holding until the LED flashed BLUE/RED then release, follow the same pairing procedure in step 1 from above.

TO RE-PAIR THE REMOTE FINGER SWITCH, FOLLOW THESE STEPS.

STEP 1: Hold down the PTT/Pairing button on the radio adapter with the tip of your finger and power up the radio at the same time. Keep holding until the LED flashed BLUE/RED then release, then press again. The LED will flash a slow BLUE/RED. Now the adapter is in pairing mode for the Finger Switch. Follow Step 2 from “Linking Remote PTT Switch” section to complete the process.

Note: Insert both earbuds to ears to ensure a solid connection, then take one out and use one at a time to conserve earbud battery life if you choose.