


# L7 | LEVER DIGITAL DOOR LOCK



Combining traditional with digital the L7 Lever Digital Door Lock is both stylish, elegant and of course traditional. The L7 digital door lock is designed for convenience without compromising security. By embedding the fingerprint scanner into the handle simply walk up grab the handle and you're in!

## COLOURS AVAILABLE



## MODULES



## TECHNICAL SPECIFICATIONS

<b>Material</b>	Aluminium, Zinc & Tempering Glass
<b>Lock Dimensions</b>	Height: 363mm, Width: 81mm, Thickness: 77mm (including handle)
<b>Mortise Dimensions</b>	Without Mortise Plate – Height: 165mm, Width: 14mm, Depth: 85mm With Mortise Plate – Height: 235mm, Width: 2mm, Depth: 24mm
<b>Unlocking Options</b>	Fingerprint / Pin Code / Swipe Card / Key
<b>Fingerprint Capacity</b>	100
<b>Fingerprint Sensor</b>	FPC
<b>RF Card Capacity</b>	100
<b>Pin Code</b>	6-12 digits 1 Master code 10 user pin codes
<b>LCD Display</b>	No
<b>RF Frequency</b>	13.56 MHz
<b>Keypad Material</b>	Tempered Glass
<b>Sliding Enclosure</b>	No
<b>Voice Guided</b>	Yes - English, Chinese, Portuguese & French

<b>Suitable Fitting Materials</b>	Wood, Steel & Aluminium
<b>Operating Conditions</b>	Temperature Range: -20°C to 55°C Humidity: 15% to 90%
<b>Door Thickness</b>	30-60 mm
<b>Mortise Options</b>	SD7260
<b>Recognition Time</b>	<0.5s
<b>False Acceptance Rate (FAR)</b>	<0.0001%
<b>False Recognition Rate (FRR)</b>	0.10%
<b>Power Supply</b>	8 x AA alkaline batteries
<b>Battery Life</b>	Up to 1 year
<b>Back Up Power Source</b>	USB power port
<b>Wrong Code Entry</b>	10 attempts will deactivate the keypad for 5 minutes
<b>Passage Mode</b>	Yes (Manual Mode)
<b>Auto Lock Options</b>	Yes
<b>Opening Direction</b>	Universal
<b>Backset</b>	60mm

Ask your query from your fav social media

