


PANTONE 285 C

95±1mm

onn.

USER GUIDE

Small Wi-Fi Speaker



100135446, EN, 02282024

Contents & Information

INFORMATION

Features

OVERVIEW

SAFETY PRECAUTIONS

OPERATION

CLEANING & CARE

SPECIFICATIONS

TROUBLESHOOTING

Features

- Multi-room Wi-Fi streaming- Play different audio content on different speakers simultaneously
- Bluetooth wireless technology streams audio from all you devices
- Broadcast mode- Stream high quality audio from anywhere in the house without calls or interruptions
- Party Sync modes- Can pair with other onn. speakers
- Apple AirPlay2 multi-room streaming- can pair with other onn. Wi-Fi speakers or AirPlay speakers
- Power sound in portable, compact design
- IP67 Waterproof
- 10W RMS output /40W peak output(4×RMS)
- Broadcast mode compatible mode:100135446, 100136627, 100136628
- Up to 15 hours of playtime
- Charging cable: 60cm

Overview

1

2

3

1. WI-FI SPEAKER

2. CHARGING CABLE

3. USER GUIDE

1 2 3 4 5

6 7

1. Wi-Fi indicator

2. Source button

3. Play button

4. Power button

5. Battery indicator

6. Bluetooth indicator

7. Volume control knob

Safety Precautions

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device must not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

WARNING:

Cancer and Reproductive Harm - [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

Warning:

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. Need help? We're here for you every day from 7 a.m.-9 p.m. CST. Give us a call at 1-888-516-2630. Produced for Walmart Inc., Bentonville,AR 72716

**FCC SAR statement**

RF Exposure Compliance

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. End user must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

The portable device is designed to meet the requirements for exposure to radio waves established by the Federal Communications Commission (USA). These requirements set a SAR limit of 1.6 W/kg averaged over one gram of tissue. The highest SAR value reported under this standard during product certification for use when properly worn on the body.

For product assistance

WE CAN HELP

1-888-516-2630

7 DAYS/WEEK

7:00am- 9:00pm CST

THIS GUIDE CONTAINS

IMPORTANT SAFETY

INFORMATION.

PLEASE READ AND KEEP

FOR FUTURE REFERENCE.

Find more at Walmart.com

Manufactured in China for: Walmart, Inc.

Ver:00.02/28/24

FCC ID: 2ALXK-ONN100135446

Front


95±1mm

760mm

Operation

FIRST TIME SETUP

Device may need to be charged before use.



CAUTION

Only use a USB charging device that is 5V DC output.

1. POWER ON

Press and hold power button for 2 seconds until you hear "power on".

2. POWER OFF

Press and hold power button for 2 seconds until you hear "power off".

PAIRING (Bluetooth mode)

One device connect to speaker

1. When you first power on, this speaker will enter into Wi-Fi mode automatically. X1 press, you will see bluetooth indicator flash.

2. Find "onn. Wi-Fi Speaker S" on your BT device and connect it.

Two devices connect to speaker(multipoint connection)

1. Press and hold source button 2 sec, now you can find it from your 2nd Bluetooth.






2. Find "onn. Wi-Fi Speaker S" from your device in Wi-Fi searching list and select it.

3. Set up to join"XXX".






4. Select and go to next, it takes 13-15 seconds to join network.

5.Select this speaker from your AirPlay picker list.

PLAY MUSIC

Control	Action	Result
	×1 press	Play/pause
	×2 press	To next song
	×3 press	To previous song
	Rotate Clockwise	Increase volume
	Clockwise	Reduce volume


OTHER OPERATION


Control	Action	Result
	Hold 2 sec	Power on/power off
	×2 Press	Broadcast
	×1 press	Switch different mode
	Hold 2 sec	Multipoint connection
	Hold 5 sec	Reset Wi-Fi/BT pairing

BROADCAST

Enter broadcast

When this speaker connect to a Bluetooth device, ×2 press power button to entry into BIS mode, you will hear "Broadcast", then ×2 press other speakers, they can connect together.





100136628

100136627

10035446

Exit broadcast

X2 Press power button


\*Sync mode compatible mode list:

10035446 100136627 100136628


CHARGE

It is recommended that you use the provided charging cable, connect USB-A end to 5V power adapter or other devices, connect USB-C end to the charging port of it.

Note: Device may take up to 3 hours to get fully charged when at 0% battery.




About 3 hours



(5V 2A)

Charging: Battery indicator is flashing



Fully charged: Battery indicator states on

Cleaning & Care

CLEANING

1. Wipe down surface with a light cloth

2. Never use abrasive pads to clean device

3. Avoid using liquids to clean device

Specifications

Weight

0.701lb

Color

Rich black

Product Dimensions (L x W x H)

4.06 x 1.84x 4.02 inches

Troubleshooting

Problem	Prevention/Solution
Cannot find "onn. Wi-Fi Speaker S" on Bluetooth device	Ensure Bluetooth function is activated on Bluetooth device. Ensure you have paired your unit with Bluetooth device. Ensure this speaker is in Bluetooth mode, press and hold Source button 2 seconds, "Bluetooth Pairing" tone) to enter into Bluetooth pairing. Ensure this speaker is in Bluetooth mode, press and hold Source button 2 seconds, "Bluetooth Reset" tone) to clean pairing records and entry Bluetooth pairing. Factory Reset: Press and hold Source button and Play button 3s, this speaker will power off. Then power on and enter into Bluetooth mode to pairing.
Cannot find "onn. Wi-Fi Speaker S" on Wi-Fi searching list	Ensure this speaker enter into Wi-Fi mode. Ensure Wi-Fi function is activated on iPhone/iPad/Mac device. Ensure this speaker is under AirPlay network configuration mode, press and hold Source button 2 seconds, "Wi-Fi Ready" tone) to clean AirPlay network configuration records. Factory Reset: Press and hold Source button and Play button 3s, this speaker will power off. Then power on and enter into Wi-Fi mode to pairing.
Cannot find "onn. Wi-Fi Speaker S" on AirPlay picker list	Ensure this speaker connect Wi-Fi successfully, you hear "AirPlay ready" tone and Wi-Fi indicator starts on. Re-configure the network: Press and hold Source button 2 seconds, "Wi-Fi Ready" tone). Factory Reset: Press and hold Source button and Play button 3s, this speaker will power off. Then power on and enter into Bluetooth mode to pairing.
Sound is not produced	Ensure this speaker is under Bluetooth pairing or AirPlay pairing, and select the correct input source. Adjust the volume control knob.
Cannot power on	Charge battery.

Back