



Light Color	Operating Status	Light Status
Blue	No configuration	Steady on
	Ready for configuration	Blinks quickly / Slowly
	Configuration successfully, Network connect	Off
	Configuration successfully, Network disconnect	Steady on
	Configuration successfully, sending Data	Blinks one time
	Access Learning mode	Steady on
	Learning instruction receive	Off
	Reset	Keep pressing reset button 5s

Add MoesGo SMART IR

1: Download Smart Life APP

QR codes for Google Play and App Store.

2: Registration or log in

- Download "Smart Life" Application.
- Enter the Register/Login interface: tap "Register" to create an account by entering your phone number to get verification code and "Set pass-word". Choose "Log in" if you already have a Smart life account

3: Configure the APP to MoesGo Smart IR

Preparation: Ensure the device has connected with electricity; ensure your phone has connected to WIFI router and is able to connect to the internet . Note: this device only supports 2.4G network. If you have connected 5G network, please disconnect 5G network firstly.

- Tap the icon "+" at the top right corner and Select Device Type: tap "All" and choose "Infrared Universal Remote Control". Add Device interface will be available then.
- Press and hold the reset button for at least 5 seconds until the network configuration indicator blinks
- Press "Confirm indicator rapidly blink"
- After Device added successfully, it can be found on "My Family" list.

Add Remote Control

Choose your existing appliance and add remote , such as Air conditioner, TV,STB,TV box ,FAN (support more than 4000+main brand).

You can also choose "Copy button" function to learn if some of the appliance cannot be controlled.

Copy Button Operation

If you cannot find the remote which is able to control appliances, you can learn the function through copy button.(Notice: Currently copy button function only support TV / STB /TV BOX / FAN, exclude Air conditioner)

Step 1: Click to enter the connected device

Step 2: Click the edit button in the upper right corner

Step 3: Select "Copy button" in the popup menu bar

Step 4: Click the on/off button

Step 5: Press your original remote button, APP will redirect to next step automatically.

Step 6: Finish copying one button, you should press the related button on APP to check if works fine.

Note:You may continuously choose to copy more or press the up right corner "Done" to save.

DIY OPERATION

If you can't find your IR appliance in existed appliance form, you may ask DIY function for help.

Step 1: Click the DIY button.

Step 2: Click "next step".

Step 3: Press your original remote button, APP will redirect to next step automatically.

Step 4: Rechrستن.

Step 5: Save settings.

Note:If need to change or add more button, you can choose up right corner "Edit" button for help.

NOTICE

1: Support learning of 38K carrier frequency, if you cannot receive instruction from original remote, the main reason maybe mismatching of carrier frequency. In this case, you cannot learn the instruction from original remote.

2: Insure MoesGo SMART IR receive instruction regularly, please do not long press original remote to give instruction, a short press should be enough.

Set your Echo speaker by Alexa APP

1.If you have finished to install Smart Life then open Amazon Alexa App: sign in your Alexa account and enter password.

2.Click the menu on the left corner-click "Settings: choose "Set up a new device"(choose a device ,like Echo)Note: When the below page appears, long press the small dot on your Echo device until the light turns to yellow. Then Click Continue on App

Note: at this moment, the mobile phone cannot open a variety of VPN software.

Choose your own WiFi and wait for a few minutes. After an introduction video, click next step, it will enter Home page automatically. Now the Echo had connected to Wi-Fi successfully.

Enable Smart Life Skill in Alexa

Step 1: Choose "Skill" in the option bar, and then search "SMART Life" in the input box.

Step 2: Select Smart Life in the search results, and then click "Enable Skill".

Step 3: Then input the user name and password of Smart Life APP that you had previously registered.

Control the device by voice

After the above operation is successful, you can control the device via Echo.

1:Discover Device

Firstly , you need to say to the Echo: Echo (or Alexa), discover my devices. Echo will start to find the device which is added in the Smart Life APP. It will take about 20 seconds, then Echo will tell you the result. You can also click "Discover devices" in Alexa APP , then it will show the devices that have been found successfully .

2:Control Device by Voice

Note: The name of the device must be consistent with the addition of Smart Life APP.

You can also group the device and give instructions to control them together.

Smart Home interface showing device groups and individual controls.

Note: Echo is one of the wake-up names, which can be any of the three names (Settings) Alexa, Echo, Amazon.

3:Support Skill List

You can control the devices by instructions like these: Alexa(or Echo), turn on the Devices Alexa(or Echo),turn off the Devices.

Google Assistant —Activate Smart Life in Google Home App

Preparation

- Have downloaded the Google Home App-compatible With Android(4.2 or higher) or ISO(8.0 or higher)smart-phones or tablet.
- Have registered your google Account.

Have paired Device with Smart Life App and named it with a recognizable name.

Have finished setting up Google Home

Step 1: Open Google Home App ;tap() on the upper left corner; select "More Settings" to enter the next interface.

Google Assistant interface showing "More settings" option.

Step 2: Choose "Services" in the options bar and select "Smart Life" to enter the next interface.

Services menu with Smart Life highlighted.

Smart Life app interface showing "Link Account" button.

Step 3: Tap "Link Account", then sign in your smart Life Account.

Smart Life app interface showing login options: Phone number or Email, Password, and Link Account.

Step 4: Tap "Link Now", after your Smart Life account had linked to Google Assistant, the smart devices will automatically appear.

Command the Device through Your Voice.

Firstly, you need to say "OK Google ,talk to Smart Life" to wake up the Smart Life. Then you can control the device by instructions like these: Turn on the/ Turn off the

Note: After Smart Life has been wakened up ,you may say "Cancel "or "Stop" to exit Smart Life or say "Nothing" when you hear "what can I do for you " .Then you can say "OK Google, talk to Smart Life" to start voice control.

Voice Control Instruct

Device	Alexa command list
AC	Alexa, turn on 'device name' Alexa, turn off 'device name' Alexa, set 'device name' temperature to ** degrees Alexa, increase 'device name' temperature Alexa, decrease 'device name' temperature
STP	Alexa, turn on 'device name' Alexa, turn off 'device name' Alexa, channel up on 'device name' Alexa, channel down on 'device name' Alexa, volume up/down 'device name' Alexa, change channel of 'device name' to 'channel number'
TV	same as STP
Device	Google Home command list
AC	Hi google, turn on/turn off the 'device name' Hi google, set 'device name' temperature to ** degrees Hi google, make 'device name' warmer/cooler
STP	Hi google, turn on/turn off the 'device name'
TV	Hi google, turn on/turn off the 'device name'

FAQ

1. Product

1.1: Built-in Battery included?

A: No built-in battery, need connect with power directly(USB line & Power adapter available);

1.2: 5G wifi supportable?

A: Only support 2.4G wifi, no 5G wifi acceptable

1.3: Is this IR universal works with internal code library?

A: Code library keeps in cloud, you must connect with internet

2. Application

2.1: Appliance compatible?

A: Support majority leading top brand include TV /STP /AC/DVD

2.2: Brand Applicable?

A: Please check brand list in App

3. Smart Device compatible?

A: Google Alexa, ECHO

4. Can they go through-wall or control AC from up stair or down stair?

A: No, Infrared cannot go through-wall

5. Is this device work with WIFI ?Must they use with smart gateway?

A: MoesGo Smart IR work completely with WIFI control, no smart gateway required

6. How many home appliances can MoesGo Smart IR control at the same time

A: MoesGo Smart IR can control multiple appliances in one room through "Smart Life" APP;

7. What is the scope can MoesGo Smart IR works

A: Within Diameter 16 meters,

8. How to use MoesGo Smart IR learning function?

A: Please check copy button instruction.

Model	SRW-001
Power Input	DC 5V/1A (Micro Usb2.0)
Stand-by Power	≤0.5W
Infrared distance	≤10m (affected by the environment)
IR control direction	Multiple Way
Operating Temperature	0-50°C (32-122°F)
Operating humidity	≤85%RH
Connection type	2.4GHz 802.11b/g/n
Carrier Frequency	38KHZ
APP SUPPORT	Android 4.0/IOS 8.0 above

Trouble Shooting Guide

Why MoesGo'S Smart Universal Remote can't control the appliance?

Step 1: Make sure if the network works well in Smart IR (Touch any button on the smart app remote side, if the indicator light works fine ,then network ok)

Step 2: Check if there is obstacle between remote and appliance, within 8 meters

Step 3: Confirm if the original remote control is Infrared control(Press the remote control after warding off the remote control head with hand or other object, if appliance do not work, it's Infrared control. If not work, it should be Bluetooth or radio frequency control)

Thank you for your support and purchase at we MoesGo, we are always here for your complete satisfaction, just feel free to share your great shopping experience with us.

★★★★★

If you have any other need, please do not hesitate to contact us first, we will try to meet your demand.

Shenzhen Juku Intelligent Technology Co., Ltd.
Address: 303, Building 12, Jinshun Industrial Zone, No.20, Huan cheng south Road, Ma'antang Community, Bantian Street, Longgang District, Shenzhen, China
Tel: +86-577-57188815
Email: service@moesgo.com

AMZLAB GmbH
Laubenhof 23, 45326 Essen