



Z-Wave Protocol Implementation Conformance Statement

10 Year Smoke Detector and Siren

General Information

| | |
|-------------------------|----------------|
| Product Identifier: | Ei600ZW |
| Brand Name: | Popp |
| Product Version: | HW: 1 FW: 1.00 |
| Z-Wave Certification #: | ZC10-16125370 |

Product Features

| | |
|------------------|-------|
| Outdoor Use | No |
| Battery Type | CR2 |
| Battery Quantity | 1 |
| Color | White |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|---------------------------------|--|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x0004 |
| Z-Wave Product Type: | 0x0004 |
| Z-Wave Hardware Platform: | ZM5202 |
| Z-Wave Development Kit Version: | 6.51.06 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Notification Sensor / Listening Sleeping Slave |

Association Group Information

| Group # / Max | Description |
|---------------|-------------|
|---------------|-------------|

Z-Wave Protocol Implementation Conformance Statement

(Continued)

10 Year Smoke Detector and Siren

- 2 / 10
- Alarm Reports. All devices in this group will receive Alarm notifications (Smoke , Battery Low, Tamper)
- 3 / 10
- Switching Command. All devices in this group will receive a BASIC SET command on Smoke Alarms.
Configuration parameter 3 and 4 will define when ON and when OFF is sent.

Supported Command Classes (15):

| | |
|----------------------------------|--------------------------|
| Association Group Information V2 | Association V2 |
| Basic | Battery |
| Configuration | Device Reset Locally |
| Firmware Update Meta-Data V3 | Manufacturer Specific V2 |
| Notification V5 | Powerlevel |
| Security S0 | Sensor Binary V2 |
| Switch Binary | Version V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

Basic