




Z50






1 SPECIFICATIONS

- 1 SPECIFICATIONS
- Product Model: Z50
- Size: 82*52*31.15mm
- Input: 5V=2A
- Storage: TF card storage, maximum support 128GB, cycle recording
- Wi-Fi: Wi-Fi/2.4GHz
- G-Sensor: Built-in 3 Gyro sensor, motion locking, adjustable sensitivity via App

2 PACKAGE CONTENTS

		
Dash Cam	Power Cable	USB Charger
		
Installation Tool	User Guide	3M Adhesive
		
Static Sticker	Bracket	

3 PRODUCT OVERVIEW

	
1 Dash Cam Screen	5 MIC
	
2 Working Indicator	6 TF Card Slot
	
3 AV Interface	7 Lens
	
4 Type-C Power Interface	


Button Description	Function description
1 Set	Click the button to enter the settings selection.
2 Sound Recording	Click the button to turn on/off recording.
3 Album	Click the button to open the album.
4 Lock	Click the button to turn on/off the screen. Reset: Long press 6s to reset.

4 LED INDICATOR INSTRUCTION


Product status	Indicator status
Working fine	Blue light is always on
Incident video/emergency video/photo video	Purple light flashes quickly
Abnormal status/upgrading	Red light flashes quickly
USB data transmission mode	Green light is always on
Test pattern	White light is always on
Parking monitoring	Red light is always on

5 INSTALLATION


1. Clean an area on the windshield where you wish the Dash Cam to be installed, this assists in adhesion.
2. Open the protection cover of TF card slot, insert the memory card into the slot, pay attention to the front and back sides, and close the protection cover after completion.



3. Remove the protective film from the back of the bracket, attach the adhesive side of the mount on the windshield where it has an unobstructed view of the road but does not interfere with the driver's view. As shown below.



4. Use the installation tool to lift the edges of the windshield/molding and tuck in the power cable. Connect the Dash Cam to the car charger (plugged into cigarette lighter socket) and power cable.



5. After the car starts, the Dash Cam powers up and starts recording.

6 APP INSTRUCTION


- Install DDPAI App**
Scan the QR code to download the "DDPAI" App.



Pair Smart Phone to Dash Cam


1. Keep the Dash Cam and mobile phone within 2.5meters.
2. Launch DDPAI App, tap on "Device" > Connect new devices".
3. Choose your DDPAI Dash Cam from the network list(For Android system, App will start to search Dash Cam network automatically. For iOS phone, turn on WLAN from "Settings->WLAN"). The Dash Cam's default SSID (or Wi-Fi name) is DDPAI_Z50_XXXX.
4. Enter the password (the default password is '1234567890').
5. Enter DDPAI App, wait a few seconds until the preview screen show.

- Preview**
1. Open the DDPAI App, and add your Dash Cam.
2. Select "Device" > "Entering" tab, this will bring you to the preview page.



- Rotate your smart phone or press expand icon, turn the preview screen to landscape mode.

- Playback**
Tap and left/right drag timeline bar at the screen bottom to create the starting point of the recording you wish to preview, then tap on thumbnail when you have made your selection, or wait for 5 sec for buffering, now you can watch the history recording.




- Download Video Files**
1. Tap and left/right drag timeline bar at the screen bottom to create the starting point of the recording you wish to download, then tap on thumbnail when you have made your selection, or wait for 5 sec for buffering, to enter the download start screen.
2. Tap on from preview screen to enter the download interface.

CONTACT

- www.ddpai.com
- feedback@ddpai.com
- DDPAI Technology Co., Ltd
- Floor 12, Yihua finance building, Software Park, Yuehai Sub district, Nanshan district, Shenzhen

For more information and FAQs, Please scan the QR code:



客户品牌: DDPAI		项目名称: 认证书 (国内海外通用版)		折叠样式: 风琴折叠式		产品料号: 20204000211		版本类型: V1.2		归档日期: 20210315					
DDPAI 		FCC statement This device complies with Part 15 of the FCC Rules. operation must meet the following two conditions: (1) This device may not cause harmful interference. (2) This device must accept any interference received, including interference that may cause undesired operation. Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception,		which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: - Relocate or relocate the receiving antenna. - Increase the separation between the equipment and receiver. - Connect the equipment to an outlet on a circuit different from that to which the receiver is connected. - Consult the dealer or an experienced radio/TV technician for help. FCC Radiation Exposure Statement: This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.		WEEE Notice The Directive on Waste Electrical and Electronic Equipment (WEEE), which entered into force as European law on 14/02/2014, resulted in a major change in the treatment of electrical equipment at end-of-life. The purpose of this Directive is, as a first priority, the prevention of WEEE, and in addition, to promote the reuse, recycling and other forms of recovery of such wastes so as to reduce disposal. The WEEE logo on the product or on its box indicating collection for electrical and electronic equipment consists of the crossed-out wheeled bin, as shown below.  This product must not be disposed of or dumped with your other household waste. You are liable to dispose of all your electronic or electrical waste equipment by relocating over to the specified collection point for recycling of such hazardous waste. Isolated collection and proper recovery of your electronic and electrical		For Products That Include Batteries EU Batteries Directive 2013/56/EU A new battery directive 2013/56/EU on Battery and Accumulator replacing directive entered into force on the 10/7/2013. The directive applies to all types of batteries and accumulators (AA, AAA, button cells, lead acid, rechargeable packs) including those incorporated into appliances except for military, medical and power tool applications. The directive sets out rules for collection, treatment, recycling and disposal of batteries, and aims to prohibit certain hazardous substances and to improve environmental performance of batteries and all operators in the supply chain. Instructions for Users on Removal, Recycling and Disposal of Used Batteries To remove the batteries from your equipment or remote control, reverse the procedure described in the owner's manual for inserting batteries. For products with a built-in battery that lasts for the lifetime of the product removal will not be possible for the user. In this case, recycling or recovery centers handle the dismantling of the product and the removal of the battery. If for any reason, it becomes necessary to replace such a battery, this procedure must be performed by authorized service centers. In the European Union and other locations, it is illegal to dispose of any battery with household trash. All batteries must be disposed of in an environmentally sound manner. Contact your local waste-management officials for information regarding the environmentally sound collection, recycling and disposal of used batteries. WARNING: Danger of explosion if battery is incorrectly replaced. To reduce risk of fire or burns, don't disassemble, crush, puncture, short external contacts, expose to temperature above 60°C (140°F), or dispose of in fire or water. Replace only with specified batteries. The symbol indicating 'separate collection' for all batteries and accumulators shall be the crossed-out wheeled bin shown below.  In case of batteries, accumulators and button cells containing more than 0.005 % mercury, more than 0.002 % cadmium or more than 0.004 % lead, shall		be marked with the chemical symbol for the metal concerned: Hg, Cd or Pb respectively. Please Refer to the below symbol.  CAUTION - The product's optimal temperature range is -20°C – 70°C. - Install the device near the rear-view mirror to obtain the best open-field view. Do NOT install the Dash Cam in a location that will obstruct your required driving view. - Dash Cam with built-in eMMC card: Featuring high efficiency, stability and durable. The dash cam should be formatted via App or PC regularly to extend its lifespan. - Dash Cam with external memory card: Support brand Class 10 micro SD card up to 128GB Max. The dash cam should be formatted before using and it can be formatted via App or PC regularly to extend its lifespan. - Do not use any cardboard, paper towel, or napkins to clean the lens. - Do not attempt to repair, dismantle, or modify the Dash Camera hardware by yourself. - Do not install the product in an environment with high humidity, or combustible gases or liquids. - Drawings for illustration purpose only. Actual product may vary due to product enhancement.		Примечание WEEE Европейский закон, вступивший в силу 14.02.2014, Директива об отходах электрического и электронного оборудования (WEEE). Были внесены серьезные изменения в утилизацию электронного оборудования, срок действия которого истекает. Первая цель директивы - предотвратить WEEE, а также улучшить повторное использование, переработку и другие формы утилизации таких отходов для уменьшения количества выхлопных газов. Логотип WEEE на продукте или его упаковке указывает на переработку электрического и электронного оборудования с помощью мусорных баков с выносными колесами, как показано ниже.  Этот продукт нельзя обрабатывать или выбрасывать вместе с другим бытовым мусором. Вы несете ответственность за утилизацию всех электронных или электрических отходов.		Соответствует RoHS Этот продукт соответствует Директиве 2011/65 / EU Европейской конференции и Европейской комиссии от 8 июня 2011 г. об ограничении использования опасных веществ в электрическом и электронном оборудовании.	
Для продуктов, содержащих батареи Директива Европейского Союза о батареях 2013/56 / EU Новая директива 2013/56 / EU по батареям и аккумуляторам заменяет директиву, вступившую в силу 01.07.2013. Эта директива применяется ко всем типам батарей и аккумуляторов (AA, AAA, клипочные батареи, свинцово-кислотные батареи и аккумуляторные батареи), включая батареи, встроенные в электрические приборы, кроме военных, медицинских и электронных инструментов. Директива устанавливает правила сбора, обработки, переработки и утилизации аккумуляторов, цель которых - предотвратить появление определенных опасных веществ и улучшить экологический показатель всех операторов аккумуляторной батареи и цепочки поставок. Инструкции для пользователей по разборке, повторному использованию и утилизации использованных батарей Чтобы извлечь аккумулятор из устройства или пульта дистанционного управления, следуйте		предназначенные батареи. Символ, указывающий на то, что все батареи и аккумуляторы «собираются отдельно», должен быть мусорным ведром на колесах, как показано на рисунке ниже.  Для содержания ртути более 0,0005%, содержания кадмия более 0,002%. Батареи, аккумуляторы и кнопки с содержанием ртути более 0,004% должны иметь химический знак металла: Hg, Cd или Pb соответственно. Обратите внимание на следующие символы: 		ВНИМАНИЕ - Оптимизация температуры хранения изделия должна составлять от -20 до 70 ° C. - Установка устройства должна осуществляться в соответствии с инструкциями производителя. Не используйте устройство в условиях повышенной влажности. - Регистратор видеонаблюдения должен быть установлен в соответствии с инструкциями производителя. Не используйте регистратор видеонаблюдения в условиях повышенной влажности. - Автомобильный магнитолный усилитель должен быть установлен в соответствии с инструкциями производителя. Не используйте магнитолный усилитель в условиях повышенной влажности. Не пытайтесь самостоятельно осуществлять ремонт или разбирать устройство. Ремонт должен выполняться только квалифицированными специалистами. Не пытайтесь использовать устройство в условиях повышенной влажности.		- Непытайтесь самостоятельно осуществлять ремонт или разбирать устройство. Ремонт должен выполняться только квалифицированными специалистами. Не пытайтесь использовать устройство в условиях повышенной влажности. - Установка устройства должна осуществляться в соответствии с инструкциями производителя. Не используйте устройство в условиях повышенной влажности. - Регистратор видеонаблюдения должен быть установлен в соответствии с инструкциями производителя. Не используйте регистратор видеонаблюдения в условиях повышенной влажности. - Автомобильный магнитолный усилитель должен быть установлен в соответствии с инструкциями производителя. Не используйте магнитолный усилитель в условиях повышенной влажности.		Uwaga dotycząca dyrektywy WEEE Prawo europejskie, które weszło w życie 14.02.2014. Dyrektywa w sprawie zużytego sprzętu elektrycznego i elektronicznego (WEEE). Wprowadzono duże zmiany w użyciu sprzętu elektrycznego, która wygasła. Pierwszym celem dyrektywy jest zapobieganie WEEE, a także poprawa ponownego wykorzystania, recyklingu i innych form odzysku takich odpadów w celu zmniejszenia emisji gazów szkodliwych. Znak WEEE na produkcie lub jego opakowaniu wskazuje na recykling i użycie elektrycznego i elektronicznego z koszmami na śmieci z widkami widowymi, jak pokazano poniżej.  Tęgo produktu nie wolno użytkować ani wyrzucać razem z innymi odpadami domowymi. Jesteś odpowiedzialny za użycie wszelkich odpadów elektrycznych lub elektronicznych, umieszczając ich w wyznaczonych punktach zbiórki i recyklingu odpadów niebezpiecznych. Segregowana zbiórka i właściwy		Do produktów zawierających baterie Dyrektywa Unii Europejskiej dotycząca baterii 2013/56 / UE Nowa dyrektywa 2013/56 / UE w sprawie baterii i akumulatorów zastępuje dyrektywę, która weszła w życie 10/7/2013. Niniejsza dyrektywa dotyczy wszystkich typów baterii i akumulatorów (AA, AAA, guzików, baterii kwasowo-ołowiowych i akumulatorów), w tym baterii wbudowanych w urządzenia elektryczne inne niż narzędzia warsztatowe, medyczne i elektroniczne. Ostrzeżenie: Jeśli bateria zostanie nieprawidłowo wymieniona, może wystąpić zagrożenie wybuchem. Aby zmniejszyć ryzyko pożaru lub porażenia, nie należy rozmontowywać, drukać, przekładywać, krótkotrwale podłączać zewnętrznych, wystawiać na działanie temperatur powyżej 60 ° C (140 ° F) ani wrzucać do W ogniu lub wodzie. Wymieniać tylko na odpowiednie baterie. Symbol wskazujący, że wszystkie baterie i akumulatory są „zbierane oddzielnie”, powinien być koszem na śmieci z widkami widowymi, jak pokazano na poniższym rysunku.  Instrukcje dla użytkowników dotyczące demontażu, ponownego użycia i użycia zużytych baterii Aby wyjąć baterię z urządzenia lub pilota, postępuj zgodnie z procedurą instalacji baterii opisaną w instrukcji obsługi. W przypadku produktów z wbudowanymi bateriami na cały okres użytkowania użytkownicy mogą nie być w stanie ich wyjąć. W takim przypadku centrum recyklingu lub recyklingu.		UWAGA - Zakres optymalnej temperatury pracy urządzenia to temperatura od -20°C do 70°C. - Aby uzyskać najlepszy widok z kamery, należy ją zainstalować w pobliżu lusterka wstecznego. NIE instalować kamery w miejscu, w którym będzie przesłaniać pole widzenia kierowcy.			
DDPAI		设计人员: 曾丽娟		产品经理: 陈奕晖		包装类型: 认证书		材质: 105g 双铜纸		工艺: 油墨印刷					
		复查人员: 罗琴		项目经理: 韦河		比例尺寸: 1 : 1		尺寸: 70*120mm		颜色: 彩色					